

IDENTIFICATION

PRODUCT CODE: MA1DEC-08-DHKKb-D-D
PRODUCT NAME: RK8E DRIVE CONTROL TEST
DATE CREATED: JANUARY 1, 1974
MAINTAINER: DIAGNOSTIC GROUP
AUTHOR: JOHN VROBEL

COPYRIGHT (C) 1972, 1973, 1974, DIGITAL EQUIPMENT CORP., MAYNARD, MASS.

THIS SOFTWARE IS FURNISHED TO PURCHASER UNDER A LICENSE FOR USE ON A SINGLE COMPUTER SYSTEM AND CAN BE COPIED (WITH INCLUSION OF DEC'S COPYRIGHT NOTICE) ONLY FOR USE IN SUCH SYSTEM, EXCEPT AS MAY OTHERWISE BE PROVIDED IN WRITING BY DEC.

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL EQUIPMENT CORPORATION.

DEC ASSUMES NO RESPONSIBILITY FOR THE USE OR RELIABILITY OF ITS SOFTWARE ON EQUIPMENT WHICH IS NOT SUPPLIED BY DEC.

RK8EDRIV

PSW 02404

DISK TO RUN

CHECK WITHOUT BY TOGGING
AND LEAVE REF

ONLY 2 TOP UNIT LIGHTS SHOULD
BE ON

LSW 0200

S MODE

I/O PRESET

START LS 00 45 min



TABLE OF CONTENTS

1.	ABSTRACT
2.	REQUIREMENTS
2.1	HARDWARE
2.2	STORAGE
3.	PRELIMINARY PROGRAMS
4.	SWITCH REGISTER SETTINGS
5.	OPERATOR AND/OR PROGRAM ACTION
5.1	STANDARD TEST PROCEDURE
5.2	RK05 DRIVE CARTRIDGE MOUNTING PROCEDURE
5.3	DRIVE CONTROL TEST (SINGLE DRIVE TESTING)
5.4	DRIVE CONTROL TEST (MULTI DRIVE TESTING)
5.5	CHECK WRITE PROTECT (MANUAL)
5.6	CHECK WRITE PROTECT (PROGRAM CONTROL)
5.7	MANUAL FUNCTIONS (FOR TROUBLE SHOOTING ONLY)
5.8	CHANGE PROGRAM IOT CODES
5.9	SEEK FROM SWITCHES (FOR RK05 ALIGNMENT)
6.	ERRORS
6.1	USEFUL ERROR INFORMATION
6.2	NON-RECOVERABLE ERROR HALTS
6.3	RECOVERABLE ERROR HALT
6.4	ERROR TYPEOUTS
6.5	SCOPE LOOPS
6.6	TYPICAL ERROR TYPEOUTS
7.	RESERVICTIONS
8.	TROUBLE SHOOTING INFORMATION
9.	PROGRAM DESCRIPTION
10.	PROGRAM LISTING

1. ABSTRACT

THE RK8E DRIVE CONTROL TEST IS DESIGNED FOR THE PURPOSE OF CHECKOUT OF THE RK8E DISK CONTROL LOGIC REQUIRING THE USE OF THE DISK DRIVE.

IN GENERAL, THE TEST IS AN INSTRUCTION TEST TO VERIFY BASIC OPERATION OF THE SEEK ONLY, RESTORE, WRITE DATA, READ DATA, WRITE ALL, AND READ ALL FUNCTIONS WITH ALL DRIVES ON THE CONTROL. SIMPLE COMPLEMENT DATA PATTERNS OF 2525 + 5252, 5252 + 2525, AND 0000 + 7777 ARE USED TO VERIFY ADDRESSING AND DATA TRANSFERS TO AND FROM EACH INDIVIDUAL DRIVE.

A MANUAL INTERVENTION TEST IS ALSO INCLUDED (SEE SECTION 5.7), TO ALLOW THE OPERATOR TO SELECT DATA PATTERNS AND COMMAND REGISTER FUNCTIONS VIA THE SWITCH REGISTER.

CONSIDERING NO ERROR CONDITIONS, THE DRIVES THAT HAVE RUN THIS TEST ARE FORMATTED, IF THE PROGRAM WAS STOPPED AT END OF PROGRAM PASS COMPLETION BY SWR9s1.

2. REQUIREMENTS

2.1 HARDWARE

A. PDP-8/E, 8/F, OR 8/M COMPUTER OR OTHER FAMILY OF 8 COMPATIBLE COMPUTER WITH NECESSARY DW8E BUS ADAPTER.

B. AT LEAST 4K OF READ/WRITE MEMORY

C. ASR-33 TELETYPE OR EQUIVALENT

D. RK8E DISK CONTROL

E. RK05 DISK DRIVE(S)

2.2 STORAGE

THE PROGRAM OCCUPIES OR UTILIZES LOCATION 0000 TO LOCATION 7400 OF THE CURRENT FIELD. IF THE CURRENT FIELD IS AN EXTENDED MEMORY FIELD, LOCATIONS 0000 TO 0003 OF FIELD 0, WILL BE USED FOR PROGRAM INTERRUPT SERVICE.

3. PRELIMINARY PROGRAMS

ALL BASIC AND EXTENDED MEMORY DIAGNOSTICS AND THE RK8E DISKLESS CONTROL TEST SHOULD BE RUN PRIOR TO THIS TEST.

1. SWITCH REGISTER SETTINGS

SWR0#1 SCOPE LOOP ON ERROR. AFTER AN ERROR
HALT AT LOCATION "ERHLT9" RAISING THIS
SWITCH AND PRESSING KEY CONTINUE
WILL RESULT IN A SCOPE LOOP ON THE
CURRENT FAILING TEST IF THE TEST CONTINUES
TO FAIL. THE ERROR TIMEOUT AND THE
ERROR HALT AT LOCATION "ERHLT9" WILL
BE INHIBITED. THE TTY BELL WILL RING
INDICATING AN ERROR IF SWR2#0.

SWR1#1 SCOPE LOOP ON CURRENT NON-FAILING TEST.
RAISING THIS SWITCH CAUSES THE PROGRAM
TO LOOP ON THE CURRENT TEST IF THE TEST
IS WORKING CORRECTLY. MAY BE USED IN
CONJUNCTION WITH SWR0#1 FOR INTERMITTENT
PROBLEMS.

SWR2#1 INHIBIT BELL ON SCOPE LOOP. WHEN IN A
SCOPE LOOP DUE TO SWR0#1, RAISING THIS
SWITCH INHIBITS THE SCOPE LOOP ERROR
BELL.

SWR3#1 TEST ON CURRENT DRIVE.
UPON INITIAL START OF PROGRAM, WHEN
"SINGLE DRIVE TESTING", RAISING THIS
SWITCH INDICATES TO THE PROGRAM TO
TEST THE DISK DRIVE IN SWR10-11. WHEN
RUNNING THE PROGRAM AND "MULTI-DRIVE
TESTING", RAISING THIS SWITCH INDICATES
TO THE PROGRAM TO CONTINUE TO TEST THE
CURRENT DRIVE UNDER TEST.

SWR4#1 STOP PROGRAM OR HALT SWITCH. RAISING THIS
SWITCH WILL RESULT IN A PROGRAM STOP
UPON COMPLETION OF THE NEXT NON-FAILING
TEST. IF POSSIBLE, THIS SWITCH SHOULD
ALWAYS BE USED TO STOP THE PROGRAM.

SWR5#1 INHIBIT THE RECOVERABLE ERROR HALT AFTER
A RECOVERABLE ERROR TIMEOUT. AFTER AN
ERROR HALT AT LOCATION "ERHLT9", RAISING
THIS SWITCH AND PRESSING KEY CONTINUE
WILL INHIBIT ALL FUTURE RECOVERABLE ERROR
HALTS. IF SWR1#0 THE PROGRAM WILL PROCEED TO
NEXT TEST AFTER EACH ERROR TIMEOUT. IF SWR1#1
THE PROGRAM WILL PROCEED BACK TO THE SAME
OR CURRENT FAILING TEST.

(4, CONT'D.)

PAGE 3

SWR6=1 RECALIBRATE IN SCOPE LOOPS, RAISING THIS SWITCH WILL RESULT IN A DISK RECALIBRATION WHEN IN A SCOPE LOOP DUE TO SWR0=1, SWR1=1, OR WHEN SWR5=1.

SWR7=1 PROGRAM WAIT LOOP FOR DISK IN SCOPE LOOPS. RAISING THIS SWITCH WILL RESULT IN A PROGRAM WAIT LOOP FOR APPROX. 500 MS WHEN IN A SCOPE LOOP DUE TO SWR0=1, SWR1=1, OR WHEN SWR5=1. IN SOME CASES, THIS MAY BE USEFUL FOR WAITING FOR THE DISK MOVEMENT TO COMPLETE IF CONTROL OR DRIVE ERRORS OCCUR, BEFORE REPEATING THE TEST AGAIN. IN SOME CASES, FAILURE TO WAIT, MAY CAUSE ADDITIONAL ERRORS.

SWR8=1 GET ALL REGISTERS AFTER THE RECOVERABLE ERROR HALT "ERHLT9". AFTER AN ERROR HALT AT LOCATION "ERHLT9", RAISING THIS SWITCH AND PRESSING KEY CONTINUE RESULTS IN AN ERROR TYPEOUT OF THE ACTUAL CONTENTS OF THE CRC, STATUS, COMMAND, LOWER DATA, AND SURFACE AND SECTOR REGISTERS.

SWR9=1 PROGRAM HALT OR STOP AT END OF PROGRAM PASS COMPLETION.

SWR10=11 DISK DRIVE(S) TO TEST, IN MULTI-DRIVE TESTING, INDICATES TO THE PROGRAM THE ACTUAL AMOUNT OF NON-EXISTING DRIVES AND THE AMOUNT OF DRIVES NUMBERED SEQUENTIALLY FROM DISK 0 TO TEST. IN SINGLE DRIVE TESTING, UPON INITIAL START OF PROGRAM, AND IF SWR3=1, INDICATES TO THE PROGRAM THE DRIVE TO TEST.

5. OPERATOR AND/OR PROGRAM ACTION

5.1 STANDARD TEST PROCEDURE

- A. START AS SPECIFIED THROUGH OUT THIS DOCUMENTATION IS KEY CLEAR AND THEN KEY CONTINUE ON PDP8/E, PDP8/M, AND PDP8/F COMPUTERS.
- B. LOAD THE PROGRAM INTO ANY R/W MEMORY BANK USING THE STANDARD BINARY LOADER TECHNIQUE.
- C. IF IT IS DESIRED TO CHANGE THE IOT CODES WITHIN THE PROGRAM, FOLLOW THE PROCEDURE IN SECTION 5.8.
- D. RUN THE DRIVE CONTROL TEST WITH ALL DRIVES ON THE DISK SYSTEM BY USING THE SINGLE OR MULTI DRIVE TESTING METHOD, SECTION 5.3 OR SECTION 5.4, RESPECTIVELY.
- E. THE PROGRAM EXECUTION TIME IS APROX. 30 MINUTES PER DISK DRIVE.
- F. RUN THE WRITE PROTECT CHECK TESTS ON ALL DRIVES ON THE DISK SYSTEM BY FOLLOWING THE PROCEDURES IN SECTIONS 5.5 AND 5.6.
- G. MANUAL FUNCTIONS, SECTION 5.7, MAY BE USED FOR TROUBLE SHOOTING, IF DESIRED.
- H. SEEK FROM SWITCHES, SECTION 5.9, MAY BE USED FOR TROUBLE SHOOTING, IF DESIRED.
- I. IF THE PROGRAM WAS STOPPED BY SW4=1 OR BY "ERHLT9", ADDRESS 0205 CAN BE USED TO RESTART THE PROGRAM AT THE LAST SUBTEST EXECUTED. (NOTE: WHICH YOUR SWITCH SETTINGS.)

5.2 PKOS DRIVE CARTRIDGE MOUNTING PROCEDURE

THE FOLLOWING IS THE CORRECT CARTRIDGE MOUNTING PROCEDURE FOR THE PKOS DISK DRIVE. ANY DEVIATION ENCOUNTERED DURING THIS PROCEDURE WILL BE CONSIDERED AS AN ERROR CONDITION.

- A. SET SWITCH LABELED "RUN/LOAD" TO THE "LOAD" POSITION.
- B. TURN AC POWER TO DISK DRIVE ON.
- C. VERIFY THAT LIGHT LABELED "PWR" IS ON.
- D. WAIT FOR LIGHT LABELED "LOAD" TO COME ON.
- E. VERIFY THAT LIGHTS LABELED "RDY", "ON CYL", "FAULT", "WT", AND "RD" ARE OFF.
- F. OPEN ACCESS DOOR.
- G. INSERT CARTRIDGE.
- H. CLOSE ACCESS DOOR.
- I. SET SWITCH LABELED "RUN/LOAD" TO THE "RUN" POSITION.
- J. WAIT FOR THE LIGHTS LABELED "RDY" AND "ON CYL" TO COME ON.
- K. TOGGLE SWITCH LABELED "WT PROT" AND VERIFY THAT THE LIGHT LABELED "WT PROT" GOES ON AND OFF.
- L. TOGGLE SWITCH LABELED "WT PROT" UNTIL THE LIGHT LABELED "WT PROT" GOES OFF.
- M. VERIFY THAT LIGHTS LABELED "FAULT", "WT", "RD", AND "LOAD" ARE OFF.

5.3 DRIVE CONTROL TEST (SINGLE DRIVE TESTING)

- A. MAKE READY THE DISK DRIVE TO BE TESTED USING THE PKOS DRIVE CARTRIDGE MOUNTING PROCEDURE SECTION 5.2.
- B. SET SWITCH LABELED "RUN/LOAD" TO THE "LOAD" POSITION ON ALL DRIVES NOT BEING TESTED.
- C. VERIFY THAT AC POWER TO ALL DRIVES IS ON.

- D. SET THE SWITCH REGISTER TO 0200 AND PRESS LOAD ADDRESS.
 - E. SET THE SWITCH REGISTER TO 0000.
 - F. SET SWR3#1 TO INDICATE "SINGLE DRIVE TESTING".
 - G. SET SWR10#11 TO THE DISK DRIVE TO BE TESTED AND START THE COMPUTER RUNNING.
 - H. THE PROGRAM SHOULD PRINT THE FOLLOWING MESSAGE AT THE COMPLETION OF EACH PASS.
"RK6E DRIVE CONTROL TEST PASS COMPLETE"
 - I. ALWAYS USE SWR4#1 FOR STOPPING THE TEST.
 - J. IF IT IS DESIRED TO HAVE THE PROGRAM HALT OR STOP AT END OF PROGRAM PASS COMPLETION SET SWR9#1.
 - K. ANY HALTS OR TYPEOUTS OTHER THAN THE PASS COMPLETE TYPEOUT OR END OF TEST HALT MENTIONED ABOVE WILL BE CONSIDERED AN ERROR CONDITION. IN ALL CASES ACCESS "ERRORS" SECTION 6 IN THIS DOCUMENTATION.
 - L. FOR ABSOLUTE LOCATIONS OF ALL KNOWN HALTS ACCESS PAGE 1 OF THE PROGRAM LISTING.
- 5.4 DRIVE CONTROL TEST (MULTI-DRIVE TESTING)

- A. MAKE READY ALL DISK DRIVES NUMBERED SEQUENTIALLY FROM DRIVE 0 TO BE TESTED USING THE RK05 DRIVE CARTRIDGE MOUNTING PROCEDURE SECTION 5.2.
 - B. SET SWITCH LABELED "RUN/LOAD" TO THE "LOAD" POSITION ON ALL DISK DRIVES NOT BEING TESTED.

(5.4 CONT'D.)

- C. VERIFY THAT AC POWER TO ALL DRIVES IS ON.
- D. SET THE SWITCH REGISTER TO 0200 AND PRESS LOAD ADDRESS.
- E. SET THE SWITCH REGISTER TO 0000.

F. SET SWP10-11 TO THE AMOUNT OF EXTRA DISK DRIVES NUMBERED SEQUENTIALLY FROM DISK 0 TO BE TESTED AND START THE COMPUTER RUNNING.

```

SWR10-11#1    2 DISK SYSTEM
SWP10-11#2    3 DISK SYSTEM
SWR10-11#3    4 DISK SYSTEM

```

G. THE PROGRAM SHOULD PRINT THE FOLLOWING MESSAGE AT THE COMPLETION OF EACH PASS.

```
"RK6E DRIVE CONTROL TEST PASS COMPLETE"
```

H. ALWAYS USE SWR4#1 FOR STOPPING THE TEST.

I. IF IT IS DESIRED TO HAVE THE PROGRAM HALT OR STOP AT THE END OF PROGRAM PASS COMPLETION SET SWR9#1.

J. ANY HALTS OR TYPEOUTS OTHER THAN THE PASS COMPLETE TYPEOUT AND THE END OF TEST HALT MENTIONED ABOVE WILL BE CONSIDERED AN ERROR CONDITION. IN ALL CASES ACCESS "ERRORS" SECTION 6 IN THIS DOCUMENTATION.

K. FOR ABSOLUTE LOCATIONS OF ALL KNOWN HALTS ACCESS PAGE 1 OF THE PROGRAM LISTING.

5.5 CHECK WRITE PROTECT (MANUAL)

```

*****

```

- A. RUN THE REGULAR DRIVE CONTROL TEST WITH ALL DRIVES ON THE CONTROL USING THE SINGLE OR MULTI DRIVE TESTING METHOD, BEFORE RUNNING THIS "WRITE PROTECT" PORTION.
- B. MAKE READY A DRIVE TO TEST USING THE RK05 DRIVE CARTRIDGE MOUNTING PROCEDURE SECTION 5.2.
- C. SET SWITCH LABELED "RUN/LOAD" TO THE "LOAD" POSITION ON ALL OTHER DRIVES.
- D. VERIFY THAT AC POWER TO ALL DRIVES IS ON.
- E. VERIFY THAT THE LIGHT LABELED "WT PROT" IS "OFF" ON THE CURRENT DRIVE UNDER TEST.

(5.5 CONT'D)

- F. SET THE SWITCH REGISTER TO 0203 AND PRESS LOAD ADDRESS.
- G. SET THE SWITCH REGISTER TO 0000.
- H. SET SWR10-11 TO THE CURRENT DRIVE NUMBER UNDER TEST.
- I. PRESS START AND THE COMPUTER SHOULD HALT AT LOCATION "MPRLT1". *4122*
- J. PRESS SWITCH LABELED "WT PROT" TO TURN "WRITE PROTECT" AND THE LIGHT LABELED "WT PROT" ON.
- K. PRESS KEY CONTINUE AND THE COMPUTER SHOULD HALT AT LOCATION "MPRLT2" INDICATING A SUCCESSFUL TEST. *4162*
- L. FOR ALL KNOWN HALTS IN THIS PROGRAM, ACCESS PAGE 1 OF THE PROGRAM LISTING.
- M. IF ANY ERRORS ARE ENCOUNTERED OR IF IT IS DESIRED TO TRY THE TEST AGAIN, REPEAT STEPS A-K.
- N. FOR POSSIBLE ERROR TIMEOUTS ACCESS SECTION 6 IN THIS DOCUMENTATION, (NOTE! NO SCOPE LOOPS ARE AVAILABLE FOR THIS TEST.)
- O. THE "CHECK WRITE PROTECT PROCEDURE" AS DESCRIBED ABOVE SHOULD BE RUN TWICE WITH ALL DRIVES ON THE CONTROL.

5.6 CHECK WRITE PROTECT (PROGRAM CONTROL)

- A. RUN THE REGULAR DRIVE CONTROL TEST WITH ALL DRIVES ON THE CONTROL USING THE SINGLE OR MULTI DRIVE TESTING METHOD, BEFORE RUNNING THIS "WRITE PROTECT" PORTION.
- B. MAKE READY A DRIVE TO TEST USING THE FKOS DRIVE CARTRIDGE MOUNTING PROCEDURE SECTION 5.2.
- C. SET SWITCH LABELED "RUN/LOAD" TO THE "LOAD" POSITION ON ALL OTHER DRIVES.
- D. VERIFY THAT AC POWER TO ALL DRIVES IS ON.
- E. VERIFY THAT THE LIGHT LABELED "WT PROT" IS "OFF" ON THE CURRENT DRIVE UNDER TEST.
- F. SET THE SWITCH REGISTER TO 0204 AND PRESS LOAD ADDRESS.
- G. SET THE SWITCH REGISTER TO 0000.
- H. SET SWR10-11 TO THE CURRENT DRIVE NUMBER UNDER TEST.

(5.6 CONT'D)

- I. PRESS START AND THE COMPUTER SHOULD HALT AT LOCATION "APULTI" INDICATING A SUCCESSFUL TEST.
4776
- J. VERIFY THAT THE WRITE PROTECT LIGHT LABELED "WI PROT" IS ON, ON THE CURRENT DRIVE.
- K. FOR ALL KNOWN HALTS IN THIS PROGRAM, ACCESS PAGE 1 OF THE PROGRAM LISTING.
- L. IF ANY ERRORS ARE ENCOUNTERED OR IF IT IS DESIRED TO TRY THE TEST AGAIN, REPEAT STEPS A-J.
- M. FOR POSSIBLE ERROR TYPEDOUTS ACCESS SECTION 6 IN THIS DOCUMENTATION. (NOTE! NO SCOPE LOOPS ARE AVAILABLE FOR THIS TEST.)
- N. THE "CHECK WRITE PROTECT PROCEDURE" AS DESCRIBED ABOVE SHOULD BE RUN TWICE WITH ALL DRIVES ON THE CONTROL.

5.7 MANUAL FUNCTIONS (FOR TROUBLE SHOOTING ONLY)

THE MANUAL FUNCTIONS ENABLES THE OPERATOR TO SELECT FUNCTIONS, DISK ADDRESS, AND DATA PATTERNS VIA THE SWITCH REGISTER. THIS IS NOT PART OF THE REGULAR TEST AND SHOULD ONLY BE USED FOR TROUBLE SHOOTING IF DESIRED.

- A. SET THE SWITCH REGISTER TO 0201 AND PRESS LOAD ADDRESS.
- B. SET THE SWITCH REGISTER TO THE DESIRED FUNCTION TO BE LOADED INTO THE COMMAND REGISTER. (SEE SECTION 8.) (NOTE! THE EXTENDED MEMORY BITS 6-9, THE ENABLE INTERRUPT BIT 3, AND THE ENABLE SET DUMP BIT ON SEEK COMPLETE BIT 4, ARE NOT RECOGNIZED. THIS MANUAL PORTION IS ONLY FLAG DRIVEN AND ALL DATA TRANSFERS ARE TO THE CURRENT FIELD.)
- C. PRESS START AND THE COMPUTER SHOULD HALT.
- D. SET THE SWITCH REGISTER TO THE DESIRED DISK ADDRESS TO BE LOADED INTO THE CYLINDER, SURFACE, AND SECTION REGISTER. (SEE SECTION 8.)
- E. PRESS START AND THE COMPUTER SHOULD HALT.
- F. SET THE SWITCH REGISTER TO THE COMPLEMENT TYPE DATA PATTERN TO BE WRITTEN ON OR READ FROM THE DISK DEPENDING ON THE FUNCTION PREVIOUSLY LOADED INTO THE COMMAND REGISTER. (NOTE! A SETTING OF 0000 WILL RESULT IN A COMPLEMENT DATA PATTERN OF 0000 + 7777. A SETTING OF 2525 WILL RESULT IN A COMPLEMENT DATA PATTERN OF 2525 + 5252.)
- G. PRESS START AND THE COMPUTER SHOULD HALT.

(5.7 CONT'D)

- H. SET THE SWITCH REGISTER TO 0000, PRESS START, AND THE FUNCTION SELECTED WILL BE EXECUTED.
- I. IF POSSIBLE, ALWAYS USE SWR4=1 FOR STOPPING PROGRAM.
- J. IN CASE OF ERRORS OR DESIRED LOOPS, USE THE REGULAR SWITCH REGISTER SETTINGS (SECTION 4.)
- K. IF A WRITE ALL OR THE WRITE DATA FUNCTION WAS SELECTED, THE DATA PATTERN SELECTED WILL BE WRITTEN ON THE DISK ADDRESS SELECTED.
- L. IF A READ ALL OR READ DATA FUNCTION WAS SELECTED, THE DATA WILL BE READ OFF THE DISK ADDRESS SELECTED AND COMPARED AGAINST THE DATA PATTERN SELECTED.
- M. IF A SEEK ONLY FUNCTION WAS SELECTED, A SEEK ONLY WILL BE EXECUTED TO THE DISK ADDRESS SELECTED.
- N. IF A WRITE LOCK FUNCTION WAS THE SELECTED THE DISK DRIVE SELECTED WILL BE WRITE LOCKED.

5.8

CHANGE PROGRAM DEVICE IOT CODES

THE PROGRAM NORMALLY RECOGNIZES DEVICE IOT CODE X74X. TO CHANGE THE DEVICE IOT CODES WITHIN THE PROGRAM:

- A. SET THE SWITCH REGISTER TO 0202 AND PRESS LOAD ADDRESS.
- B. SET THE SWITCH REGISTER TO 0000, SET SWITCH REGISTER BITS 3-8 TO THE DESIRED DEVICE IOT CODE, AND PRESS START.
- C. THE PROGRAM WILL CHANGE THE DEVICE IOT CODES WITHIN THE PROGRAM AND THEN HALT.

- D. THE REGULAR TESTS CAN THEN BE RUN (SEE SECTIONS 5.3, 5.4, 5.5, OR 5.6).

5.9

SEEK FROM SWITCHES (FOR RK05 ALIGNMENT)

THE FOLLOWING SUBTEST WAS REQUESTED BY FIELD SERVICE TO AID IN RK05 ALIGNMENT. THE PROGRAM WILL SEEK ONLY BETWEEN ADDRESSES FROM SWITCH REGISTER.

- A. SET THE SWITCH REGISTER TO 4000 AND PRESS LOAD ADDRESS.
- B. SET THE SWITCH REGISTER TO 0000.
- C. SET SWR9-11 TO THE DRIVE NUMBER AND EXTENDED CYLINDER BIT OF THE FIRST SEEK ADDRESS (BITS 9-10 TO DRIVE NUMBER AND BIT 11 TO EXTENDED CYLINDER).

(5.9 CONT'D)

- D. SET SW0-7 TO THE REMAINDER OF THE CYLINDER BITS AND THE SURFACE OF THE FIRST SEEK ADDRESS.
- E. PRESS START AND THE COMPUTER SHOULD HALT.
- F. SET THE SWITCH REGISTER TO 0000.
- G. SET SW9-11 TO THE DRIVE NUMBER AND EXTENDED CYLINDER BIT OF THE SECOND SEEK ADDRESS (BITS 9-10 TO THE DRIVE NUMBER AND BIT 11 TO THE EXTENDED CYLINDER).
- H. SET SW0-7 TO THE CYLINDER BITS AND SURFACE OF THE SECOND SEEK ADDRESS.
- I. PRESS START AND THE DRIVE SHOULD SEEK BETWEEN THE ADDRESSES SPECIFIED BY THE SWITCH REGISTER.
- J. THE SECOND SEEK ADDRESS CAN BE CHANGED AT ANY TIME BY SIMPLY CHANGING THE SWITCH REGISTER TO SELECT A NEW ADDRESS.
- K. CARE SHOULD BE TAKEN TO NOT SELECT A NON-EXISTENT DISK DRIVE OR NON-EXISTENT CYLINDER.
- L. NO ERROR CHECKING IS DONE DURING THIS SUBTEST.
- M. IT IS POSSIBLE TO SEEK TO A CONSTANT ADDRESS BY MAKING THE FIRST AND SECOND ADDRESS EQUAL.

6. ERRORS

6.1 USEFUL ERROR INFORMATION

IN THE REGULAR TEST, THE DISK SKIP IOT IS FIRST CHECKED AND TIMED-OUT USING AN "ISZ" TIME LOOP. IF THE SKIP IOT FAILS, AN ERROR TYPEOUT AND ERROR HALT SHOULD OCCUR, ONCE PROVEN TO WORK, THE IOT IS NOT TIMED-OUT. THE PROGRAM MAY HANG-UP IF THE SKIP IOT FAILS INTERMITTENTLY. (NOTE: THE MANUAL FUNCTIONS, SECTION 5.7, ALWAYS TIMES OUT THE SKIP IOT TO PREVENT HANGING UP.

ALL ERRORS FOUND WHEN RUNNING THIS TEST SHOULD BE CORRECTED BEFORE PROCEEDING ON IN THE TEST.

(6.1 CONT'D)

WHEN AN OPERATOR ENCOUNTERS AN ERROR WHEN RUNNING THIS TEST HE SHOULD, IN ALL CASES, READ THE ERROR TYPEOUT INFORMATION, NOTE THE LOCATION OF THE FAILURE, READ ALL THE INFORMATION UNDER ERRORS IN THIS DOCUMENTATION, AND THEN ACCESS THE PROGRAM LISTING FOR FURTHER INFORMATION.

THE ABSOLUTE LOCATION OF ALL KNOWN HALTS CAN BE FOUND ON PAGE 1 OF THE PROGRAM.

A COMPLEMENT TYPE DATA PATTERN (I.E. 2525 + 5252, 5252 + 2525, OR 0000 + 7777) IS ALWAYS USED IN THIS TEST WHEN DATA IS WRITTEN AND THEN CHECKED. IN SOME CASES, ALL 0'S IS USED IN CHECKING CRC AND STATUS REGISTERS, HOWEVER, THE DATA IS NOT CHECKED.

THE PROGRAM USES THE SAME PROGRAM BUFFER FOR WRITING AND READING DATA, THE BUFFER IS SETUP BEFORE A WRITE FUNCTION AND CLEARED BEFORE THE DATA IS READ AND CHECKED. THE BUFFER OCCUPIES THE CURRENT FIELD FROM THE END OF THE PROGRAM +400 LOCATIONS.

BEFORE DATA IS WRITTEN ON THE DISK, THE FIRST TWO WORDS OF THE BUFFER ARE SET TO THE ABSOLUTE DISK ADDRESS. THE FIRST WORD OF THE BUFFER (BITS 9-11) IS SET TO THE DRIVE NUMBER AND THE EXTENDED CYLINDER BIT, THE SECOND WORD TO THE 12 REMAINDER CYLINDER, SURFACE, AND SECTOR BITS. ALSO THE BUFFER +1 IS SET TO THE DATA WORD OF "1234". AFTER THE WRITE THEN READ, THE WORDS ARE CHECKED FOR CORRECT VALUES, INDICATING THAT THE INFORMATION WAS WRITTEN ON AND READ FROM THE SAME PLACE ON THE DISK AND THAT THE DATA BREAK STOPPED CORRECTLY. WHEN AN ERROR EXISTS WITH THE WORDS AS STATED PREVIOUSLY, THE OPERATOR SHOULD REALIZE THAT THE PROBLEM IS MOST LIKELY ADDRESSING AND SOMETIMES DATA ERRORS.

WHEN DATA IS BEING READ OFF THE DISK AND A CRC ERROR OCCURS THE PROGRAM WILL THEN CHECK THE DATA READ FOR DATA ERRORS. IF NO DATA ERRORS EXIST THE CRC ERROR FOUND WILL BE REPORTED AS A STATUS REGISTER ERROR. IF DATA ERRORS ARE FOUND THE DATA ERRORS WILL BE REPORTED AS DISK DATA ERRORS AND THE CRC STATUS ERROR INDICATED IN THE "STI". (SEE SECTION 6.4 FOR ERROR HEADERS AND TYPEOUTS).

THE ABSOLUTE ADDRESS LOCATIONS OF THE DATA BUFFER CAN BE FOUND ON PAGE 1 OF THE PROGRAM LISTING.

6.2 NON-RECOVERABLE ERROR HALTS

NON-RECOVERABLE ERROR HALTS FOR WHICH THERE ARE NO
 TYPEOUTS OR SCOPE LOOPS ARE LISTED AND DEFINED AS FOLLOWS.

- ERHLT1 UNDEFINED INTERRUPT
- ERHLT2 SKIP TRAP FOR IOT "DCLR"
- ERHLT3 SKIP TRAP FOR IOT "DLAG"
- ERHLT4 SKIP TRAP FOR IOT "DLCA"
- ERHLT5 SKIP TRAP FOR IOT "DRSI"
- ERHLT6 SKIP TRAP FOR IOT "DLDC"
- ERHLT7 SKIP TRAP FOR IOT "DMAN"

6.3 RECOVERABLE ERROR HALT

ALL RECOVERABLE ERRORS, FOR WHICH THERE ARE SCOPE LOOPS
 AND ERROR TYPEOUTS, SHOULD RESULT IN AN ERROR HALT AT
 LOCATION "ERHLT9".

- ERHLT9 RECOVERABLE ERROR HALT. READ INFORMATION
 TYPEOUT ON TTY AND ACCESS PROGRAM
 LISTING AND DOCUMENTATION.

6.4 ERROR TYPEOUTS

WHEN A RECOVERABLE ERROR OCCURRES THE PROGRAM WILL
 PRINT AN "ERROR HEADER" WHICH WILL SPECIFY THE
 PARTICULAR REGISTER OR TYPE OF ERROR FOUND
 AT THE TIME OF THE FAILURE.

POSSIBLE "ERROR HEADERS" ARE AS FOLLOWS.

- STATUS REGISTER ERROR
- COMMAND REGISTER ERROR
- DISK ADDRESS REGISTER ERROR
- DISK DATA ERROR
- CRC REGISTER ERROR
- DATA REGISTER ERROR
- DISK SKIP ERROR
- DISK INTERRUPT ERROR

(6.4 CONT'D)

AFTER THE "ERROR HEADER" MENTIONED ABOVE IS TYPED, THE PROGRAM WILL PRINT THE FOLLOWING ERROR INFORMATION FOUND AT THE TIME OF THE FAILURE, PERTAINING TO THE FAILURE. POSSIBLE TYPEDOUTS ARE AS FOLLOWS.

- PCI PROGRAM LOCATION OF THE ACTUAL FAILURE.
- GDI REFERS TO THE DATA EXPECTED IN THE REGISTER OR TYPE OF TEST SPECIFIED IN THE "ERROR HEADER".
- CRI CONTENTS OF THE CRC REGISTER.
- STI CONTENTS OF THE STATUS REGISTER.
- DBI CONTENTS OF THE LOWER DATA REGISTER.
- CHI CONTENTS OF THE COMMAND REGISTER.
- DAI CONTENTS OF THE DISK ADDRESS REGISTER OR THE CYLINDER, SURFACE, AND SECTOR BITS.
- CAI CONTENTS OF THE INITIAL CURRENT ADDRESS
- ADI BREAK ADDRESS OF DATA BREAK IN COMPUTER.
- DTI DATA FOUND DURING DATA BREAK.

THE "GDI" INFORMATION TYPED OUT POINTS TO THE DATA EXPECTED IN THE REGISTER OR TYPE OF ERROR TYPED OUT IN THE "ERROR HEADER".

THE ERROR INFORMATION INDICATOR SUGGESTED BY THE "ERROR HEADER" (I.E. DAI FOR DISK ADDRESS ERROR, CHI FOR COMMAND REGISTER ERROR, CRI FOR CRC REGISTER ERROR, ETC.), IS THE ACTUAL CONTENTS OF THAT PARTICULAR REGISTER. ERROR INFORMATION OTHER THAN THAT SUGGESTED BY THE ERROR HEADER IS THE SOFTWARE VALUE LOADED INTO THAT REGISTER PRIOR TO THE FAILURE.

TO TYPE THE ACTUAL CONTENTS OF THE REGISTERS, SET SWR621 AFTER AN ERROR HALT AT LOCATION "ERHL19", AND PRESS KEY CONTINUE. THE CONTENTS OF THE CRC, STATUS, LOWER DATA, COMMAND, AND SURFACE AND SECTOR REGISTERS WILL THEN BE TYPED.

6.5 SCOPE LOOPS

THERE ARE SCOPE LOOPS AVAILABLE FOR ALL ERRORS RESULTING IN AN ERROR HALT AT LOCATION "ERHLT9".

TO ENTER SCOPE LOOP, INHIBIT ERROR TYPEOUT, AND INHIBIT ERROR HALT, AFTER AN ERROR HALT AT "ERHLT9", SET SWRO=1 TO INDICATE SCOPE LOOP AND PRESS KEY CONTINUE.

IF THE SCOPE LOOP IS WORKING CORRECTLY AND THE TEST IS STILL FAILING, THE TTY BELL SHOULD RING INDICATING AN ERROR, THEN SET SWR2=1 TO INHIBIT THE TTY ERROR BELL.

SWR1=1 MAY HAVE TO BE USED IN SCOPE LOOPS IN CONJUNCTION WITH SWRO=1, IF THE CURRENT TEST IS WORKING INTERMITTENTLY.

6.6 TYPICAL ERROR TYPEOUTS

THE FOLLOWING IS AN EXAMPLE OF AN "ERROR HEADER" AND TYPEOUT THAT COULD HAVE OCCURRED IF THE DISK SKIP IOT FAILED TO SKIP.

DISK SKIP ERROR
PC10267

THE FOLLOWING IS AN EXAMPLE OF AN "ERROR HEADER" AND ERROR TYPEOUT THAT COULD HAVE OCCURRED ON A DATA BREAK ERROR, (NOTE CRC IN THE STATUS INDICATOR "ST:").

DISK DATA ERROR
PC1161 GD15252 ST14010 CM11000 DA10001 CA17000 AD17010 DI15250

THE FOLLOWING IS A TYPICAL ERROR THAT COULD HAVE OCCURRED WHILE READING THE CRC REGISTER.

CRC REGISTER ERROR
PC12246 GD116047 CR116046 CM11000 DA17777

THE FOLLOWING IS AN EXAMPLE OF AN ERROR TYPEOUT THAT COULD HAVE OCCURRED IF THE STATUS REGISTER FAILED. (NOTE: IN THIS CASE THE OPERATOR INDICATED TO THE PROGRAM TO TYPE THE ACTUAL CONTENTS OF THE REGISTERS BY SETTING SWR8=1 AFTER THE ERROR HALT AT LOCATION "ERHLT9" AND PRESSING KEY CONTINUE).

STATUS REGISTER ERROR
PC11100 GD14000 ST12000 CM15002 DA10000
CR100000 ST12000 DB10000 CM15002 DA10000

7. RESTRICTIONS

ALL DISK DRIVES SHOULD BE SET TO THE LOAD POSITION THAT ARE NOT BEING TESTED.

ALL ERRORS SHOULD BE CORRECTED BEFORE PROCEEDING ON IN THE PROGRAM.

8. TROUBLE SHOOTING INFORMATION

IOT ---	FUNCTION -----
6741 DSKP	"SKIP" SKIP IF TRANSFER DONE FLAG OR ERROR FLAG IS SET.
6742 DCLR	"CLEAR" FUNCTION IS REGULATED BY AC BITS 10 AND 11. THE AC IS THEN CLEARED.
AC10 AC11 -----	
0 0	CLEAR THE AC AND STATUS REGISTER.
0 1	CLEAR THE AC, CONTROL, AND MAJOR REGISTERS. THIS INSTRUCTION WILL STOP THE CONTROL EVEN IF IT IS WRITING A HEADER. THIS IS THE ONLY INSTRUCTION THAT CLEARS MAINTENANCE MODE.
1 0	CLEAR AC, RECALIBRATE DISK DRIVE, AND CLEAR STATUS REGISTER.
6743 DLAG	"LOAD DISK ADDRESS AND GO" LOAD THE DISK CYLINDER, SURFACE, AND SECTOR FROM THE AC, CLEAR THE AC, AND DO THE COMMAND IN THE COMMAND REGISTER.

(8. CONT'D)

AC
--

0-6

7

8-11

6744 DLCA

AC
--

0-11

6745 DRST

AC
--

0

1

2

3

4

5

6

7

8

9

10

11

6746 DLDC

CYLINDER
SURFACE (1=UPPER) (0=LOWER)

SECTOR

"LOAD CURRENT ADDRESS" LOAD THE
CURRENT ADDRESS FROM AC. THE AC
IS THEN CLEARED.

CURRENT ADDRESS

"READ STATUS" CLEAR THE AC AND
READ THE CONTENTS OF THE STATUS
REGISTER INTO THE AC.

TRANSFER DONE
READY TO SEEK, READ, OR WRITE,
NOT USED
SEEK FAIL
DISK FILE READY
CONTROL BUSY ERROR
TIME OUT ERROR
WRITE LOCK ERROR
CRC ERROR
DATA RATE ERROR
DRIVE STATUS ERROR
CYLINDER ADDRESS ERROR

"LOAD COMMAND" LOAD THE COMMAND
REGISTER FROM AC. CLEAR THE AC,
AND CLEAR THE STATUS REGISTER.

(8. CONT'D)

AC		
--		
0-2=0	READ DATA	
0-2=1	READ ALL	
0-2=2	WRITE LOCK	
0-2=3	SEEK ONLY	
0-2=4	WRITE DATA	
0-2=5	WRITE ALL	
0-2=6	NOT USED	
0-2=7	NOT USED	
3	ENABLE INTERRUPT	
4	ENABLE SET TRANSFER DONE ON SEEK DONE	
5	HALF BLOCK 128 WORDS	
6	EXTENDED MEMORY ADDRESS	
7	EXTENDED MEMORY ADDRESS	
8	EXTENDED MEMORY ADDRESS	
9	UNIT SELECT	
10	UNIT SELECT	
11	EXTENDED CYLINDER ADDRESS	

6747 DMAN

"MAINTENANCE IOT" LOAD THE MAINTENANCE REGISTER FROM THE AC, THE FUNCTION IS REGULATED BY THE AC BITS. MAINTENANCE MODE CAN ONLY BE CLEARED BY DCUR "CLEAR CONTROL".

AC		
--		
0	ENTER MAINTENANCE MODE	
1	ENABLE SHIFT TO LOWER BUFFER	
2	AC BIT 10, CRC REGISTER, AND THE LOWER DATA BUFFER ARE CONNECTED AS A SHIFT REGISTER. AC BIT 10 DATA SHIFTS TO THE CRC, THE CRC SHIFTS TO THE LOWER DATA BUFFER.	
3	SHIFT COMMAND REGISTER TO THE LOWER DATA BUFFER.	
4	SHIFT THE SURFACE AND SECTOR REGISTER TO THE LOWER DATA BUFFER.	
5	SHIFT AC 10 DATA TO THE UPPER DATA BUFFER, THE UPPER BUFFER SHOULD SINK IN THE SILD WHEN FULL.	
6	ONE SINGLE CYCLE BREAK REQUEST. DIPECTION IS REGULATED BY FUNCTION IN THE COMMAND REGISTER.	
7	CLEAR AC THEN READ THE LOWER DATA BUFFER TO THE AC.	
8	NOT USED.	
9	NOT USED.	
10	USED AS DATA WITH OTHER BITS IN THE MAINTENANCE MODL.	
11	NOT USED	

9. PROGRAM DESCRIPTION

THE RK8E DRIVE CONTROL TEST VERIFIES BASIC FUNCTIONAL OPERATION OF THE RK8E CONTROL LOGIC WITH THE RK05 DISK DRIVE(S). THE PROGRAM IS COMPRISED OF MANY INDIVIDUAL SUBTESTS WHICH ARE AUTOMATICALLY RUN IN A SEQUENTIAL FLOW. ABOVE EACH SUBTEST, IN THE LISTING, IS A BRIEF DESCRIPTION OF EACH SUBTEST.

WHEN SINGLE DRIVE TESTING, ONE PASS THROUGH ALL SUBTESTS (TS10-TS145) RESULTS IN A PASS COMPLETION. WHEN MULTI-DRIVE TESTING, ONE PASS THROUGH ALL SUBTESTS (TS10-TS145) ON ALL DRIVES AND THE RUNNING OF THE OVERLAP SEEK TESTS(OVRLAP, GRONK, AND OVRRED) RESULTS IN A PASS COMPLETION.

CONSIDERING NO ERROR CONDITIONS, THE DRIVES THAT HAVE RUN THIS TEST ARE FORMATTED, IF THE PROGRAM WAS STOPPED AT END OF PROGRAM PASS COMPLETION BY SWR9=1.

10. PROGRAM LISTING

```

/
/PRK# DRIVE CONTROL TEST
/COPYRIGHT (C) 1972,1973,1974 DIGITAL EQUIP. CORP., MAYNARD, MASS.
/
/ALL KNOWN HALTS
/
0200 5217 ERHLT1 /UNDEFINED INTERRUPT
0201 5343 ERHLT2 /SKIP TRAP FOR DCLP
0202 5324 ERHLT3 /SKIP TRAP FOR DLAG
0203 5316 ERHLT4 /SKIP TRAP FOR DLCA
0204 5303 ERHLT5 /SKIP TRAP FOR DRST
0205 5332 ERHLT6 /SKIP TRAP FOR DLDC
0206 5347 ERHLT7 /SKIP TRAP FOR DMAN
0207 5142 ERHLT9 /THE RECOVERABLE ERROR HALT
0210 6410 STPHLF /PROGRAM STOP OR HALT FROM SWR4=1
0211 6555 CNMMLI /IOT CHANGE HALT
0212 4122 MPHLT1 /HALT FOR "CHECK WRITE PROTECT"
0213 4162 MPHLT2 /HALT FOR "CHECK WRITE PROTECT"
0214 4776 APHLT1 /HALT FOR "CHECK WRITE PROTECT"
0215 4072 ENDHLE /END OF TEST HALT FROM SWR9=1
0216 4002 WEDHLT /FROM ALIGNMENT SUBTEST
/
/BUFFER LOCATION INFORMATION
/
0217 7000 WRKBUF /START OF PROGRAM DATA BUFFER
0220 7377 ENDBUF /END OF PROGRAM DATA BUFFER
0221 7000 HTRK /DISK ADDRESS WORD IF BUFFER
0222 7001 LTRK /DISK ADDRESS WORD IN BUFFER
0223 7400 STPCHK /BUFFER +1 "BREAK STOP CHECK" "1234"
/
6741 DSKP=6741 /SKIP ON TRANSFER DONE OR ERROR
6742 DCLR=6742 /CLEAR DISK CONTROL LOGIC
6743 DLAG=6743 /LOAD ADDRESS AND GO
6744 DLCA=6744 /LOAD CURRENT ADDRESS
6745 DRST=6745 /READ STATUS REGISTER
6746 DLDC=6746 /LOAD COMMAND REGISTER
6747 DMAN=6747 /LOAD MAINTENANCE
/
4420 DSKOUT=JMS I XDDUT
4421 DSKIN=JMS I XDIN
4422 RANADD=JMS I XRNAD
4424 RECAL=JMS I XRESTR
4423 SEEK=JMS I XONLY
4425 DISKGO=JMS I XDISKG
4426 HATCHK=JMS I XHFCNK
4431 KILBUF=JMS I XKLBUF
4430 FILBUF=JMS I XFLBUF
4433 WATISZ=JMS I XWTSZ
4432 SKPAT=JMS I XSKPAT
4427 FIGURE=JMS I XFIGURE
4437 NERROR=JMS I XNERRO
4440 ERROR=JMS I XERRO
4441 IONWAT=JMS I XIONWT

```

```

4442 ACCMP1=JMS I XCOMP1
4443 ACCMP2=JMS I XCOMP2
4444 RDSSTAT=JMS I XNDST
4445 RDCND=JMS I XRDCA
4446 RDADD=JMS I XRDAD
4452 LDADD=JMS I XLDAD
4447 DSKSKP=JMS I XSDKP
4450 LDCMD=JMS I XLDCM
4451 LDCUR=JMS I XLDCA
4453 CLRALL=JMS I XCLDR
4454 RDCRC=JMS I XRDCA
4455 LDMAN=JMS I XLDMA
4456 RDBUF=JMS I XRDBF
4457 PRNFR=JMS I XPRN
4460 OCTEL=JMS I XFRDCT
4461 TWOC=JMS I XTCT
4436 TYPE=JMS I XPRINT
4462 CRLF=JMS I XCRLF
/
0000 *0
/
0000 0000 0
0001 5001 5001
0002 0002 0002
0003 0003 0003
/
0010 *10
/
0010 0000 AUTO10, 0
/
0011 0010 K0010, 0010
0012 0020 K0020, 0020
0013 0040 K0040, 0040
0014 0100 K0100, 0100
0015 0200 K0200, 0200
0016 0400 K0400, 0400
0017 1000 K1000, 1000
/
0020 *20
/
0020 5553 XDDUT, DDUT
0021 4536 XDIN, DIN
0022 6320 XRNAD, RNAD
0023 8215 XONLY, ONLY
0024 6200 XRESTR, RESTR
0025 5600 XDISKG, DISKG
0026 6432 XHFCNK, HFCNK
0027 5656 XFIGURE, FIGURE
0030 5447 XFLBUF, FLBUF
0031 5435 XKLBUF, KLBUF
0032 5261 XSKPAT, SKPAT
0033 5247 XWTSZ, WTSZ
0034 5215 INTRG, INTADD
0035 0272 TRSFLD, PRSFLD
0036 6151 XPRINT, PRINT

```

0037	6400	XNERR0, NERR0
0040	5000	XERR0, ERR0
0041	5200	XIONWT, IONWT
0042	5221	XCOMP1, COMP1
0043	5231	XCOMP2, COMP2
0044	5300	XROST, ROST
0045	5412	XRDCH, RDCH
0046	5350	XRDAD, RDAD
0047	5333	XSDKP, SDKP
0050	5325	XLDCH, LDCH
0051	5307	XLDCA, LDCA
0052	5317	XLDAD, LDAD
0053	5340	XCLDR, CLDR
0054	6000	XRDCH, RDCH
0055	5244	XLDCH, LDCH
0056	5400	XROST, ROST
0057	6111	XPRN, PRN
0060	6066	XPROCT, PROCT
0061	6036	XTOCT, TOCT
0062	6053	XCLPF, UPONE
0063	7001	XLOTRK, LOTRK
0064	7000	XHITRK, HITRK
0065	4500	CIL450, 4500
0066	4520	TRK212, 4520
0067	7000	SGNBUF, WRKBUF
0070	6000	DRVNO, 0
0071	0000	DRVSV, 0
0072	0001	K0001, 0001
0073	0002	K0002, 0002
0074	0003	K0003, 0003
0075	0004	K0004, 0004
0076	0005	K0005, 0005
0077	0006	K0006, 0006
0100	0007	K0007, 0007
0101	1234	K1234, 1234
0102	2000	K2000, 2000
0103	3000	K3000, 3000
0104	4000	K4000, 4000
0105	6000	K6000, 6000
0106	7000	K7000, 7000
0107	7760	K7760, 7760
0110	7700	K7700, 7700
0111	0077	K0077, 0077
0112	2525	K2525, 2525
0113	5252	K5252, 5252
0114	5000	K5000, 5000
0115	7771	K7771, 7771
0116	0017	K0017, 0017
0117	0037	K0037, 0037
0120	6201	K6201, 6201
0121	6244	K6244, 6244
0122	7740	K7740, 7740
0123	7400	K7400, 7400
0124	7600	K7600, 7600
0125	5403	K5403, 5403

0126	0770	K0770, 0770
0127	7007	K7007, 7007
		/
		DECIMAL
		/
0130	7764	M12, -12
		/
		OCTAL
		/
0131	7774	M4, -4
0132	0000	REG0, 0
0133	0000	REG1, 0
0134	0000	SBCNT1, 0
0135	0000	TCNTR1, 0
0136	0000	TCNTR2, 0
0137	0000	TCNTR3, 0
0140	0000	TCNTR4, 0
0141	0000	TCNTR5, 0
0142	0000	TCNTR6, 0
		/
0143	0000	GDREG1, 0
0144	0000	GDREG2, 0
0145	0000	CRREG1, 0
0146	0000	CRREG2, 0
0147	0000	STREG, 0
0150	0000	DBREG, 0
0151	0000	CHREG, 0
0152	0000	DAREG, 0
0153	0000	CAREG, 0
0154	0000	ADREG, 0
0155	0000	DTREG, 0
0156	0000	ACREG, 0
0157	0000	HOWEMA, 0
0160	0000	RAPCNT, 0
0161	2200	STCON, 2200
0162	0011	CRWRD1, 0011
0163	6047	CRWRD2, 6047
0164	0000	DATCNT, 0
0165	0000	SAVDAT, 0
0166	0306	K0306, 0306
0167	5373	K5373, 5373
0170	5300	K5300, 5300
0171	6304	K6304, 6304
0172	3240	ENDTRK, 3240
0173	7777	SOPERR, 7777
0174	0000	SAVPCI, 0
0175	0200	RESTR1, 0200
		/
		*200
		/
0200	5206	BGN, JMP
0201	5777	JMP
0202	5776	JMP
0203	5775	JMP
0204	5774	JMP

*,+6	/TO NORMAL TEST
MANGAL	/TO MANUAL TEST
CHANG	/TO CHANGE LOT DEVICE CODES
MANPRO	/CHECK MANUAL WRITE PROTECT
AUTPRO	/CHECK PROGRAM WRITE PROTECT

```

0205 5575      JMP I  RESTR1      /RESTART AFTER PROGRAM STOP1
0206 6224      RIF
0207 3157      DCA   HOMEHA
0210 1157      TAD   HOMEHA
0211 1120      TAD   KCDF        /MAKE HOMEOP
0212 3222      DCA   PRSFLD
0213 1123      TAD   KRMF        /GET RNF FOR INT, RETURN
0214 6201      CDF   0          /SWITCH FIELD 0
0215 3472      DCA I  K0001
0216 1125      TAD   K5403      /JMP I 3 FOR LOC. 2
0217 3473      DCA I  K0002
0220 1034      TAD   INTRQ      /GET ADDRESS RETURN
0221 3474      DCA I  K0003
0222 7402      PRSFLD, HLT
0223 7604      LAB
0224 0074      AND   K0003      /MASK AMOUNT OF DRIVES
0225 3071      DCA   DRIVSV
/
0226 7604      LAB
0227 0016      AND   K0400      /MASK SWR3
0230 7640      SZA  CLA        /TEST DISK IN 10=11
0231 1071      TAD   DRIVSV     /YES, GET DISK NO. TO TEST
0232 7104      CLL  RAL        /MAKE IT IN 9=10
0233 3070      DCA   DRIVNO     /START WITH THIS DRIVE X
0234 3132      DCA   REGO

```

/VERIFY THAT THE DISK DRIVE IN "DRIVNO" IS
/READY TO SEEK, READ, OR WRITE, STATUS REGISTER
/SHOULD GO TO 4000.

```

0235 7330      TST0,  CLA CLL  CML RAR      /EXPECTED STATUS
0236 3144      DCA   GDREG2      /SETUP COMPARE REGISTER
0237 1015      TAD   K0200      /ENABLE SET DONE BIT
0240 1070      TAD   DRIVNO     /GET CURRENT DRIVE NUMBER
0241 4450      LDCMD          /LOAD COMMAND REGISTER
0242 4444      RDSTAT        /READ STATUS
0243 4442      ACCMFI       /CHECK RESULTS
0244 7610      SKP  CLA      /O.K. SO FAR
0245 5253      JMP   TOE
0246 3144      DCA   GDREG2      /SETUP COMPARE REGISTER
0247 4453      CLRALL        /CLEAR STATUS
0250 4444      RDSTAT        /READ STATUS
0251 7650      SNA  CLA      /SHOULD BE 0000
0252 4437      NERROR      /O.K. 4096 LOOPS
0253 4440      ERROR      /ERROR, STATUS
0254 0235      TST0          /SCOPE LOOP POINTER
0255 5200      S200         /TEXT POINTER

```

/VERIFY THAT "DSKP" SKIPS ON TRANSFER DONE FLAG
/WHEN THE DISK DRIVE IS READY.

```

0256 1015      TST1,  TAD   K0200      /ENABLE SET DONE BIT
0257 1070      TAD   DRIVNO     /CURRENT DRIVE
0260 4450      LDCMD          /LOAD COMMAND
0261 4447      DSKSKP       /DSKP "DISK SKIP IOT"

```

```

0262 5266      JMP   T1E        /ERROR, NO SKIP
0263 4453      CLRALL        /CLEAR SKIP FLAG OUT
0264 4447      DSKSKP       /DSKP "DISK SKIP IOT"
0265 4437      NERROR      /O.K. 4096 LOOPS
0266 4440      ERROR      /ERROR, DSKP FAILED
0267 0256      TST1          /SCOPE LOOP POINTER
0270 0006      S006         /TEXT POINTER

```

/VERIFY THAT INT, OCCURS FROM
/THE TRANSFER DONE FLAG WHEN DISK
/DRIVE UNDER TEST IS READY TO SEEK,
/READ, OR WRITE.

```

0271 1015      TST2,  TAD   K0200      /ENABLE SET DONE BIT
0272 1016      TAD   K0400      /ENABLE DISK INT.
0273 1070      TAD   DRIVNO     /GET CURRENT DRIVE
0274 4450      LDCMD          /LOAD COMMAND REGISTER
0275 7240      CLA  CMA      /SOFTWARE FLAG
0276 4441      IONWAT       /WAIT FOR DISK INTERRUPT
0277 5313      JMP   T2E
0300 4453      CLRALL        /CLEAR THE INT. OUT
0301 7240      CLA  CMA      /SOFTWARE FLAG
0302 4441      IONWAT       /WAIT FOR DISK INTERRUPT
0303 7610      SKP  CLA      /O.K. NO INT.
0304 5313      JMP   T2E
0305 1015      TAD   K0200      /ERROR, INT.
0306 1070      TAD   DRIVNO     /ENABLE SET DONE BIT
0307 4450      LDCMD          /CURRENT DRIVE
0310 7340      CLA  CLL  CMA      /LOAD COMMAND
0311 4441      IONWAT       /SOFTWARE FLAG
0312 4437      NERROR      /WAIT FOR DISK INTERRUPT
0313 4440      ERROR      /O.K. 4096 LOOPS
0314 0271      TST2          /ERROR, DISK INT.
0315 0007      S007         /SCOPE LOOP POINTER
0315 0007      S007         /TEXT POINTER

```

/VERIFY A "TIMING ERROR" DOES OCCUR IN STATUS REGISTER
/IF A FLAG IS ISSUED WITH THE COMMAND REGISTER IS SET TO
/A FUNCTION OF "1".

```

0316 2132      ISZ   REGO
0317 1106      TAD   K7000
0320 1157      TAD   HOMEHA
0321 1070      TAD   DRIVNO     /GET CURRENT DRIVE
0322 4450      LDCMD          /LOAD COMMAND REGISTER
0323 1077      TAD   K0006
0324 3350      DCA   T3T        /SETUP TEXT POINTER
0325 4452      LDADD        /FLAG, LOAD DISK ADDRESS
0326 4437      SKPWAT       /WAIT FOR ERROR SKIP
0327 5346      JMP   T3E
0330 1170      TAD   K5300
0331 3350      DCA   T3T        /SETUP TEXT POINTER
0332 7330      CLA  CLL  CML RAR
0333 1013      TAD   K0040
0334 3144      DCA   GDREG2      /SETUP EXPECTED STATUS
0335 4444      RDSTAT        /READ STATUS REGISTER

```

```

0336 4442          ACCMP1          /CHECK RESULTS
0337 7610          SKP CLA          /STATUS IS O.K.
0340 5346          JMP T3E          /ERROR STATUS INCORRECT
0341 4453          CLRALL          /CLEAR STATUS
0342 3144          DCA GDREG2       /SETUP EXPECTED STATUS
0343 4444          RDSTAT          /READ STATUS
0344 4442          ACCMP1          /CHECK RESULTS
0345 4437          NERROR          /ALL IS O.K.
0346 4440          T3E, ERROR       /ERROR, TIMING SKIP OR STATUS
0347 0317          TST3          /SCOPE LOOP POINTER
0350 0006          T3T, 0006         /TEXT POINTER
/
/VERIFY THAT "RECALIBRATE" SETS TRANSFER
/DONE THEN DRIVE READY ON SELECTED DRIVE.
/
0351 4424          T8T4, RECAL          /*"RECALIBRATE"
0352 0357          T4T          /TEXT POINTER
0353 5355          JMP T4E          /ERROR, SKIP OR STATUS
0354 4437          NERROR          /O.K. TO NEXT TEST
0355 4440          T4E, ERROR       /ERROR, DISK SKIP OR STATUS
0356 0351          T8T4          /SCOPE LOOP POINTER
0357 0006          T4T, 0006         /TEXT POINTER
/
/VERIFY THAT "SEEK ONLY" TRACK 312 SETS
/TRANSFER DONE THEN DRIVE IS READY.
/
0360 7301          T8T5, CLA CLL IAC       /EXTENDED
0361 3151          DCA CMREG       /SETUP EXTENDED BIT
0362 1066          TAD TRK212      /GET LOWER DISK ADDRESS
0363 4423          SEEK          /SEEK ONLY 312
0364 0371          TST          /TEXT POINTER
0365 5367          JMP T5E          /ERROR, SKIP OR STATUS
0366 4437          NERROR          /O.K. TO NEXT TEST
0367 4440          T5E, ERROR       /ERROR, DISK SKIP OR STATUS
0370 0360          T8T5          /SCOPE LOOP POINTER
0371 0006          T8T, 0006        /TEXT POINTER
/
0372 5773          JMP I ,+1          /TO NEXT TEST
0373 0400          T8T6
/
0374 4710
0375 4101
0376 6535
0377 4600
PAGE
/
/SOMETHING IS WORKING. NOW SEEK ONLY TRACK 312
/WHEN RECALIBRATE AND CHECK FOR NO ERRORS IN STATUS.
/
0400 7301          T8T6, CLA CLL IAC       /SETUP EXTENDED BIT
0401 3151          DCA CMREG       /EXTENDED BIT
0402 1066          TAD TRK212      /GET LOWER DISK ADDRESS
0403 4423          SEEK          /SEEK ONLY 312
0404 0414          T6T          /TEXT POINTER
0405 5212          JMP T6E          /ERROR, SKIP OR STATUS

```

```

0406 4424          RECAL          /*"RECALIBRATE"
0407 0414          T6T          /TEXT POINTER
0410 5212          JMP T6E          /ERROR, SKIP OR STATUS
0411 4437          NERROR          /O.K. TO NEXT TEST
0412 4440          T6E, ERROR       /ERROR, STATUS
0413 0400          T8T6          /SCOPE LOOP POINTER
0414 5300          T6T, 5300        /TEXT POINTER
/
/VERIFY A "RECALIBRATE" FORM CYLINDER,
/SURFACE, AND SECTOR 07777.
/
0415 3151          T8T7, DCA CMREG       /CLEAR EXTENDED BIT
0416 7340          CLA CLL CMA
0417 4423          SEEK          /SEEK ONLY
0420 0430          T7T          /TEXT POINTER
0421 5226          JMP T7E          /ERROR, SEEK ONLY
0422 4424          RECAL          /*"RECALIBRATE"
0423 0430          T7T          /TEXT POINTER
0424 5226          JMP T7E          /ERROR, SKIP OR STATUS
0425 4437          NERROR          /O.K. TO NEXT TEST
0426 4440          T7E, ERROR       /ERROR, STATUS
0427 0415          T8T7          /SCOPE LOOP POINTER
0430 5300          T7T, 5300        /TEXT POINTER
/
/VERIFY A SEEK ONLY AND FIND ALL ADDRESSES
/INCREMENTAL SEEK TEST. SEEK 0, 1, 2, 3, ETC.
/CHECK TIMING AND NO ERRORS IN STATUS.
/
0431 3135          T8T8, DCA TCNTR1
0432 3136          DCA TCNTR2
0433 1135          T8R, TAD TCNTR1
0434 3151          DCA CMREG       /SETUP EXTENDED BIT
0435 1136          TAD TCNTR2      /LOWER DISK ADDRESS BITS
0436 4423          SEEK          /SEQUENTIAL SEEK ONLY
0437 0456          T8T          /TEXT POINTER
0440 5254          JMP T8E          /ERROR, SKIP OR STATUS
0441 2136          ISZ TCNTR2      /UPDATE POINTER
0442 7610          SKP CLA
0443 2135          ISZ TCNTR1
0444 1135          TAD TCNTR1      /SET EXTENDED BIT
0445 7650          SNA CLA
0446 5233          JMP T8R          /IS EXTENDED BIT SET YET
0447 1136          TAD TCNTR2      /NO, CONTINUE
0450 1172          TAD ENDTRK      /YES
0451 7640          SZA CLA
0452 5233          JMP T8R          /WAS IT LAST TRACK
0453 4437          NERROR          /NO, CONTINUE
0454 4440          T8E, ERROR       /O.K. TO NEXT TEST
0455 0431          T8T8          /ERROR, STATUS
0456 5300          T8T, 5300        /SCOPE LOOP POINTER
/
/VERIFY A SEEK ONLY AND FIND ALL ADDRESSES
/312, 311, 310, 307, ETC. CHECK FOR
/NO ERRORS IN STATUS REGISTER.
/

```

```

0457 1066 /
0460 1110 TST9, TAD TRK212
0461 1135 TAD K0017
0462 7301 DCA TCNTR1 /SETUP LOWER DISK ADDRESS POINT
0463 1136 DCA TCNTR2 /SETUP EXTENDED POINTER
0464 1136 T9R, TAD TCNTR2
0465 1151 DCA CMREG /SETUP EXTENDED BIT
0466 1135 TAD TCNTR1
0467 4423 SEEK /DECREMENTAL SEEK ONLY
0470 0511 T9T /TEXT POINTER
0471 5307 JMP T9E /ERROR, SKIP OR STATUS
0472 7340 CLA CLL CMA
0473 1135 TAD TCNTR1
0474 1135 DCA TCNTR1 /DECREMENT
0475 7301 CLA CLL IAC
0476 1135 TAD TCNTR1
0477 7640 SZA CLA /FIRST TIME 0 YET
0500 5264 JMP T9R /NO, CONTINUE
0501 1136 TAD TCNTR2
0502 7650 SNA CLA /PAST EXTENDED BIT
0503 5306 JMP T9OK /YES, TEST O.K.
0504 1136 DCA TCNTR2 /CLEAR EXTENDED BIT
0505 5264 JMP T9R /CONTINUE
0506 4437 T9OK, NERRDR /O.K. TO NEXT TEST
0507 4440 T9E, ERROR /ERROR, SEEK ONLY
0510 0457 TST9 /SCOPE LOOP POINTER
0511 5300 T9T, 5300 /TEXT POINTER
/
/VERIFY & RECALIBRATE FROM ALL
/CYLINDERS, CHECK ALL CYLINDERS
/BETWEEN 0000-14500.
/
0512 1135 TST10, DCA TCNTR1
0513 1136 DCA TCNTR2
0514 1135 T10R, TAD TCNTR1 /GET EXTENDED BIT
0515 1151 DCA CMREG /SETUP EXTENDED BIT
0516 1136 TAD TCNTR2 /GET CYLINDER
0517 4423 SEEK /SEEK ONLY
0520 0545 T10T /TEXT POINTER
0521 5343 JMP T10E /ERROR IN SEEK ONLY
0522 4424 RECAL /"RECALIBRATE"
0523 0545 T10T /TEXT POINTER
0524 5343 JMP T10E /ERROR, SKIP OR STATUS
0525 7300 CLA CLL
0526 1136 TAD TCNTR2 /GET LAST CYLINDER
0527 1013 TAD K0040 /UPDATE
0530 1136 DCA TCNTR2
0531 7430 S2L /TIME TO SET EXTENDED?
0532 2135 ISZ TCNTR1 /YES
0533 1135 TAD TCNTR1 /GET EXTENDED POINTER
0534 7650 SNA CLA /SET?
0535 5314 JMP T10R /NO DO THIS CYLINDER
0536 1136 TAD TCNTR2 /GET LAST CYLINDER
0537 1172 TAD ENDTRK /GET LAST POINTER

```

```

0540 7640 SZA CLA /NON-EXISTENT CYLINDER?
0541 5314 JMP T10R /NO, DO IT
0542 4437 NERRDR /O.K. TO NEXT TEST
0543 4440 T10E, ERROR /STATUS
0544 0512 T10T, 5300 /SCOPE LOOP POINTER
0545 5300 /TEXT POINTER
/
0546 5747 JMP I .+1 /TO NEXT TEST
0547 0600 TST11
/
0600 PAGE
/
/SEEK ONLY SEEMS TO BE WORKING, NOW DO
/A FEW RANDOM SEEKS TO REALLY SHAKE THE
/DISK DRIVE UNDER TEST.
/
0600 1122 TST11, TAD K7740 /AMOUNT OF PASSES
0601 1135 DCA TCNTR1 /SETUP COUNTER
0602 4422 T11R1, RANADD /GENERATE A RANDOM ADDRESS
0603 1136 DCA TCNTR2 /SAVE IT
0604 7004 RAL /LINK IS EXTENDED BIT
0605 1137 DCA TCNTR3 /SAVE IT
0606 4422 RANADD /GENERATE A RANDOM ADDRESS
0607 1140 DCA TCNTR4 /SAVE IT
0610 7004 RAL /LINK IS EXTENDED BIT
0611 1141 DCA TCNTR5 /SAVE IT
0612 4422 T11R2, RANADD /GET A RANDOM NUMBER
0613 0111 AND K0077 /MASK OUT
0614 1110 TAD K7700 /MAKE COUNT VALUE
0615 1160 DCA RANCNT /SETUP COUNTER
0616 1137 T11R3, TAD TCNTR3 /GET EXTENDED BIT
0617 1151 DCA CMREG /SETUP COMMAND REGISTER
0620 1136 TAD TCNTR2
0621 4423 SEEK /SEEK ONLY
0622 0641 T11T /TEXT POINTER
0623 5237 JMP T11E /ERROR, SKIP OR STATUS
0624 1141 TAD TCNTR5 /GET EXTENDED BIT
0625 1151 DCA CMREG /SETUP COMMAND
0626 1140 TAD TCNTR4
0627 4423 SEEK /SEEK ONLY
0630 0641 T11T /TEXT POINTER
0631 5237 JMP T11E /ERROR, SKIP OR STATUS
0632 2160 ISZ RANCNT /UPDATE COUNTER
0633 5216 JMP T11R3 /SAME LOOP
0634 2135 ISZ TCNTR1 /UPDATE PASS COUNTER
0635 5202 JMP T11R1 /MAKE NEW ADDRESS
0636 4437 NERRDR /O.K. TO NEXT
0637 4440 T11E, ERROR /ERROR, SKIP OR STATUS
0640 0600 TST11 /SCOPE LOOP POINTER
0641 0000 T11T, 0000 /MODIFIED TEXT POINTER
/
/NOTE: THE FOLLOWING TWO (2) TESTS WILL NOT BE RUN
/IF SINGLE DRIVE TESTING OTHER THAN DRIVE 0
/OR WHEN MULTI-DRIVE TESTING WITH 4 DRIVES.
/

```

/VERIFY A "NOT READY" ON ALL
/DRIVES NOT ON THE CONTROL.
/

```

0642 3132          DCA  REG0          /SETUP FOR 4096 PASSES
0643 7604          L&S
0644 0016          AND  K0400
0645 7650          SNA CLA          /RUN NEXT TWO TESTS
0646 5252          JMP  ,+4          /MAYBE
0647 1071          TAD  DRIVSV          /TEST FOR OTHER THAN 0
0650 7640          SZA CLA          /MORE ON SYSTEM
0651 5777          JMP  TST14 -1        /YES, DON'T TEST
0652 7346          CLA CLL CMA RTL        /AC TO 775
0653 1071          TAD  DRIVSV          /AMOUNT OF DRIVES
0654 7650          SNA CLA          /ARE THERE FOUR
0655 5777          JMP  TST14 -1        /YES, CAN'T TEST
0656 7301          TST12, CLA CLL IAC
0657 4453          CLRALL
0660 1161          TAD  STCON          /CLEAR CONTROL
0661 3144          DCA  GDREG2         /EXPECTED STATUS
0662 7346          CLA CLL CMA RTL        /SETUP COMPARE
0663 1071          TAD  DRIVSV          /AMOUNT OF DRIVES
0664 3135          DCA  TCNTR1         /AMOUNT NOT THERE
0665 7301          CLA CLL IAC
0666 1071          TAD  DRIVSV          /START WITH THIS DRIVE
0667 3136          DCA  TCNTR2
0670 1136          T12R, TAD  TCNTR2
0671 7104          CLL RAL          /SHIFT TO UNIT BITS
0672 1015          TAD  K0200          /ENABLE SET DONE
0673 4450          LD CMD          /LOAD COMMAND
0674 4444          RD STAT          /READ STATUS
0675 4442          ACC MP1         /CHECK RESULTS
0676 7610          SKP CLA          /O.K.
0677 5305          JMP  T12E          /ERROR, STATUS
0700 4453          CLRALL          /CLEAR STATUS
0701 2136          ISZ  TCNTR2         /UPDATE DRIVE NO.
0702 2135          ISZ  TCNTR1         /WAS IT LAST DRIVE
0703 5270          JMP  T12R          /NO, MORE TO TEST
0704 4437          NERROR          /O.K. 4096 LOOPS
0705 4440          T12E, ERROR          /ERROR, STATUS
0706 0656          TST12          /SCOPE LOOP POINTER
0707 5200          S200          /TEXT POINTER

```

/VERIFY A DRIVE STATUS ERROR ON ALL DRIVES
/NOT ON THE CONTROL, ACTUALLY A SELECT ERROR.
/

```

0710 7301          TST13, CLA CLL IAC
0711 4453          CLRALL          /CLEAR CONTROL
0712 7346          CLA CLL CMA RTL
0713 1071          TAD  DRIVSV          /AMOUNT OF DRIVES
0714 3135          DCA  TCNTR1         /SETUP COUNTER
0715 7301          CLA CLL IAC
0716 1071          TAD  DRIVSV          /START WITH THIS DRIVE
0717 3136          DCA  TCNTR2
0720 1073          T13R, TAD  K0002
0721 1161          TAD  STCON          /EXPECTED STATUS
0722 3144          DCA  GDREG2         /SETUP COMPARE REGISTER

```

```

0723 1136          TAD  TCNTR2
0724 7104          CLL RAL          /GET DRIVE NO.
0725 1015          TAD  K0200          /PUT IN UNIT BITS
0726 1104          TAD  K3000          /ENABLE SET DONE
0727 4450          LD CMD          /FUNCTION SEEK ONLY
0730 4452          LD ADD          /LOAD COMMAND
0731 4444          RD STAT          /LOAD AND GO
0732 4442          ACC MP1         /READ STATUS
0733 7610          SKP CLA          /CHECK RESULTS
0734 5356          JMP  T13E          /O.K.
0735 4453          CLRALL          /ERROR, STATUS
0736 1161          TAD  STCON          /CLEAR STATUS
0737 3144          DCA  GDREG2         /EXPECTED STATUS
0740 4444          RD STAT          /SETUP COMPARE
0741 4442          ACC MP1         /READ STATUS
0742 7610          SKP CLA          /CHECK RESULTS
0743 5356          JMP  T13E          /O.K.
0744 7301          CLA CLL IAC          /ERROR, STATUS
0745 4453          CLRALL
0746 3144          DCA  GDREG2         /CLEAR CONTROL
0747 4444          RD STAT          /SETUP COMPARE
0750 7640          SZA CLA          /READ STATUS
0751 5356          JMP  T13E          /STATUS SHOULD BE 0000
0752 2136          ISZ  TCNTR2         /ERROR, STATUS
0753 2135          ISZ  TCNTR1
0754 5320          JMP  T13R
0755 4437          NERROR          /TRY NEXT DRIVE
0756 4440          T13E, ERROR          /O.K. 4096 LOOPS
0757 0710          TST13          /ERROR, STATUS
0760 5300          S300          /SCOPE LOOP POINTER
0761 5762          /
0762 1000          JMP I ,+1          /TO NEXT TEST
0763 1000          TST14 -1

```

/PAGE
/VERIFY THAT DISK CAPACITY EXCEEDED DOES OCCUR
/

```

1000 2132          TST14, ISZ  REG0          /SETUP FOR ONE PAS
1001 1066          TAD  TRK212
1002 1012          TAD  K0020
1003 3135          DCA  TCNTR1         /ADDRESS POINTER
1004 7301          T14R, CLA CLL IAC          /ENABLE CLEAR CONTRL BIT
1005 4453          CLRALL          /CLEAR CONTROL
1006 7330          CLA CLL CML RAR
1007 1073          TAD  K0002         /EXPECTED STATUS
1010 3144          DCA  GDREG2         /SETUP COMPARE REGISTER
1011 7301          CLA CLL IAC          /EXTENDED TRACK BIT
1012 1103          TAD  K3000          /FUNCTION SEEK ONLY
1013 1070          TAD  DRIVND          /CURRENT DRIVE
1014 4450          LD CMD          /LOAD COMMAND
1015 1135          TAD  TCNTR1
1016 4452          LD ADD          /LOAD AND GO
1017 4432          SKP WAT          /WAIT FOR SKIP

```

```

1020 5260      JMP      T14KE      /ERROR, NO SKIP
1021 4444      RDSTAT      /READ STATUS
1022 4442      ACCMPI      /CHECK RESULTS
1023 7610      SKP CLA      /STATUS O.K.
1024 5254      JMP      T14SE      /ERROR, STATUS
1025 7301      CLA CLL IAC      /ENABLE CLEAR CONTROL BIT
1026 4453      CLRALL      /CLEAR CONTROL
1027 1151      TAD      CMREG      /GET LAST COMMAND
1030 1015      YAD      K0200      /GET ENABLE SEEK DONE BIT
1031 4450      LDCHD      /LOAD COMMAND
1032 4432      SKP=AT      /WAIT FOR DISK SKIP
1033 5260      JMP      T14KE      /ERROR, SKIP
1034 7330      CLA CLL CHL RAR      /EXPECTED STATUS
1035 3144      DCA      GDREG2
1036 4444      RDSTAT      /READ STATUS
1037 4442      ACCMPI      /CHECK RESULTS
1040 7610      SKP CLA      /STATUS O.K.
1041 5254      JMP      T14SE      /ERROR, STATUS
1042 1070      TAD      DRIVNO      /CURRENT DRIVE
1043 4450      LDCHD      /LOAD COMMAND
1044 3144      DCA      GDREG2      /SETUP COMPARE REGISTER
1045 4444      RDSTAT      /READ STATUS
1046 4442      ACCMPI      /CHECK RESULTS
1047 7610      SKP CLA      /STATUS O.K.
1050 5254      JMP      T14SE      /ERROR
1051 2135      ISZ      TCNTR1
1052 5204      JMP      T14R
1053 4437      NERROR      /LOOP
1054 4440      T14SE, ERROR      /O.K. TO NEXT TEST
1055 1001      TST14      /ERROR, DISK CAPACITY EXCEEDED
1056 5300      B300
1057 5263      JMP      .+4
1060 4440      T14KE, ERROR      /SCOPE LOOP POINTER
1061 1001      TST14      /MODIFIED TEXT POINTER
1062 0006      0006      /TO NEXT TEST
1063 4431      /
1064 1114      KILBUF      /ZERO WRITE BUFFER
1065 3151      TST15, TAD      K5000      /WRITE ALL FUNCTION
1066 4425      DCA      CMREG      /SETUP COMMAND
1067 1101      DISKGU      /DISK WRITE ALL
1070 5277      T15T      /TEXT POINTER
1071 1017      JMP      T15E      /ERROR, SKIP OR STATUS
1072 3151      TAD      K1000      /FUNCTION READ ALL
1073 4425      DCA      CMREG      /SETUP COMMAND REGISTER
1074 1101      DISKGU      /DISK READ ALL
1075 5277      T15T      /TEXT POINTER
1076 4437      JMP      T15E      /ERROR, SKIP OR STATUS
1077 4440      NERROR      /O.K. TO NEXT TEST
1100 1064      T15E, ERROR      /ERROR, WRITE ALL
1101 5300      TST15      /SCOPE LOOP POINTER

```

```

1101 5300      T15T, 5300      /MODIFIED TEXT POINTER
/
/VERIFY THAT SKIP AND STATUS DOES OCCUR AFTER
/128 WRITE ALL AND READ ALL BREAKS,
/THIS SHOULD WRITE ALL ZEROS ON AND READ ALL
/ALL ZEROS OFF THE DISK SECTOR 00000.
/
1102 1114      TST15, TAD      K5000      /FUNCTION WRITE ALL
1103 1014      TAD      K0100      /HALF BIT
1104 3151      DCA      CMREG      /SETUP COMMAND
1105 4425      DISKGU      /DISK WRITE ALL
1106 1121      T16T      /TEXT POINTER
1107 5317      JMP      T16E      /ERROR, DISK SKIP OR STATUS
1110 1017      TAD      K1000      /FUNCTION READ ALL
1111 1014      TAD      K0100      /HALF BIT
1112 3151      DCA      CMREG      /SETUP COMMAND
1113 4425      DISKGU      /DISK READ ALL
1114 1121      T16T      /TEXT POINTER
1115 5317      JMP      T16E      /ERROR, SKIP OR STATUS
1116 4437      NERROR      /O.K. TO NEXT TEST
1117 4440      T16E, ERROR      /ERROR, WRITE ALL
1120 1102      TST15      /SCOPE LOOP POINTER
1121 5300      T16T, 5300      /MODIFIED TEXT POINTER
/
/VERIFY A WRITE ALL TO ALL OF CYLINDER 0
/AND USE DATA PATTERN 2525 + 5252,
/MAKE THE FIRST TWO WORDS IN THE BUFFER
/EQUAL THE DISK ADDRESS, CHECK THE DATA WITH
/READ ALL,
/
1122 1122      TST17, TAD      K7740
1123 3135      DCA      TCNTR1      /SETUP SECTOR COUNTER
1124 1112      T17S, TAD      K2525
1125 4430      FILBUF      /FILL OUTBOUND BUFFER
1126 1114      TAD      K5000      /FUNCTION WRITE ALL
1127 3151      DCA      CMREG      /SETUP COMMAND
1130 1135      TAD      TCNTR1
1131 0117      AND      K0037      /MASK OFF SECTORS
1132 3463      DCA I XLOTRK      /SETUP ADDRESS WORD IN BUFFER
1133 1070      TAD      DRIVNO      /GET DRIVE NUMBER
1134 3464      DCA I XHITRK      /SETUP ADDRESS WORD IN BUFFER
1135 1463      TAD I XLOTRK
1136 4425      DISKGU      /DISK WRITE ALL
1137 1162      T17T      /TEXT POINTER
1140 5360      JMP      T17E      /ERROR, SKIP OR STATUS
1141 4431      KILBUF      /KILL DATA BUFFER
1142 1017      TAD      K1000      /FUNCTION READ ALL
1143 3151      DCA      CMREG      /SETUP COMMAND
1144 1135      TAD      TCNTR1
1145 0117      AND      K0037      /MASK OF SECTORS
1146 4425      DISKGU      /DISK READ ALL
1147 1162      T17T      /TEXT POINTER
1150 5360      JMP      T17E      /ERROR, STATUS OR SKIP
1151 1112      TAD      K2525
1152 4427      FIGURE      /WORD BY WORD COMPARE OF DATA

```

```

1153 7610      SKP CLA      /THIS SECTOR O.K.
1154 5360      JMP T17E      /ERROR, DATA
1155 2135      ISZ TCNTR1  /UPDATE SECTOR COUNTER
1156 5324      JMP T17E      /TRY NEXT SECTION
1157 4437      NERROR      /O.K. TO NEXT TEST
1160 4440      T17E, ERROR  /ERROR, READ ALL
1161 1122      TST17      /SCOPE LOOP POINTER
1162 5373      T17T, 5373 /TEXT POINTER
/
1163 5764      JMP I  ,+1    /TO NEXT TEST
1164 1200      TST18
/
1200          PAGE
/
/VERIFY A WRITE DATA TO ALL OF CYLINDER 0
/AND USE DATA PATTERN 5252 + 2525.
/MAKE THE FIRST TWO WORDS OF THE BUFFER
/EQUAL THE DISK ADDRESS, CHECK THE
/DATA WITH READ DATA.
/
1200 1122      TST18, TAD K7740
1201 3135      DCA TCNTR1  /SECTOR COUNTER
1202 1113      T18S, TAD K5252
1203 4430      FILBUF      /FILL OUTBOUND BUFFER
1204 1104      TAD K4000  /FUNCTION WRITE DATA
1205 3151      DCA CMREG   /SETUP COMMAND
1206 1135      TAD TCNTR1
1207 0117      AND K0037  /MASK OF SECTORS
1210 3463      DCA I XLOTRK /SETUP ADDRESS WORD IN BUFFER
1211 1070      TAD DRIVNO  /GET DRIVE NUMBER
1212 3464      DCA I XNITRK /SETUP ADDRESS WORD IN BUFFER
1213 1463      TAD I XLOTRK /GET ADDRESS
1214 4425      DISKGO   /DISK WRITE DATA
1215 1237      T18T      /TEXT POINTER
1216 5235      JMP T18E      /ERROR, STATUS OR SKIP
1217 4431      KILBUF      /CLEAR DATA BUFFER
1220 3151      DCA CMREG   /SETUP COMMAND
1221 1135      TAD TCNTR1
1222 0117      AND K0037  /MASK OFF SECTORS
1223 4425      DISKGO   /DISK READ DATA
1224 1237      T18T      /TEXT POINTER
1225 5235      JMP T18E      /ERROR, STATUS OR SKIP
1226 1113      TAD K5252
1227 4427      FIGURE   /WORD BY WORD COMPARE OF DATA
1230 7610      SKP CLA      /THIS SECTOR O.K.
1231 5235      JMP T18E      /ERROR, DATA
1232 2135      ISZ TCNTR1  /UPDATE SECTOR COUNTER
1233 5202      JMP T18E      /TRY NEXT SECTION
1234 4437      NERROR      /O.K. TO NEXT TEST
1235 4440      T18E, ERROR  /ERROR, DATA BREAK
1236 1200      TST18      /SCOPE LOOP POINTER
1237 5373      T18T, 5373 /TEXT POINTER
/
/VERIFY THAT DISK STOPS BREAK AFTER 128

```

```

/IF THE HALF BIT IS SET, THE REMAINDER OF THE
/THE BUFFER SHOULD BE 0000.
/THE FIRST TWO WORDS OF THE BUFFER SHOULD
/EQUAL THE ABSOLUTE DISK ADDRESS.
/THE DATA PATTERN USED IS 2525 + 5252.
/
1240 1113      TST19, TAD K2525
1241 4430      FILBUF      /FILL BUFFER WITH DATA
1242 1070      TAD DRIVNO
1243 3464      DCA I XNITRK /MAKE DISK ADDRESS WORD
1244 3463      DCA I XLOTRK /MAKE DISK ADDRESS WORD
1245 1114      TAD K5000  /FUNCTION WRITE ALL
1246 1014      TAD K0100  /HALF BIT
1247 3151      DCA CMREG   /SETUP COMMAND
1250 4425      DISKGO   /DISK WRITE ALL
1251 1267      T19T      /TEXT POINTER
1252 5265      JMP T19E      /ERROR, SKIP OR STATUS
1253 4453      CLRALL      /CLEAR STATUS
1254 4431      KILBUF      /ZERO BUFFER
1255 1017      TAD K1000  /FUNCTION READ ALL
1256 3151      DCA CMREG   /SETUP COMMAND
1257 4425      DISKGO   /DISK READ ALL
1260 1267      T19T      /TEXT POINTER
1261 5265      JMP T19E      /ERROR, SKIP OR STATUS
1262 1113      TAD K2525
1263 4426      MAPCHK      /WORD BY WORD COMPARE DATA
1264 4437      T19K, NERROR  /O.K. TO NEXT TEST
1265 4440      T19E, ERROR  /ERROR, DATA BREAK
1266 1240      TST19      /SCOPE LOOP POINTER
1267 5373      T19T, 5373 /TEXT POINTER
/
/VERIFY THAT DISK STOPS BREAK AFTER 128
/IF THE HALF BIT IS SET, THE REMAINDER OF THE
/THE BUFFER SHOULD BE 0000.
/THE FIRST TWO WORDS OF THE BUFFER SHOULD
/EQUAL THE ABSOLUTE DISK ADDRESS.
/THE DATA PATTERN USED IS 5252 + 2525.
/
1270 1113      TST20, TAD K5252
1271 4430      FILBUF      /FILL BUFFER WITH DATA
1272 1070      TAD DRIVNO
1273 3464      DCA I XNITRK /MAKE DISK ADDRESS WORD
1274 3463      DCA I XLOTRK /MAKE DISK ADDRESS WORD
1275 1114      TAD K5000  /FUNCTION WRITE ALL
1276 3151      DCA CMREG   /SETUP COMMAND
1277 4425      DISKGO   /DISK WRITE ALL
1300 1317      T20T      /TEXT POINTER
1301 5315      JMP T20E      /ERROR, SKIP OR STATUS
1302 4453      CLRALL      /CLEAR STATUS
1303 4431      KILBUF      /CLEAR BUFFER
1304 1017      TAD K1000  /FUNCTION READ ALL
1305 1014      TAD K0100  /HALF BIT
1306 3151      DCA CMREG   /SETUP COMMAND
1307 4425      DISKGO   /DISK READ ALL
1310 1317      T20T      /TEXT POINTER

```



```

1311 5315      JMP      T20E      /ERROR, SKIP OR STATUS
1312 1113      TAD      K5252
1313 4426      HAFCHK      /WORD BY WORD COMPARE DATA
1314 4437      T20OK,  NERROR   /O.K. TO NEXT TEST
1315 4440      T20E,   ERROR    /ERROR, DATA BREAK
1316 1270      TST20     /SCOPE LOOP POINTER
1317 5373      T20T,   5373     /TEXT POINTER

```

```

/VERIFY A WRITE ALL THEN READ ALL 128 WORDS.
/THE FIRST TWO WORDS OF THE BUFFER SHOULD
/EQUAL THE ABSOLUTE DISK ADDRESS,
/THE DATA PATTERN USED IS 2525 + 5252.

```

```

1320 1112      TST21,  TAD      K2525
1321 4430      FILBUF      /FILL BUFFER WITH DATA
1322 1070      TAD      DRIVNO
1323 3464      DCA I  XHITRK  /MAKE DISK ADDRESS WORD
1324 3463      DCA I  XLOTRK  /MAKE DISK ADDRESS WORD
1325 1114      TAD      K5000   /FUNCTION WRITE ALL
1326 1014      TAD      K0100   /HALF BIT
1327 3151      DCA      CMREG   /SETUP COMMAND
1330 4425      DISKGO     /DISK WRITE ALL
1331 1350      T21T      /TEXT POINTER
1332 5246      JMP      T21E     /ERROR, SKIP OR STATUS
1333 4453      CLRALL     /CLEAR STATUS
1334 4431      KILBUF     /ZERO BUFFER
1335 1017      TAD      K1000   /FUNCTION READ ALL
1336 1014      TAD      K0100   /HALF BIT
1337 3151      DCA      CMREG   /SETUP COMMAND
1340 4425      DISKGO     /DISK READ ALL
1341 1350      T21T      /TEXT POINTER
1342 5346      JMP      T21E     /ERROR, SKIP OR STATUS
1343 1112      TAD      K2525
1344 4426      HAFCHK      /WORD BY WORD COMPARE DATA
1345 4437      T21OK,  NERROR   /O.K. TO NEXT TEST
1346 4440      T21E,   ERROR    /ERROR, DATA BREAK
1347 1320      TST21     /SCOPE LOOP POINTER
1350 5373      T21T,   5373     /TEXT POINTER

```

```

1351 5752      JMP I    ,+1      /TO NEXT TEST
1352 1400      TST22

```

1400 PAGE

```

/VERIFY A WRITE ALL TO ALL OF CYLINDER 0
/USE DATA PATTERN 2525 + 5252
/CHECK FOR NO ERRORS IN STATUS.
/MAKE FIRST TWO WORDS OF EVERY SECTOR
/EQUAL TO ADDRESS OF SECTOR.

```

```

1400 1122      TST22,  TAD      K7740
1401 3135      DCA      TCNTR1  /SETUP SECTOR COUNTER
1402 1112      DCA      K2525
1403 4430      FILBUF      /FILL BUFFER WITH DATA
1404 1135      T22R1,  TAD      TCNTR1

```

```

1405 0117      AND      K0037      /MASK SECTOR BITS
1406 3463      DCA I  XLOTRK  /SETUP ADDRESS WORD IN BUFFER
1407 1070      TAD      DRIVNO  /GET DRIVE NUMBER
1410 3464      DCA I  XHITRK  /SETUP ADDRESS WORD IN BUFFER
1411 1114      TAD      K5000   /FUNCTION WRITE ALL
1412 3151      DCA      CMREG   /SETUP COMMAND
1413 1463      TAD I  XLOTRK  /GET TRACK AND SECTOR
1414 4425      DISKGO     /DISK WRITE ALL
1415 1444      T22T      /TEXT POINTER
1416 5242      JMP      T22E     /ERROR, STATUS OR SKIP
1417 2135      ISZ      TCNTR1  /UPDATE SECTOR COUNTER
1420 5204      JMP      T22R1  /MORE SECTORS TO GO

```

```

/VERIFY THAT THE DATA WRITTEN ABOVE
/ON CYLINDER 0 WAS O.K. CHECK WITH READ ALL.

```

```

1421 1122      TAD      K7740
1422 3135      DCA      TCNTR1  /COUNTER FOR 37 SECTORS
1423 4431      T22R2,  KILBUF     /CLEAR DATA BUFFER
1424 1017      TAD      K1000   /READ ALL FUNCTION
1425 3151      DCA      CMREG   /SETUP COMMAND
1426 1135      TAD      TCNTR1
1427 0117      AND      K0037
1430 4425      DISKGO     /DISK READ ALL
1431 1444      T22T      /TEXT POINTER
1432 5242      JMP      T22E     /ERROR, STATUS OR SKIP
1433 1112      TAD      K2525
1434 4427      FIGURE     /WORD BY WORD COMPARE OF DATA
1435 7610      SKP CLA     /BUFFER O.K.
1436 5242      JMP      T22E     /ERROR, DATA
1437 2135      ISZ      TCNTR1  /UPDATE SECTOR COUNTER
1440 5223      JMP      T22R2  /MORE SECTORS TO CHECK
1441 4437      NERROR   /O.K. TO NEXT TEST
1442 4440      T22E,   ERROR    /ERROR, STATUS
1443 1400      TST22     /SCOPE LOOP POINTER
1444 5373      T22T,   5373     /TEXT POINTER

```

```

/VERIFY A WRITE DATA TO ALL OF CYLINDER 0
/USE DATA PATTERN 5252 + 2525
/CHECK FOR NO ERRORS IN STATUS.
/MAKE FIRST TWO WORDS OF EVERY SECTOR
/EQUAL TO ADDRESS OF SECTOR.

```

```

1445 1122      TST23,  TAD      K7740
1446 3135      DCA      TCNTR1  /SETUP SECTOR COUNTER
1447 1113      TAD      K5252
1448 4430      FILBUF      /FILL BUFFER WITH DATA
1451 1135      T23R1,  TAD      TCNTR1
1452 0117      AND      K0037      /MASK SECTOR BITS
1453 3463      DCA I  XLOTRK  /SETUP ADDRESS WORD IN BUFFER
1454 1070      TAD      DRIVNO  /GET DRIVE NUMBER
1455 3464      DCA I  XHITRK  /SETUP ADDRESS WORD IN BUFFER
1456 3104      TAD      K4000   /FUNCTION WRITE DATA
1457 3151      DCA      CMREG   /SETUP COMMAND
1460 1463      TAD I  XLOTRK  /SECTOR TO LOAD

```

```

1461 4425          DISKGO          /DISK WRITE ALL
1462 1510          T23T          /TEXT POINTER
1463 5306          JMP T23E          /ERROR, STATUS OR SKIP
1464 2135          ISZ TCNTR1       /UPDATE SECTOR COUNTER
1465 5251          JMP T23R1          /MORE SECTORS TO GO
/
/VERIFY THAT THE DATA WRITTEN ABOVE
/ON CYLINDER 0 WAS O.K, CHECK WITH READ DATA.
/
1466 1122          TAD K7740          /
1467 3135          DCA TCNTR1          /COUNTER FOR 37 SECTORS
1470 4431          T23R2, KILBUF          /CLEAR DATA BUFFER
1471 3151          DCA CMREG          /SETUP COMMAND
1472 1135          TAD TCNTR1          /SECTOR COUNTER
1473 0117          AND K0037          /MASK OFF SECTOR BITS
1474 4425          DISKGO          /DISK READ DATA
1475 1510          T23T          /TEXT POINTER
1476 5306          JMP T23E          /ERROR, STATUS OR SKIP
1477 1113          TAD K5252          /
1500 4427          FIGURE          /WORD BY WORD COMPARE OF DATA
1501 7610          SKP CLA          /DATA O.K,
1502 5306          JMP T23E          /ERROR, DATA
1503 2135          ISZ TCNTR1       /UPDATE SECTOR COUNTER
1504 5270          JMP T23R2          /MORE SECTORS TO CHECK
1505 4437          NERROR          /O.K, TO NEXT TEST
1506 4440          T23E, ERROR          /ERROR, WRITE ALL
1507 1445          TST23          /SCOPE LOOP POINTER
1510 5373          T23T, 5373          /TEXT POINTER
/
/VERIFY A WRITE ALL TO ALL OF CYLINDER 1450
/AND USE DATA PATTERN 2525 + 5252,
/THE FIRST TWO WORDS OF THE SECTOR SHOULD
/EQUAL THE DISK ADDRESS, CHECK THE DATA
/WITH READ ALL.
/
1511 1122          TST24, TAD K7740          /
1512 3135          DCA TCNTR1          /SETUP SECTOR COUNTER
1513 1112          T24E, TAD K2525          /
1514 4430          FILBUF          /FILL OUTBOUND BUFFER
1515 7301          CLA CLL IAC          /
1516 1070          TAD DRIVNO          /GET DRIVE NUMBER
1517 3464          DCA I XNITRK          /SETUP ADDRESS WORD IN BUFFER
1520 7301          CLA CLL IAC          /EXTENDED BIT
1521 1114          TAD K5000          /FUNCTION WRITE ALL
1522 3151          DCA CMREG          /SETUP COMMAND
1523 1135          TAD TCNTR1          /SECTOR COUNTER
1524 0117          AND K0037          /MASK OFF SECTOR BITS
1525 1065          TAD CYL450          /ADD IN CYLINDER
1526 3463          DCA I XLOTRK          /SETUP ADDRESS WORD IN BUFFER
1527 1463          TAD I XLOTRK          /
1530 4425          DISKGO          /DISK WRITE ALL
1531 1556          T24T          /TEXT POINTER
1532 5354          JMP T24E          /ERROR, SKIP OR STATUS
1533 4431          KILBUF          /CLEAR DATA BUFFER
1534 7301          CLA CLL IAC          /EXTENDED BIT

```

```

1535 1017          TAD K1000          /FUNCTION READ ALL
1536 3151          DCA CMREG          /SETUP COMMAND
1537 1135          TAD TCNTR1          /SECTOR COUNTER
1540 0117          AND K0037          /MASK OFF SECTORS
1541 1065          TAD CYL450          /
1542 4425          DISKGO          /DISK READ ALL
1543 1556          T24T          /TEXT POINTER
1544 5354          JMP T24E          /ERROR, STATUS OR SKIP
1545 1112          TAD K2525          /
1546 4427          FIGURE          /WORD BY WORD COMPARE OF DATA
1547 7610          SKP CLA          /THIS SECTOR O.K,
1550 5354          JMP T24E          /ERROR, DATA
1551 2135          ISZ TCNTR1       /UPDATE SECTOR COUNTER
1552 5313          JMP T24E          /TRY NEXT SECTOR
1553 4437          NERROR          /O.K, TO NEXT TEST
1554 4440          T24E, ERROR          /ERROR, READ ALL
1555 1511          TST24          /SCOPE LOOP POINTER
1556 5373          T24T, 5373          /TEXT POINTER
/
1557 5760          JMP I ,+1          /TO NEXT TEST
1560 1600          TST25          /
/ PAGE
/
/VERIFY A WRITE DATA TO ALL OF CYLINDER 1450
/AND USE DATA PATTERN 5252 + 2525,
/THE FIRST TWO WORDS OF THE SECTOR SHOULD
/EQUAL THE DISK ADDRESS, CHECK THE DATA
/WITH READ DATA.
/
1600 1122          TST25, TAD K7740          /
1601 3135          DCA TCNTR1          /SETUP SECTOR COUNTER
1602 1113          T25S, TAD K5252          /
1603 4430          FILBUF          /FILL OUTBOUND BUFFER
1604 7301          CLA CLL IAC          /
1605 1070          TAD DRIVNO          /GET DRIVE NUMBER
1606 3464          DCA I XNITRK          /SETUP ADDRESS WORD IN BUFFER
1607 7301          CLA CLL IAC          /EXTENDED BIT
1610 1104          TAD K4000          /FUNCTION WRITE DATA
1611 3151          DCA CMREG          /SETUP COMMAND
1612 1135          TAD TCNTR1          /SECTOR COUNTER
1613 0117          AND K0037          /MASK OFF SECTOR BITS
1614 1065          TAD CYL450          /ADD IN CYLINDER
1615 3463          DCA I XLOTRK          /SETUP ADDRESS WORD IN BUFFER
1616 1463          TAD I XLOTRK          /
1617 4425          DISKGO          /DISK WRITE DATA
1620 1644          T25T          /TEXT POINTER
1621 5242          JMP T25E          /ERROR, SKIP OR STATUS
1622 4431          KILBUF          /CLEAR DATA BUFFER
1623 7301          CLA CLL IAC          /EXTENDED BIT
1624 3151          DCA CMREG          /SETUP COMMAND
1625 1135          TAD TCNTR1          /SECTOR COUNTER
1626 0117          AND K0037          /MASK OFF SECTORS
1627 1065          TAD CYL450          /
1630 4425          DISKGO          /DISK READ DATA

```

```

1631 1644      T25I      /TEXT POINTER
1632 5242      JMP      T25E      /ERROR, STATUS OR SKIP
1633 1113      TAD      K5252
1634 4427      FIGURE      /WORD BY WORD COMPARE OF DATA
1635 7610      SKP CLA      /THIS SECTOR O.K.
1636 5242      JMP      T25E      /ERROR, DATA
1637 2135      ISZ     TCNTR1    /UPDATE SECTOR COUNTER
1640 5202      JMP      T25S      /TRY NEXT SECTOR
1641 4437      NERROR      /O.K. TO NEXT TEST
1642 4440      T25E,  ERROR      /ERROR, DATA BREAK
1643 1600      TST25      /SCOPE LOOP POINTER
1644 5373      T25T,  5373      /TEXT POINTER
/
/VERIFY A WRITE ALL TO ALL OF CYLINDER 1450
/USE DATA PATTERN 5252 + 2525
/CHECK FOR NO ERRORS IN STATUS.
/MAKE FIRST TWO WORDS OF EVERY SECTOR
/EQUAL TO ADDRESS OF SECTOR.
/
1645 1122      TST26,  TAD      K7740
1646 3135      DCA     TCNTR1    /SETUP SECTOR COUNTER
1647 1113      TAD      K5252
1650 4430      FILBUF      /FILL BUFFER WITH DATA
1651 1135      T26N1,  TAD      TCNTR1
1652 0117      AND     K0037    /MASK SECTOR BITS
1653 1065      TAD     CYL450
1654 3463      DCA I  XLOTRK    /SETUP ADDRESS WORD IN BUFFER
1655 7301      CLA CLL IAC
1656 1070      TAD     DRIVNO   /GET DRIVE NUMBER
1657 3464      DCA I  XHITRK    /SETUP ADDRESS WORD IN BUFFER
1660 7301      CLA CLL IAC      /EXTENDED BIT
1661 1114      TAD     K5000    /FUNCTION WRITE ALL
1662 3131      DCA     CMREG    /SETUP COMMAND
1663 1463      TAD I  XLOTRK    /GET TRACK AND SECTOR
1664 4425      DISKGO      /DISK WRITE ALL
1665 1716      T26I      /TEXT POINTER
1666 5314      JMP      T26E      /ERROR, STATUS OR SKIP
1667 2135      ISZ     TCNTR1    /UPDATE SECTOR COUNTER
1670 5251      JMP      T26R1    /MORE SECTORS TO GO
/
/VERIFY THAT THE DATA WRITTEN ABOVE
/ON CYLINDER 1450 WAS O.K. CHECK WITH READ ALL.
/
1671 1122      TAD      K7740
1672 3135      DCA     TCNTR1    /COUNTER FOR 37 SECTORS
1673 4431      T26R2,  KILBUF      /CLEAR DATA BUFFER
1674 7301      CLA CLL IAC      /EXTENDED BIT
1675 1017      TAD     K1000    /READ ALL FUNCTION
1676 3151      DCA     CMREG    /SETUP COMMAND
1677 1135      TAD     TCNTR1
1678 0117      AND     K0037
1679 1065      TAD     CYL450
1680 4425      DISKGO      /DISK READ ALL
1681 1716      T26I      /TEXT POINTER
1684 5314      JMP      T26E      /ERROR, STATUS OR SKIP

```

```

1705 1113      TAD      K5252
1706 4427      FIGURE      /WORD BY WORD COMPARE OF DATA
1707 7610      SKP CLA      /BUFFER O.K.
1710 5314      JMP      T26E      /ERROR, DATA
1711 2135      ISZ     TCNTR1    /UPDATE SECTOR COUNTER
1712 5273      JMP      T26R2    /MORE SECTORS TO CHECK
1713 4437      NERROR      /O.K. TO NEXT TEST
1714 4440      T26E,  ERROR      /ERROR, STATUS
1715 1645      TST26      /SCOPE LOOP POINTER
1716 5373      T26I,  5373      /TEXT POINTER
/
/VERIFY A WRITE DATA TO ALL OF CYLINDER 1450
/USE DATA PATTERN 2525 + 5252
/CHECK FOR NO ERRORS IN STATUS.
/MAKE FIRST TWO WORDS OF EVERY SECTOR
/EQUAL TO ADDRESS OF SECTOR.
/
1717 1122      TST27,  TAD      K7740
1720 3135      DCA     TCNTR1    /SETUP SECTOR COUNTER
1721 1112      TAD      K2525
1722 4430      FILBUF      /FILL BUFFER WITH DATA
1723 1135      T27R1,  TAD      TCNTR1
1724 0117      AND     K0037    /MASK SECTOR BITS
1725 1065      TAD     CYL450
1726 3463      DCA I  XLOTRK    /SETUP ADDRESS WORD IN BUFFER
1727 7301      CLA CLL IAC
1728 1070      TAD     DRIVNO   /GET DRIVE NUMBER
1729 3464      DCA I  XHITRK    /SETUP ADDRESS WORD IN BUFFER
1732 7301      CLA CLL IAC      /EXTENDED BIT
1733 1104      TAD     K4000    /FUNCTION WRITE DATA
1734 3151      DCA     CMREG    /SETUP COMMAND
1735 1463      TAD I  XLOTRK    /SECTOR TO LOAD
1736 4425      DISKGO      /DISK WRITE ALL
1737 1767      T27I      /TEXT POINTER
1740 5365      JMP      T27E      /ERROR, STATUS OR SKIP
1741 2135      ISZ     TCNTR1    /UPDATE SECTOR COUNTER
1742 5323      JMP      T27R1    /MORE SECTORS TO GO
/
/VERIFY THAT THE DATA WRITTEN ABOVE
/ON CYLINDER 1450 WAS O.K. CHECK WITH READ DATA.
/
1743 1122      TAD      K7740
1744 3135      DCA     TCNTR1    /COUNTER FOR 37 SECTORS
1745 4431      T27R2,  KILBUF      /CLEAR DATA BUFFER
1746 7301      CLA CLL IAC      /FUNCTION READ DATA
1747 3151      DCA     CMREG    /SETUP COMMAND
1750 1135      TAD     TCNTR1
1751 0117      AND     K0037
1752 1065      TAD     CYL450
1753 4425      DISKGO      /DISK READ DATA
1754 1767      T27I      /TEXT POINTER
1755 5365      JMP      T27E      /ERROR, STATUS OR SKIP
1756 1112      TAD     K2525
1757 4427      FIGURE      /WORD BY WORD COMPARE OF DATA
1760 7610      SKP CLA      /DATA O.K.

```

```

1761 5365      JMP      T27E      /ERROR, DATA
1762 2135      ISZ     TCNTR1   /UPDATE SECTOR COUNTER
1763 5345      JMP      T27R2   /MORE SECTORS TO CHECK
1764 4437      MERROR /O.K. TO NEXT TEST
1765 4440      T27E,  ERROR    /ERROR, WRITE ALL
1766 1717      T27I,  TST27   /SCOPE LOOP POINTER
1767 5373      /TEXT POINTER
/
/SECTOR TIMING TEST
/VERIFY THAT WRITE AND READ ALL ARE ACTUALLY DOING CONSECUTIVE
/SECTORS, WHEN DOING CONSECUTIVE SECTORS IN WRITE OR READ
/ALL MODE, SECTOR TRANSFERS SHOULD OCCUR EVERY 2.5 MILLI-
/SECONDS, THE PROGRAM WILL REPORT A STATUS ERROR OF
/NO DONE FLAG IF THIS DOES NOT OCCUR.
/
1770 1157      TAD     HOMEWA
1771 1070      TAD     DRIVNO
1772 3137      DCA     TCNTR3   /SAVE FIELD + DRIVE
1773 1122      TST28, TAD     K7140
1774 3135      DCA     TCNTR1   /SETUP SECTOR COUNTER
1775 1114      TAD     K5000    /FUNCTION WRITE ALL
1776 3151      DCA     CMREG    /SETUP COMMAND
1777 7340      CLA     CLL     CNA
2000 1117      TAD     K0037
2001 4425      DISKGO /SECTOR TO GO
2002 2052      T28I,  /DISK WRITE ALL
2003 5250      JMP     T28E     /TEXT POINTER
2004 1170      TAD     K5300    /ERROR, DISK SKIP OR STATUS
2005 3252      DCA     T28T   /MODIFY TEXT POINTER
2006 1135      T28H,  TAD     TCNTR1
2007 7110      CLL     RAR
2010 7630      SZL     CLA     /WRITE OR READ ALL?
2011 1104      TAD     K4000    /HERE IF WRITE ALL?
2012 1017      TAD     K1000
2013 1137      TAD     TCNTR3   /GET FIELD + DRIVE
2014 3151      DCA     CMREG    /SAVE FOR ERROR TYPEOUT
2015 1151      TAD     CMREG
2016 6746      T2810A, DLDC    /LOAD COMMAND REGISTER
2017 1067      TAD     BGNBUF
2020 3153      DCA     CAREG    /SAVE FOR ERROR TYPEOUT
2021 1153      TAD     CAREG
2022 6744      T2810B, DLCA    /LOAD CURRENT ADDRESS
2023 1135      TAD     TCNTR1
2024 0117      AND     K0037    /MASK SECTOR BITS
2025 3152      DCA     DAREG    /SAVE FOR ERROR TYPEOUT
2026 1152      TAD     DAREG
2027 6743      T2810C, DLAG    /LOAD AND GO
2030 1105      TAD     K6000
2031 3136      DCA     TCNTR2   /TIME COUNTER
2032 6745      T2810D, DRST    /READ STATUS REGISTER
2033 3147      DCA     STREG    /SAVE FOR ERROR TYPEOUT
2034 1147      TAD     STREG
2035 1104      TAD     K4000
2036 7650      SNA     CLA     /WAS STATUS 4000
2037 5245      JMP     T280K    /YES, GOT TRANSFER DONE

```

```

2040 2136      ISZ     TCNTR2   /UPDATE TIME COUNTER
2041 5232      JMP     T2810D  /HALT FOR GOOD STATUS
2042 4447      DSXSKP /ERROR, HAVE TO WAIT FOR FLAG
2043 5242      JMP     ,=1    /HANG IF NO SKIP
2044 5250      JMP     T28E     /ERROR, WRITE ALL
2045 2135      T280K, ISZ     TCNTR1 /UPDATE SECTOR COUNTER
2046 5206      JMP     T28R     /MORE TO TEST
2047 4437      MERROR /O.K. TO NEXT TEST
2050 4440      T28E,  ERROR    /ERROR, WRITE OR READ ALL
2051 1773      TST28 /SCOPE LOOP POINTER
2052 5300      T28I,  5300    /TEXT POINTER
/
/SECTOR TIMING TEST
/VERIFY THAT READ AND WRITE DATA ARE NOT DOING CONSECUTIVE
/SECTORS, WHEN TRYING TO DO CONSECUTIVE SECTORS IN READ DATA
/OR WRITE DATA MODE, SECTOR TRANSFERS SHOULD OCCUR EVERY DISK
/REVOLUTION, APROX. EVERY 40 MILLISECOND. THE PROGRAM WILL
/REPORT AN ERROR OF A DONE FLAG IF THIS DOES NOT OCCUR
/
2053 1122      TST29, TAD     K7740
2054 3135      DCA     TCNTR1   /SECTOR COUNTER
2055 3151      DCA     CMREG    /SETUP COMMAND
2056 1117      TAD     K0037
2057 4425      DISKGO /DISK READ DATA
2060 2126      T29I,  /TEXT POINTER
2061 5324      JMP     T29E     /ERROR, SKIP OR STATUS
2062 1170      TAD     K5300
2063 3326      DCA     T29T   /MODIFY TEXT POINTER
2064 1135      T29H,  TAD     TCNTR1
2065 7110      CLL     RAR
2066 7630      SZL     CLA     /READ DATA OR WRITE DATA
2067 1104      TAD     K4000    /HERE IF WRITE DATA?
2070 1137      TAD     TCNTR3   /GET FIELD + DRIVE
2071 3151      DCA     CMREG    /SAVE FOR ERROR TYPEOUT
2072 1151      TAD     CMREG
2073 6746      T2910A, DLDC    /LOAD COMMAND REGISTER
2074 1067      TAD     BGNBUF
2075 3153      DCA     CAREG    /SAVE FOR ERROR TYPEOUT
2076 1153      TAD     CAREG
2077 6744      T2910B, DLCA    /LOAD CURRENT ADDRESS
2100 1135      TAD     TCNTR1
2101 0117      AND     K0037    /MASK SECTOR BITS
2102 3152      DCA     DAREG    /SAVE FOR ERROR TYPEOUT
2103 1152      TAD     DAREG
2104 6743      T2910C, DLAG    /LOAD AND GO
2105 1105      TAD     K6000
2106 3136      DCA     TCNTR2   /TIME COUNTER
2107 3144      DCA     GDREG2   /EXPECTED STATUS
2110 6745      T2910D, DRST    /READ STATUS REGISTER
2111 3147      DCA     STREG    /SAVE FOR ERROR TYPEOUT
2112 1147      TAD     STREG
2113 7640      SZA     CLA     /STATUS O.K.?
2114 5244      JMP     T29E     /ERROR IN STATUS
2115 2136      ISZ     TCNTR2   /UPDATE TIME COUNTER

```

```

2116 5310      JMP      T2910D      /WAIT FOR GOOD STATUS
2117 4447      DSKSKY           /ERROR, HAVE TO WAIT FOR FLAG
2120 5317      JMP      .-1      /HANG IF NO SKIP
2121 2135      T290K, ISZ  TCNTR1 /UPDATE SECTOR COUNTER
2122 5264      JMP      T29R      /MORE TO TEST
2123 4437      NERROR          /O.K. TO NEXT TEST
2124 4440      T29E,  ERROR      /ERROR, STATUS
2125 2053      TST29           /SCOPE LOOP POINTER
2126 5300      T29T,  5300      /MODIFIED TEXT POINTER
/
/ DATA TRANSFER IS WORKING, NO CHECK CRC WORD IN
/ THE CRC REGISTER AFTER A READ ALL, THE CRC SHOULD BE
/ ALL 0'S FOR ALL 0'S DATA PATTERN.
/
2127 1107      TST30, TAD      K7760
2130 3135      DCA      TCNTR1      /SETUP SECTOR COUNTER
2131 7301      T30R,  CLA CLL IAC
2132 4453      CLRALL           /CLEAR CONTROL
2133 4431      KILBUF          /CLEAR BUFFER AREA
2134 1114      TAD      K5000      /FUNCTION WRITE ALL
2135 3151      DCA      CMREG      /SETUP COMMAND
2136 1135      TAD      TCNTR1
2137 0116      AND      K0017      /MASK SECTOR BITS
2140 4425      DISKGO          /DISK WRITE ALL
2141 2171      T30I           /TEXT POINTER
2142 5367      JMP      T30E      /ERROR, STATUS OR SKIP
2143 1017      TAD      K1000      /FUNCTION READ ALL
2144 3151      DCA      CMREG      /SETUP COMMAND
2145 1135      TAD      TCNTR1
2146 0116      AND      K0017      /MASK SECTOR BITS
2147 4425      DISKGO          /DISK READ ALL
2150 2171      T30I           /TEXT POINTER
2151 5367      JMP      T30E      /ERROR, STATUS OR SKIP
2152 1171      TAD      K6304
2153 3371      DCA      T30T      /MODIFY TEXT POINTER
2154 7301      CLA CLL IAC      /ENABLE CLEAR CONTROL
2155 4453      CLRALL           /AND CLEAR BRK ENABLE FLOP
2156 3143      DCA      GDREG1      /STORE IN COMPARE REGISTER
2157 3144      DCA      GDREG2      /STORE IN COMPARE REGISTER
2160 4454      RDCRC           /READ CRC REGISTER
2161 4443      ACCMP2          /CHECK RESULTS
2162 7610      SKP CLA
2163 5367      JMP      T30E      /O.K.
2164 2135      ISZ  TCNTR1      /ERROR, CRC
2165 5331      JMP      T30R      /UPDATE SECTOR COUNTER
2166 4437      NERROR          /MORE SECTORS TO TEST
2167 4440      T30E,  ERROR      /O.K. TO NEXT TEST
2170 2127      TST30           /ERROR, CRC
2171 6304      T30I,  6304      /SCOPE LOOP POINTER
/
/
2172 5773      JMP I      .+1
2173 2200      TST31
/
PAGE
/

```

```

/ VERIFY THAT THE CRC WORD WRITTEN
/ ON DISK IS CORRECT, COMPARE IT TO
/ XNUM VALUE IN CORE, ON A READ ALL THE
/ CRC HEAD FROM DISK IS LEFT IN THE CRC BUFFER,
/ THE CRC SHOULD BE 116047 FOR DATA 2525 + 5252.
/
2200 1107      TST31, TAD      K7760
2201 3135      DCA      TCNTR1      /SETUP SECTOR COUNTER
2202 7301      T31R,  CLA CLL IAC
2203 4453      CLRALL           /CLEAR CONTROL
2204 1112      TAD      K2525
2205 4430      FILBUF          /FILL DATA BUFFER
2206 1114      TAD      K5000      /FUNCTION WRITE ALL
2207 3151      DCA      CMREG      /SETUP COMMAND
2210 1135      TAD      TCNTR1
2211 0116      AND      K0017      /MASK SECTOR BITS
2212 1107      TAD      K7760
2213 4425      DISKGO          /DISK WRITE ALL
2214 2247      T31T           /TEXT POINTER
2215 5245      JMP      T31E      /ERROR, STATUS OR SKIP
2216 1017      TAD      K1000      /FUNCTION READ ALL
2217 3151      DCA      CMREG      /SETUP COMMAND
2220 1135      TAD      TCNTR1
2221 0116      AND      K0017      /MASK SECTOR BITS
2222 1107      TAD      K7760
2223 4425      DISKGO          /DISK READ ALL
2224 2247      T31T           /TEXT POINTER
2225 5245      JMP      T31E      /ERROR, STATUS OR SKIP
2226 1171      TAD      K6304
2227 3247      DCA      T31T      /MODIFY TEXT POINTER
2230 7301      CLA CLL IAC      /ENABLE CLEAR CONTROL AND
2231 4453      CLRALL           /CLEAR BRK ENABLE FLOP.
2232 1162      TAD      CRWRD1      /GET GOOD CRC
2233 3143      DCA      GDREG1      /STORE IN COMPARE REGISTER
2234 1163      TAD      CRWRD2      /GET GOOD CRC
2235 3144      DCA      GDREG2      /STORE IN COMPARE REGISTER
2236 4454      RDCRC           /READ CRC REGISTER
2237 4443      ACCMP2          /CHECK RESULTS
2240 7610      SKP CLA
2241 5245      JMP      T31E      /O.K.
2242 2135      ISZ  TCNTR1      /ERROR, CRC
2243 5202      JMP      T31R      /UPDATE SECTOR COUNTER
2244 4437      NERROR          /MORE SECTORS TO TEST
2245 4440      T31E,  ERROR      /O.K. TO NEXT TEST
2246 2200      TST31           /ERROR, CRC
2247 6304      T31T,  6304      /SCOPE LOOP POINTER
/
/
/ REALLY PROVE THE HEADS ARE MOVING.
/ VERIFY A WRITE ALL TO ALL OF CYLINDER 1450
/ AND THEN CYLINDER 0, USE DATA PATTERN 5252 + 2525 ON
/ CYLINDER 1450 AND 2525 + 5252 ON CYLINDER 0.
/ CHECK FOR NO ERRORS IN STATUS,
/ MAKE FIRST TAD WORDS OF EVERY SETUP
/ EQUAL TO ADDRESS OF SECTOR.
/

```

```

/ FIRST WRITE CYLINDER 1450
/
2280 1122 TST32, TAD K7740
2281 3135 DCA TCNTR1 /SETUP SECTOR COUNTER
2282 1113 TAD K5252
2283 4430 FILBUF /FILL BUFFER WITH DATA
2284 7301 CLA CLL IAC
2285 1070 TAD DRIVNO /GET DRIVE NUMBER
2286 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
2287 1135 T32R1, TAD TCNTR1
2288 0117 AND K0037 /MASK SECTOR BITS
2289 1065 TAD CYL450 /LOWER CYLINDER
2290 3463 DCA I XLOTRK /SETUP WORD IN BUFFER
2291 7301 CLA CLL IAC
2292 1114 TAD K5000 /FUNCTION WRITE ALL
2293 3151 DCA CMREG /SETUP COMMAND
2294 1463 TAD I XLOTRK /SECTOR TO GO
2295 4425 DISKGD /DISK WRITE ALL
2296 2362 T32I /TEXT POINTER
2297 5360 JMP T32E /ERROR, STATUS OR SKIP
2298 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2299 5257 JMP T32R1 /MORE SECTORS TO GO
/
/ WRITE ALL TO ALL OF CYLINDER 0
/
2274 1122 TAD K7740
2275 3135 DCA TCNTR1 /SETUP SECTOR COUNTER
2276 1112 TAD K2525
2277 4430 FILBUF /FILL BUFFER WITH DATA
2278 1135 T32R2, TAD TCNTR1
2279 0117 AND K0037 /MASK SECTOR BITS
2280 3463 DCA I XLOTRK /SETUP ADDRESS WORD IN BUFFER
2281 1070 TAD DRIVNO /GET DRIVE NUMBER
2282 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
2283 1114 TAD K5000 /FUNCTION WRITE ALL
2284 3151 DCA CMREG /SETUP COMMAND
2285 1463 TAD I XLOTRK /SECTOR TO LOAD
2286 4425 DISKGD /DISK WRITE ALL
2287 2362 T32I /TEXT POINTER
2288 5360 JMP T32E /ERROR, SKIP OR STATUS
2289 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2290 5300 JMP T32R2 /MORE SECTORS TO GO
/
/ VERIFY THAT THE DATA WRITTEN ABOVE
/ ON CYLINDER 1450 WAS O.K. CHECK WITH READ ALL.
/
2315 1122 TAD K7740
2316 3135 DCA TCNTR1 /COUNTER FOR 37 SECTORS
2317 4431 KILBUF /CLEAR DATA BUFFER
2318 7301 CLA CLL IAC
2319 1017 TAD K1000 /READ ALL FUNCTION
2320 3151 DCA CMREG /SETUP COMMAND
2321 1135 TAD TCNTR1
2322 0117 AND K0037
2323 1065 TAD CYL450 /ADD IN CYLINDER

```

```

2326 4425 DISKGD /DISK READ ALL
2327 2362 T32I /TEXT POINTER
2328 5360 JMP T32E /ERROR, STATUS OR SKIP
2329 1113 TAD K5252
2330 4427 FIGURE /WORD BY WORD COMPARE OF DATA
2331 7610 SKP CLA /DATA O.K.
2332 5360 JMP T32E /ERROR, DATA
2333 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2334 5317 JMP T32R3 /MORE SECTORS TO CHECK
/
/ VERIFY THAT THE DATA WRITTEN ABOVE
/ ON CYLINDER 0 WAS O.K. CHECK WITH READ ALL.
/
2337 1122 TAD K7740
2338 3135 DCA TCNTR1 /COUNTER FOR 37 SECTORS
2339 4431 KILBUF /CLEAR DATA BUFFER
2340 1017 TAD K1000 /READ ALL FUNCTION
2341 3151 DCA CMREG /SETUP COMMAND
2342 1135 TAD TCNTR1
2343 0117 AND K0037
2344 4425 DISKGD /DISK READ ALL
2345 2362 T32I /TEXT POINTER
2346 5360 JMP T32E /ERROR, STATUS OR SKIP
2347 1112 TAD K2525
2348 4427 FIGURE /WORD BY WORD COMPARE OF DATA
2349 7610 SKP CLA /DATA O.K.
2350 5360 JMP T32E /ERROR, DATA
2351 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2352 5341 JMP T32R4 /MORE SECTORS TO CHECK
2353 4437 MERROR /O.K. TO NEXT TEST
2354 4440 T32E, ERROR /ERROR, WRITE ALL
2355 2250 TST32 /SCOPE LOOP POINTER
2356 5373 T32I, 5373 /TEXT POINTER
/
2363 5764 JMP I ,+1 /TO NEXT TEST
2364 2400 TST33
/
PAGE
/
/ REALLY PROVE HEADS ARE MOVING.
/ VERIFY A WRITE DATA TO ALL OF CYLINDER 0
/ THEN CYLINDER 1450. USE DATA PATTERN 2525 + 5252 ON
/ CYLINDER 1450 AND 5252 + 2525 ON CYLINDER 0.
/ CHECK FOR NO ERRORS IN STATUS.
/ MAKE FIRST TWO WORDS OF EVERY SECTOR
/ EQUAL TO ADDRESS OF SECTOR.
/
/ FIRST WRITE DATA TO CYLINDER 0.
/
2400 1122 TST33, TAD K7740
2401 3135 DCA TCNTR1 /SETUP SECTOR COUNTER
2402 1113 TAD K5252
2403 4430 FILBUF /FILL BUFFER WITH DATA
2404 7300 T33R1, CLA CLL
2405 1135 TAD TCNTR1

```

```

2406 0117 AND K0037 /MASK OFF SECTOR BITS
2407 3463 DCA I XLOTRK /SETUP ADDRESS WORD IN BUFFER
2410 1070 TAD DRIVNO /GET DRIVE NUMBER
2411 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
2412 1104 TAD K4000 /FUNCTION WRITE DATA
2413 3151 DCA CMREG /SETUP COMMAND
2414 1463 TAD I XLOTRK /SECTOR TO LOAD
2415 4425 DISKGO /DISK WRITE DATA
2416 2511 T33T /TEXT POINTER
2417 5307 JMP T33E /ERROR, STATUS OR SKIP
2420 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2421 5204 JMP T33R1 /MORE SECTORS TO GO

```

/WRITE DATA TO ALL OF CYLINDER 1450

```

2422 1122 TAD K7740
2423 3135 DCA TCNTR1 /SETUP SECTOR COUNTER
2424 1112 TAD K2525
2425 4430 FILBUF /FILL BUFFER WITH DATA
2426 7301 CLA CLL IAC
2427 1070 TAD DRIVNO /GET DRIVE NUMBER
2430 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
2431 1135 T33R2, TAD TCNTR1
2432 0117 AND K0037 /MASK OFF SECTOR BITS
2433 1065 TAD CYL450 /ADD IN CYLINDER
2434 3463 DCA I XLOTRK /SETUP ADDRESS WORD IN BUFFER
2435 7301 CLA CLL IAC /EXTENDED TRACK BIT
2436 1104 TAD K4000 /FUNCTION WRITE DATA
2437 3151 DCA CMREG /SETUP COMMAND
2440 1463 TAD I XLOTRK /SECTOR TO LOAD
2441 4425 DISKGO /DISK WRITE DATA
2442 2511 T33T /TEXT POINTER
2443 5307 JMP T33E /ERROR, STATUS OR SKIP
2444 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2445 5231 JMP T33R2 /MORE SECTORS TO GO

```

/VERIFY THAT THE DATA WRITTEN ABOVE
/ON CYLINDER 0 WAS O.K., CHECK WITH READ DATA.

```

2446 1122 TAD K7740
2447 3135 DCA TCNTR1 /COUNTER FOR 37 SECTORS
2450 4431 T33R3, KILBUF /CLEAR DATA BUFFER
2451 3151 DCA CMREG /SETUP COMMAND
2452 1135 TAD TCNTR1
2453 0117 AND K0037
2454 4425 DISKGO /DISK READ DATA
2455 2511 T33T /TEXT POINTER
2456 5307 JMP T33E /ERROR, STATUS OR SKIP
2457 1113 TAD K2525
2460 4427 FIGURE /WORD BY WORD COMPARE OF DATA
2461 7610 SKP CLA /DATA O.K.
2462 5307 JMP T33E /ERROR, DATA
2463 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2464 5250 JMP T33R3 /MORE SECTORS TO CHECK

```

/VERIFY THAT THE DATA WRITTEN ABOVE
/ON CYLINDER 1450 WAS O.K., CHECK WITH READ DATA.

```

2465 1122 TAD K7740
2466 3135 DCA TCNTR1 /SECTOR COUNTER
2467 4431 T33R4, KILBUF /CLEAR DATA BUFFER
2470 7301 CLA CLL IAC
2471 3151 DCA CMREG /SETUP COMMAND
2472 1135 TAD TCNTR1
2473 0117 AND K0037
2474 1065 TAD CYL450 /ADD IN CYLINDER
2475 4425 DISKGO /DISK READ DATA
2476 2511 T33T /TEXT POINTER
2477 5307 JMP T33E /ERROR, STATUS OR SKIP
2500 1112 TAD K2525
2501 4427 FIGURE /WORD BY WORD COMPARE OF DATA
2502 7610 SKP CLA /DATA O.K.
2503 5307 JMP T33E /ERROR, DATA
2504 2135 ISZ TCNTR1 /UPDATE SECTOR COUNTER
2505 5267 JMP T33R4 /MORE SECTORS TO CHECK
2506 4437 HERROR /O.K., TO NEXT TEST
2507 4440 T33E, ERROR /ERROR, WRITE DATA
2510 2400 T33I, T33I3 /SCOPE LOOP POINTER
2511 5373 T33I, 5373 /TEXT POINTER

```

/VERIFY A CYLINDER ADDRESS ERROR IN
/STATUS REGISTER, CAN BE CAUSED BY ISSUING
/MAINTENANCE SHIFT CRC AFTER DISK
/HAS ACCEPTED THE ADDRESS.

```

2512 7301 T33I4, CLA CLL IAC
2513 4453 CLRALL /CLEAR CONTROL
2514 4423 SEEK /SEEK ONLY TRACK 0
2515 2546 T34T /TEXT POINTER
2516 5344 JMP T34E /ERROR, SKIP OR STATUS
2517 7301 CLA CLL IAC
2520 1157 TAD HOMEMA
2521 1070 TAD DRIVNO
2522 1104 TAD K4000 /TOTAL COMMAND WRITE DATA,
2523 4450 LDCMD /LOAD COMMAND REGISTER
2524 7301 CLA CLL IAC
2525 1104 TAD K4000
2526 3144 DCA GDRKG2 /EXPECTED STATUS
2527 1066 TAD TRK212
2530 4452 LOADD /LOAD AND GO READ
2531 7330 CLA CLL CML RAR
2532 4455 LDMAN /ENTER MAINTENANCE
2533 7010 RAR
2534 4455 LDMAN /SET LB4 FOR ENABLE SHIFT
2535 7010 RAR
2536 4455 LDMAN /SHIFT CRC
2537 4447 DSXSK2 /WAIT FOR FLAG
2540 5337 JMP ,=1
2541 4444 RDSTAT /READ STATUS REGISTER
2542 4442 ACCNPI /CHECK RESULTS

```

```

2543 4437          NERROR          /O.K. TO NEXT TEST
2544 4440 T34E,  ERROR          /ERROR, CYLINDER ADDRESS
2545 2512          TSTJ4          /SCOPE LOOP POINTER
2546 5300          T34T,  5300          /TEXT POINTER
/
2547 5750          JMP I    .+1          /TO NEXT TEST
2550 2600          TSTJ5
/
PAGE
/
/VERIFY A CRC ERROR BY ENTERING MAINTENANCE
/AND SHIFTING CRC IN *WRITE ALL MODE,
/
2600 7301          TSTJ5,  CLA CLL IAC
2601 4453          CLRALL          /CLEAR CONTROL
2602 4431          KILBUF          /CLEAR BUFFER AREA
2603 1067          TAD    RGNBUF
2604 4451          LDCUR          /LOAD CURRENT ADDRESS
2605 1157          TAD    HOMEHA
2606 1070          TAD    DRIVNO
2607 1114          TAD    K5000
/
2610 4450          /TOTAL WRITE COMMAND
2611 4452          /LOAD COMMAND
2612 7330          LDCMD          /LOAD AND GO WRITE ALL
2613 4455          LDADD          /ENTER MAINTENANCE
2614 7010          LDMAN          /SET DB4 TO ENABLE SHIFT
2615 4455          RAR
2616 7010          LDMAN          /SET AC BIT 10 DATA
2617 1073          RAR          /SHIFT CRC
2620 4455          TAD    K0002          /SKIP ON ERROR FLAG
2621 4447          DSKSKP          /KEEP SHIFTING CRC TILL ERROR
2622 5220          JMP    .+2
2623 7301          CLA CLL IAC
2624 4453          CLRALL          /CLEAR CONTROL
2625 7330          CLA CLL CML RAP
2626 1011          TAD    K0010          /EXPECTED STATUS REGISTER
2627 3144          DCA    CDREG2
2630 1067          TAD    BGNBUF
2631 4451          LDCUR          /LOAD CURRENT ADDRESS
2632 1157          TAD    HOMEHA
2633 1070          TAD    DRIVNO
2634 1017          TAD    K1000
/
2635 4450          /TOTAL READ ALL COMMAND
2636 4452          /LOAD COMMAND REGISTER
2637 4447          LDADD          /LOAD AND GO READ ALL
2640 5237          /WAIT AND SKIP ON CRC ERROR
2641 4444          JMP    .-1
2642 4442          RDSTAT          /READ STATUS REGISTER
2643 4437          ACCMP1          /CHECK RESULTS
2644 4440          NERROR          /O.K. TO NEXT TEST
2645 2600          T35E,  ERROR          /ERROR, CRC ERROR
2646 5300          TSTJ5          /SCOPE POINTER
/
/TEXT POINTER
/
/BIG ADDRESSING TEST
/FORMAT THE COMPLETE DISK SURFACE WITH

```

```

/WRITE ALL, USE DATA PATTERN 2625 + 5252
/MAKE FIRST TWO WORDS OF EVERY SECTOR
/EQUAL TO ABSOLUTE ADDRESS OF SECTOR,
/
2647 7301          TSTJ6,  CLA CLL IAC
2650 4453          CLRALL          /CLEAN CONTROL
2651 1112          TAD    K2525
2652 4430          FILBUF          /FILL BUFFER WITH DATA
2653 3463          DCA I  XLOTRK          /COUNTER + TRACK WORD
2654 1070          TAD    DRIVNO          /GET DRIVE NUMBER
2655 3464          DCA I  XHIRK          /COUNTER + TRACK WORD
2656 1070          TAD    DRIVNO          /CURRENT DRIVE
2657 1157          TAD    HOMEHA          /CURRENT FIELD
2660 1114          TAD    K5000          /FUNCTION WRITE ALL
2661 3151          DCA    CMREG          /SETUP COMMAND
2662 1067          TAD    BGNBUF          /GET START OF BUFFER
2663 3153          DCA    CAREG          /FOR ERROR PRINTER
2664 7330          T36R,  CLA CLL CML RAP
2665 3144          DCA    GDREG2          /SETUP EXPECTED STATUS COMPARE
2666 1463          TAD I  XLOTRK
2667 3152          DCA    DAREG
2670 1067          TAD    RGNBUF
/
2671 6744          /FOR ERROR PRINTER
2672 1151          IOT4A1,  DLCA          /START OF BUFFER
2673 6746          TAD    CMREG          /LOAD CURRENT ADDRESS
2674 1463          IOT6A1,  BLDC          /LAST COMMAND
2675 6743          TAD I  XLOTRK          /LOAD COMMAND REGISTER
2676 6741          IOT3A1,  DLAG          /SECTOR TO LOAD
2677 5276          IOT1A1,  DSKP          /LOAD AND GO
2678 6745          IOT5A1,  JNP    .-1          /DISK SKIP IOT
2679 3147          DCA    STREG          /WAIT FOR FLAG
2682 1147          TAD    STREG          /READ STATUS
2683 1104          TAD    K4000          /SAVE FOR ERROR PRINTER
2684 7640          SZA CLA          /GET IT
2685 5325          JMP    T36E          /ADD IN FUDGE FACTOR
2686 7301          CLA CLL IAC          /STATUS O.K.????
2687 6742          IOT2A1,  DCLR          /NO, STATUS ERROR
2688 2463          ISZ I  XLOTRK          /ENABLE CLEAR CONTROL
2689 5314          JMP    .+3          /CLEAR CONTROL
2692 2191          ISZ    CMREG          /DON'T SET EXTENDED TRACK
2693 2464          ISZ I  XHIRK          /YES, SET IT
2694 1464          TAD I  XHIRK          /SETUP BUFFER ALAG
2695 7110          CLL RAR          /GET TRACK WORD
2696 7620          SNL CLA          /GET EXTENDED BIT TO LINK
2697 5264          JMP    T36R          /WAS IT SET
2698 1463          TAD I  XLOTRK          /NO, CONTINUE
2699 1172          TAD    ENDTRK          /GET LOWER TRACK WORD
2702 7640          SZA CLA          /ADD IN FUDGE FACTOR
2703 5264          JMP    T36R          /DONE WITH DISK
2704 4437          NERROR          /NO, MORE TO GO
2705 4440          T36E,  ERROR          /O.K. TO NEXT TEST
2706 2641          TSTJ6          /ERROR, STATUS
2707 5300          T36T,  5300          /SCOPE LOOP POINTER
/
/TEXT POINTER
/
2730 5731          JMP I    .+1          /TO NEXT TEST

```



```

2731 3000      TST37
      3000      PAGE
      /
      /BIG ADDRESSING CHECK/
      /IF A DATA ERROR SHOULD HAPPEN TO OCCUR
      /WITH THE FIRST TWO WORDS OF THE BUFFER, YOU
      /SHOULD REALIZE THAT THE PROBLEM COULD BE
      /ADDRESSING.
      /
      /VERIFY THAT THE DATA ON DISK IS CORRECT
      /CHECK THE COMPLETE SURFACE
      /THE DATA ON THE COMPLETE DISK SHOULD BE 2525 + 5252.
      /HOWEVER, THE TWO FIRST WORDS OF EVERY SECTOR
      /SHOULD EQUAL THE ABSOLUTE DISK ADDRESS.
      /
3000 3135      TST37, DCA      TCNTR1
3001 1017      TAD      K1000      /FUNCTION READ ALL
3002 1157      TAD      HOMEWA      /CURRENT FIELD
3003 1070      TAD      DRIVNO      /CURRENT DRIVE
3004 3151      DCA      CMREG      /SETUP COMMAND
3005 1207      TAD      ,+2      /GET TEXT POINTER
3006 7410      SKP
3007 3077      T37T      /TEXT POINTER
3010 3174      DCA      SAVPCT      /SAVE FOR CRC ERROR
3011 1067      TAD      BGNBUF      /GET START OF BUFFER
3012 3153      DCA      CAREG      /SAVE FOR ERROR POINTER
3013 7340      T37R, CLA CLL CMA
3014 3173      DCA      SDFERR      /SETUP CRC ERROR POINTER
3015 4431      KILBUF      /CLEAR DATA BUFFER
3016 1135      TAD      TCNTR1      /LOWER DISK ADDRESS
3017 3152      DCA      DAREG      /SAVE FOR PRINTER
3020 1067      TAD      BGNBUF      /GET START OF BUFFER
3021 6744      IOT4A2, DLCA      /LOAD CURRENT ADDRESS
3022 1151      TAD      CMREG      /GET COMMAND
3023 6746      IOT6A2, DLDC      /LOAD COMMAND REGISTER
3024 1135      TAD      TCNTR1      /GET DISK ADDRESS
3025 6743      IOT3A2, DLAG      /LOAD DISK ADDRESS AND GO
3026 6741      IOT1A2, DSKP      /DISK SKIP IOT
3027 5226      JMP      ,+1      /WAIT FOR DISK SKIP
3030 6745      IOTS2, DRST      /READ STATUS
3031 3147      DCA      STREG      /SAVE FOR ERROR POINTER
3032 1147      TAD      STREG
3033 1104      TAD      K4000
3034 7650      SNA CLA      /ADD IN FUDGE FACTOR
3035 5251      JMP      T37A      /STATUS O.K.
3036 7330      CLA CLL CML RAR      /NO STATUS ERRORS
3037 3144      DCA      GDREG2      /EXPECTED STATUS
3040 1147      TAD      STREL      /SETUP COMPARE REGISTER
3041 0011      AND      R0010      /GET STATUS READ
3042 7640      SZA CLA      /MASK FOR CRC
3043 5247      JMP      ,+4      /AS IF CRC ERROR
3044 1170      TAD      K5300      /YES CRC ERROR
3045 3277      DCA      T37T      /GET TEXT POINTER
      /SAVE IT

```

```

3046 5275      JMP      T37E      /STATUS ERROR NOT CRC
3047 3173      DCA      SDFERR      /SET CRC ERROR POINTER
3050 5253      JMP      ,+3      /DON'T CLEAR CONTROL
3051 7301      T37A, CLA CLL IAC      /ENABLE CLEAR CONTROL
3052 6742      IOT2A2, DCLR      /CLEAR CONTROL
3053 1167      TAD      K5373
3054 3277      DCA      T37T      /SETUP TEXT POINTER
3055 1112      TAD      K2525      /GET EXPECTED DATA
3056 4427      FIGURE      /CHECK DATA READ
3057 7610      SKP CLA      /THIS ONE O.K.
3060 5275      JMP      T37E      /ERROR, DATA
3061 2135      ISZ      TCNTR1      /UPDATE LOWER DISK ADDRESS
3062 7610      SKP CLA
3063 2151      ISZ      CMREG      /SET EXTENDED BIT
3064 1151      TAD      CMREG
3065 0072      AND      K6001
3066 7650      SNA CLA      /IS EXTENDED SET
3067 5213      JMP      T37R      /NO, CONTINUE
3070 1135      TAD      TCNTR1
3071 1172      TAD      ENDTRK
3072 7640      SZA CLA      /ADD IN FUDGE FACTOR
3073 5213      JMP      T37R      /DONE WITH DISK
3074 4437      NERROR      /NO, MORE TO GO
3075 4440      T37E, ERROR      /O.K. TO NEXT TEST
3076 3000      TST37      /ERROR, STATUS
3077 5300      T37T, S300      /SCOPE LOOP POINTER
      /TEXT POINTER
      /
      /BIG ADDRESSING CHECK/
      /IF A DATA ERROR SHOULD HAPPEN TO OCCUR
      /WITH THE FIRST TWO WORDS OF THE BUFFER, YOU
      /SHOULD REALIZE THAT THE PROBLEM COULD BE
      /ADDRESSING.
      /
      /READ ALL SECTORS ON THE DISK AND CHECK
      /THE STATUS, IF STATUS ERROR OCCURS THEN CHECK THE DATA.
      /THE DATA ON THE COMPLETE DISK SHOULD BE 2525 + 5252.
      /HOWEVER, THE TWO FIRST WORDS OF EVERY SECTOR
      /SHOULD EQUAL THE ABSOLUTE DISK ADDRESS.
      /
3100 7340      TST38, CLA CLL CMA
3101 3171      DCA      SDFERR      /SETUP CRC ERROR POINTER
3102 3135      DCA      TCNTR1      /SETUP LOWER ADDRESS
3103 3136      DCA      TCNTR2      /SETUP EXTENDED
3104 1017      TAD      K1000      /FUNCTION READ ALL
3105 1070      TAD      DRIVNO      /CURRENT DRIVE
3106 1157      TAD      HOMEWA      /CURRENT FIELD
3107 3151      DCA      CMREG      /SETUP COMMAND
3110 1067      T38R, TAD      BGNBUF      /START OF BUFFER
3111 4451      LDCUR      /LOAD CURRENT
3112 1151      TAD      CMREG      /LAST COMMAND ISSUED
3113 4450      LDCMD      /LOAD COMMAND
3114 1135      TAD      TCNTR1      /LOWER ADDRESS
3115 4452      LDADD      /LOAD AND GO
3116 4447      DSKSKP      /DISK SKIP IOT
3117 5316      JMP      ,+1      /HANG IF NO SKIP

```

```

3120 4444          RDSTAT          /READ STATUS
3121 1104          TAD          K4000      /SHOULD ONLY BE DONE
3122 7640          SZA CLA          /JUST DONE FLAG ?
3123 5340          JMP          T39E      /STATUS ERROR
3124 2135          ISZ          TCNTR1    /UPDATE ADDRESS
3125 5330          JMP          .+3      /DON'T SET EXTENDED TRACK
3126 2151          ISZ          CMREG     /YES, SET IT
3127 2136          ISZ          TCNTR2
3130 1136          TAD          TCNTR2
3131 7650          SNA CLA          /IS EXTENDED SET
3132 5310          JMP          T39R      /NO, CONTINUE
3133 1135          TAD          TCNTR1
3134 1172          TAD          ENDTRK    /ADD IN FUDGE FACTOR
3135 7640          SZA CLA          /DONE WITH DISK
3136 5310          JMP          T39R      /NO, MORE TO GO
3137 5350          JMP          T39OK     /ALL O.K.
3140 1112          T39E, TAD          K2525
3141 4427          FIGURE          /WORD BY WORD COMPARE OF DATA
3142 5345          JMP          .+3      /ERROR, JUST THE STATUS
3143 1167          TAD          K5373    /TEXT POINTER
3144 7410          SKP          /ERROR
3145 1170          TAD          K5300    /STATUS TEXT POINTER
3146 3353          DCA          T39T     /SETUP
3147 7610          SKP CLA          /STATUS ERROR
3150 4437          T39OK, NERROR      /O.K. TO NEXT TEST
3151 4440          T39DE, ERROR      /ERROR, READ DATA
3152 3100          TST39, TST39      /SCOPE LOOP POINTER
3153 5300          /TEXT POINTER
/
3154 8755          JMP I          .+1      /TO NEXT TEST
3155 3200          TST39
/
PAGE
/
/BIG ADDRESSING CHECK!
/IF A DATA ERROR SHOULD HAPPEN TO OCCUR
/WITH THE FIRST TWO WORDS OF THE BUFFER, YOU
/SHOULD REALIZE THAT THE PROBLEM COULD BE
/ADDRESSING.
/
/CHECK DISK HEADER WORD WITH READ DATA
/IF STATUS ERROR OCCURS THEN CHECK DATA,
/THE DATA ON THE COMPLETE DISK SHOULD BE 2525 + 5252,
/HOWEVER, THE TWO FIRST WORDS OF EVERY SECTOR
/SHOULD EQUAL THE ABSOLUTE DISK ADDRESS.
/
3200 7340          TST39, CLA CLL CHA
3201 3173          DCA          SOFERR     /NO SOFT ERRORS
3202 3135          DCA          TCNTR1    /SETUP LOWER ADDRESS
3203 3136          DCA          TCNTR2    /SETUP EXTENDED
3204 1070          TAD          DRIVNO    /CURRENT DRIVE
3205 1157          TAD          HOMLWA    /CURRENT FIELD
3206 3151          DCA          CMREG     /SETUP COMMAND
3207 1067          T39R, TAD          BGNBUF /START OF BUFFER
3210 4451          LDCUR          /LOAD CURRENT

```

```

3211 1151          TAD          CMREG     /LAST COMMAND
3212 4450          LDCMD          /LOAD COMMAND
3213 1135          TAD          TCNTR1    /LOWER ADDRESS
3214 4452          LDADD          /LOAD AND GO
3215 4447          DSKSKP          /DISK SKIP IOT
3216 5215          JMP          .-1      /HANG IF NO SKIP
3217 4444          ROSTAT          /READ STATUS
3220 1104          TAD          K4000      /SHOULD ONLY BE DONE
3221 7640          SZA CLA          /JUST DONE FLAG ?
3222 5237          JMP          T39E      /STATUS ERROR
3223 2135          ISZ          TCNTR1    /UPDATE ADDRESS
3224 5227          JMP          .+3      /DON'T SET EXTENDED TRACK
3225 2151          ISZ          CMREG     /YES, SET IT
3226 2136          ISZ          TCNTR2
3227 1136          TAD          TCNTR2
3230 7650          SNA CLA          /IS EXTENDED SET
3231 5207          JMP          T39R      /NO, CONTINUE
3232 1135          TAD          TCNTR1
3233 1172          TAD          ENDTRK    /ADD IN FUDGE FACTOR
3234 7640          SZA CLA          /DONE WITH DISK
3235 5207          JMP          T39R      /NO, MORE TO GO
3236 5247          JMP          T39OK     /ALL O.K.
3237 1112          T39E, TAD          K2525
3240 4427          FIGURE          /WORD BY WORD COMPARE OF DATA
3241 5244          JMP          .+3      /ERROR, JUST STATUS
3242 1167          TAD          K5373    /TEXT POINTER
3243 7410          SKP          /ERROR
3244 1170          TAD          K5300    /STATUS ERROR POINTER
3245 3252          DCA          T39T     /SETUP
3246 7610          SKP CLA          /STATUS ERROR
3247 4437          T39OK, NERROR      /O.K. TO NEXT TEST
3250 4440          T39DE, ERROR      /ERROR, READ DATA
3251 3200          TST39, TST39      /SCOPE LOOP POINTER
3252 5300          /TEXT POINTER
/
/DD A RANDOM READ DATA
/THE DATA ON THE COMPLETE DISK SHOULD BE 2525 + 5252,
/HOWEVER, THE TWO FIRST WORDS OF EVERY SECTOR
/SHOULD EQUAL THE ABSOLUTE DISK ADDRESS.
/
3253 1106          TST40, TAD          K7000
3254 3141          DCA          TCNTR5    /LENGTH OF TIME FOR THIS TEST
3255 4422          T40R, FANADD        /GET AN ADDRESS FOR SEEK/READ
3256 3137          DCA          TCNTR3    /SAVE IT
3257 7004          RAL          /LINK IS EXTENDED
3260 3140          DCA          TCNTR4    /SAVE IT
3261 1140          T40S, TAD          TCNTR4
3262 3151          DCA          CMREG     /SETUP COMMAND
3263 1137          TAD          TCNTR3
3264 4425          DISKGO          /DISK READ DATA
3265 3300          T40T          /TEXT POINTER
3266 5276          JMP          T40E      /ERROR, SKIP OR STATUS
3267 1112          TAD          K2525
3270 4427          FIGURE          /WORD BY WORD COMPARE OF DATA
3271 7610          SKP CLA          /DATA O.K.

```

```

3272 5276      JMP      T40E      /DATA ERROR
3273 2141      ISZ      TCNTR5
3274 5255      JMP      T40R      /LOOP
3275 4437      NERMDR      /O.K. TO NEXT TEST
3276 4440      T40E,  ERRPR      /ERROR, READ
3277 3253      TST40      /SCOPE LOOP POINTER
3300 0000      T40T,  0000      /TEXT POINTER
/
/RANDOM SEEK THEN WRITE THEN SEEK THEN READ TEST
/THE DATA WRITTEN IS 2525 + 5252 AND THE TWO
/FIRST WORDS OF THE SECTOR ARE SET TO THE DISK ADDRESS.
/
3301 1110      TST41,  TAD      K7700
3302 3141      DCA      TCNTR5      /PASS COUNTER
3303 4422      T41R,  RANADD      /GENERATE RANDOM NUMBER
3304 0116      AND      K0017
3305 1107      TAD      K7760
3306 3160      DCA      RAPCNT      /SAVE COUNTER
3307 4422      RANADD      /RANDOM SEEK DISK ADDRESS
3310 3135      DCA      TCNTR1      /SAVE
3311 7004      RAL      /LINK IS EXTENDED BIT
3312 3136      DCA      TCNTR2      /SAVE
3313 4422      RANADD      /RANDOM SEEK/WRITE DISK ADDRESS
3314 3137      DCA      TCNTR3      /SAVE
3315 7004      RAL      /LINK IS EXTENDED BIT
3316 3140      DCA      TCNTR4      /SAVE IT
3317 1112      T41S,  TAD      K2525
3320 4430      FILBUF      /FILL BUFFER
3321 1140      TAD      TCNTR4      /GET EXTENDED BIT
3322 1070      TAD      DRIVNO      /GET DRIVE NUMBER
3323 3464      DCA I  XHITRK      /DISK ADDRESS WORD IN BUFFER
3324 1137      TAD      TCNTR3      /LOWER DISK ADDRESS
3325 3463      DCA I  XLOTRK      /DISK ADDRESS WORD IN BUFFER
3326 1136      TAD      TCNTR2      /GET EXTENDED BIT
3327 3151      DCA      CMREG      /SETUP COMMAND
3330 1135      TAD      TCNTR1      /DISK ADDRESS
3331 4423      SEEK      /SEEK ONLY
3332 3372      T41T      /TEXT POINTER
3333 5370      JMP      T41E      /ERROR SKIP OR STATUS
3334 1140      TAD      TCNTR4      /EXTENDED BIT
3335 1104      TAD      K4000      /FUNCTION WRITE DATA
3336 3151      DCA      CMREG      /SETUP COMMAND
3337 1137      TAD      TCNTR3      /DISK ADDRESS
3340 4425      DISKGO      /DISK WRITE DATA
3341 3372      T41T      /TEXT POINTER
3342 5370      JMP      T41E      /ERROR SKIP OR STATUS
3343 1136      TAD      TCNTR2      /GET EXTENDED BIT
3344 3151      DCA      CMREG      /SETUP COMMAND REGISTER
3345 1135      TAD      TCNTR1      /GET DISK ADDRESS
3346 4423      SEEK      /GO SEEK ONLY
3347 3372      T41T      /TEXT POINTER
3350 5370      JMP      T41E      /ERROR, SEEK SKIP OR STATUS
3351 1140      TAD      TCNTR4      /GET EXTENDED BIT
3352 3151      DCA      CMREG      /SETUP READ DATA COMMAND
3353 1137      TAD      TCNTR3      /DISK ADDRESS

```

```

3354 4425      DISKGO      /DISK READ DATA
3355 3372      T41T      /TEXT POINTER
3356 5370      JMP      T41E      /ERROR, SKIP OR STATUS
3357 1112      TAD      K2525
3360 4427      FIGURE      /WORD BY WORD COMPARE OF DATA
3361 7010      SAP CLA      /DATA O.K.
3362 5370      JMP      T41E      /DATA ERROR
3363 2160      ISZ      RAPCNT      /COUNT TO SAME TRACKS
3364 5317      JMP      T41S      /REPEAT
3365 2141      ISZ      TCNTR5      /PASS COUNTER
3366 5303      JMP      T41R      /LOOP
3367 4437      NERMDR      /O.K. TO NEXT TEST
3370 4440      T41L,  ERRPR      /ERROR
3371 3301      TST41      /SCOPE LOOP POINTER
3372 5373      T41T,  5373      /TEXT POINTER
/
3373 5774      JMP I  *+1      /TO NEXT TEST
3374 3400      TST42
/
PAGE
/
/VERIFY A RECALIBRATE THEN A RANDOM WRITE DATA,
/THEN A RECALIBRATE THEN RANDOM READ DATA,
/THE DATA PATTERN WRITTEN IS 2525 + 5252 AND
/THE FIRST TWO WORDS OF EVERY SECTOR
/SHOULD EQUAL THE ABSOLUTE DISK ADDRESS.
/
3400 1110      TST42,  TAD      K7700
3401 3141      DCA      TCNTR5      /PASS COUNTER
3402 4422      T42R,  RANADD      /RANDOM DISK ADDRESS
3403 3135      DCA      TCNTR1      /SAVE
3404 7004      RAL      /LINK IS EXTENDED BIT
3405 3136      DCA      TCNTR2      /SAVE
3406 1112      T42S,  TAD      K2525
3407 4430      FILBUF      /FILL BUFFER
3410 1136      TAD      TCNTR2      /GET EXTENDED BIT
3411 1070      TAD      DRIVNO      /GET DRIVE NUMBER
3412 3464      DCA I  XHITRK      /DISK ADDRESS WORD IN BUFFER
3413 1135      TAD      TCNTR1      /LOWER DISK ADDRESS
3414 3463      DCA I  XLOTRK      /DISK ADDRESS WORD IN BUFFER
3415 4424      RECAL      /RESTORE DRIVE
3416 3451      T42T      /TEXT POINTER
3417 5247      JMP      T42E      /ERROR SKIP OR STATUS
3420 1136      TAD      TCNTR2      /EXTENDED BIT
3421 1104      TAD      K4000      /FUNCTION WRITE DATA
3422 3151      DCA      CMREG      /SETUP COMMAND
3423 1135      TAD      TCNTR1      /DISK ADDRESS
3424 4425      DISKGO      /DISK WRITE DATA
3425 3451      T42T      /TEXT POINTER
3426 5247      JMP      T42E      /ERROR SKIP OR STATUS
3427 4424      RECAL      /RESTORE DRIVE
3428 3451      T42T      /TEXT POINTER
3431 5247      JMP      T42E      /ERROR, SKIP OR STATUS
3432 1136      TAD      TCNTR2      /GET EXTENDED BIT
3433 3151      DCA      CMREG      /SETUP READ DATA COMMAND

```

```

3434 1135 TAD TCNTR1 /DISK ADDRESS
3435 4425 DISAGU /DISK READ DATA
3436 3451 T42I /TEXT POINTER
3437 5247 JMP T42E /ERROR, SKIP OR STATUS
3440 1112 TAD K2525
3441 4427 FIGURE /WORD BY WORD COMPARE OF DATA
3442 7610 SKP CLA /DATA O.K.
3443 5247 JMP T42E /DATA ERROR
3444 2141 ISZ TCNTR5 /PASS COUNTER
3445 5202 JMP T42R /LOOP
3446 4437 NEPROR /O.K. TO NEXT TEST
3447 4440 T42E, ERROR /ERROR
3450 3400 TST42, TST42 /SCOPE LOOP POINTER
3451 5373 T42I, 5373 /TEXT POINTER
/
/TRY TO CAUSE CYLINDER ADDRESS ERRORS BY
/DOING A FEW RANDOM SEEKS THEN A READ DATA.
/
3452 1336 TST43, TAD TIMSTP
3453 3141 DCA TCNTR6 /SETUP PASS COUNTER
3454 4431 T43H1, KILBUF /CLEAR BUFFER
3455 4422 RANAOD /GET RANDOM NUMBER
3456 0117 AND K0037
3457 1122 TAD K7740
3460 3140 OCA TCNTR4 /SETUP COUNTER FOR SEEKS
3461 4422 T43H2, RANAOD /GET RANDOM SEEK ADDRESS
3462 3137 DCA TCNTR3 /SAVE IT
3463 7004 RAL /LINK IS EXTENDED BIT
3464 3136 DCA TCNTR2 /SAVE IT
3465 1136 TAD TCNTR2
3466 3151 DCA CMREG /SETUP COMMAND
3467 1137 TAD TCNTR3
3470 4423 SEFK /SEEK ONLY A RANDOM TRACK
3471 3514 T43T /TEXT POINTER
3472 5312 JMP T43E /ERROR, SKIP OR STATUS
3473 2140 ISZ TCNTR4 /COUNT NUMBER TO GO
3474 5261 JMP T43H2
3475 1136 TAD TCNTR2
3476 3151 DCA CMREG /SETUP FOR READ DATA
3477 1137 TAD TCNTR3
3500 4425 DISKGO /LOAD AND GO READ DATA
3501 3514 T43T /TEXT POINTER
3502 5312 JMP T43E /ERROR SKIP OR STATUS
3503 1112 TAD K2525
3504 4427 FIGURE /CHECK DATA READ
3505 7610 SKP CLA /ALL O.K.
3506 5312 JMP T43E /ERROR, DATA
3507 2141 ISZ TCNTR5
3510 5254 JMP T43R1 /MORE TO TEST
3511 4437 NEPROR /P.K. TO NEXT TEST
3512 4440 T43E, ERROR /ERROR, SKIP, STATUS, OF DATA
3513 3452 TST43, TST43 /SCOPE LOOP POINTER
3514 0000 T43I, 0000 /TEXT POINTER
/
/CHECK DISK HEADER WORDS WITH READ DATA

```

```

/IF STATUS ERROR OCCURRES THEN CHECK DATA.
/THE DATA ON THE COMPLETE DISK SHOULD BE 2525 + 5252.
/HOWEVER, THE TWO FIRST WORDS OF EVERY SECTOR
/SHOULD EQUAL THE ABSOLUTE DISK ADDRESS.
/
3515 7340 TST44, CLA CLL CMA
3516 3173 DCA SUFERM /SETUP CRC ERROR POINTER
3517 3135 OCA TCNTR1 /SETUP LOWER ADDRESS
3520 3136 DCA TCNTR2 /SETUP EXTENDED
3521 1070 TAD DRIVNO /CURRENT DRIVE
3522 1157 TAD HOMEMA /CURRENT FIELD
3523 3151 DCA CMREG /SETUP COMMAND
3524 1067 T44R, TAD BGMBUF /START OF BUFFER
3525 4451 LDCUR /LOAD CURRENT ADDRESS
3526 1151 TAD CMREG /LAST COMMAND ISSUED
3527 4450 LDCMD /LOAD COMMAND
3530 1135 TAD TCNTR1 /LOWER ADDRESS
3531 4452 LDADD /LOAD AND GO
3532 4447 DSKSKP /DISK SKIP 10T
3533 5332 JMP ,+1 /HANG IF NO SKIP
3534 4444 RDSTAT /READ STATUS
3535 1104 TAD K4000 /SHOULD ONLY BE DONE
3536 7640 TIMSTP, SZA CLA /JUST DONE FLAG ?
3537 5354 JMP T44E /STATUS ERROR
3540 2135 ISZ TCNTR1 /UPDATE ADDRESS
3541 5344 JMP ,+3 /DON'T SET EXTENDED TRACK
3542 2151 ISZ CMREG /YES, SET IT
3543 2136 ISZ TCNTR2
3544 1136 TAD TCNTR2
3545 7650 SNA CLA /IS EXTENDED SET
3546 5324 JMP T44R /NO, CONTINUE
3547 1135 TAD TCNTR1
3550 1172 TAD ENDRK /ADD IN FUDGE FACTOR
3551 7640 SZA CLA /DONE WITH DISK
3552 5324 JMP T44R /NO, MORE TO GO
3553 5364 JMP T44OK, T44OK /ALL O.K.
3554 1112 T44E, TAD K2525
3555 4427 FIGURE /WORD BY WORD COMPARE OF DATA
3556 5361 JMP ,+3 /ERROR, JUST STATUS
3557 1167 TAD K5373 /TEXT POINTER
3560 7410 SKP /ERROR
3561 1170 TAD X5300 /STATUS ERROR POINTER
3562 3367 DCA T44T /SETUP
3563 7610 SKP CLA
3564 4437 NEPROR /O.K. TO NEXT TEST
3565 4440 ERROR /ERROR, READ DATA
3566 3515 TST44, TST44 /SCOPE LOOP POINTER
3567 5300 T44T, 5300 /TEXT POINTER
/
/TO NEXT TEST
3570 5771 JMP I ,+1
3571 3600 TST45
/
PAGE
/
/VERIFY THAT WRITING ON A TRACK DOES NOT AFFECT

```

AN ADJACENT TRACK. THE TEST SEQUENCE IS AS FOLLOWS:
 /WRITE TRACKS 00000-00100-00040 THEN READ AND CHECK
 /TRACKS 00040-00000-00100, WRITE TRACKS 00020-00120-00000
 /THEN READ AND CHECK TRACKS 00060-00020-00120, ETC.
 /THE CENTER TRACK IS SET TO A DATA PATTERN OF
 /2525 * 5252, THE LOWER AND UPPER TRACKS ARE
 /SET TO A DATA PATTERN OF 5252 * 2525. THE FIRST TWO
 /WORDS OF EVERY SECTION ARE SET TO THE ABSOLUTE
 /DISK ADDRESS.

3600	1012	T5145,	TAD	K0020	/GET STARTING POINTER
3601	3135		DCA	TCNTR1	/SAVE IT
3602	1350		TAD	K7156	
3603	3141		DCA	TCNTR5	/COUNTER FOR TRACKS TO DO
3604	7346	T455C,	CLA	CLL CMA RIL	
3605	3140		DCA	TCNTR4	/THREE TRACK COUNTER POINTER
3606	1135		TAD	TCNTR1	
3607	3137		DCA	TCNTR3	/WRITE CENTER TRACK FIRST
3610	1112		TAD	K2525	/DATA PATTERN FOR CENTER TRACK
3611	5222		JMP	T45A1	/GO WRITE CENTER TRACK
3612	1140	T45R1,	TAD	TCNTR4	/GET POINTER
3613	7110		CLL	RAR	
3614	7630		SZL	CLA	
3615	1122		TAD	K7740	/WRITE UPPER OR LOWER????
3616	1012		TAD	K0020	/DO LOWER
3617	1135		TAD	TCNTR1	
3620	3137		DCA	TCNTR3	/REDUCE OR UPDATE
3621	1113		TAD	K5252	/SAVE TRACK TO DO
3622	4430	T45A1,	FILLBUF		/USE COMPLEMENT OF CENTER TRACK
3623	1107		TAD	K7760	/FILL BUFFER WITH DATA
3624	3136		DCA	TCNTR2	/GET SECTOR COUNTER POINTER
3625	3142		DCA	TCNTR6	/SETUP COUNTER
3626	1142	T45R2,	TAD	TCNTR6	/START WITH 0
3627	0116		AND	K0017	/GET SECTOR POINTER
3630	3463		DCA	I XLOTRK	/MASK SECTORS
3631	1137		TAD	TCNTR3	/SETUP ADDRESS WORD IN BUFFER
3632	7104		CLL	RAL	/GET DISK ADDRESS
3633	0107		AND	K7760	/PUT EXTENDED BIT IN LINK
3634	1463		TAD	I XLOTRK	
3635	3463		DCA	I XLOTRK	/ADD IN SECTORS
3636	7630		SZL	CLA	/SETUP ADDRESS WORD IN BUFFER
3637	7001		IAC		/SET EXTENDED BIT???
3640	1070		TAD		/YES!!!
3641	3464		DCA	I DRIVNO	/ADD IN CURRENT DRIVE
3642	1464		TAD	I XHITRK	/SETUP ADDRESS WORD IN BUFFER
3643	1104		TAD	K4000	/GET EXTENDED BIT
3644	3151		DCA	CHREG	/FUNCTION WRITE DATA
3645	1463		TAD	I XLOTRK	/SETUP COMMAND REGISTER POINTER
3646	4425		DISKGD		/GET CYL., SURFACE, AND SECTOR
3647	3745		T45T		/WRITE ALL
3650	5343		JMP	T45E	/TEXT POINTER
3651	1142		TAD	TCNTR6	/ERROR, WRITE SKIP OR STATUS
3652	1074		TAD	K0003	
3653	3142		DCA	TCNTR6	/UPDATE SECTOR POINTER
3654	2136		ISZ	TCNTR2	/UPDATE SECTOR COUNTER

3655	5226		JMP	T45R2	/DO REST OF TRACK
3656	2140		ISZ	TCNTR4	/UPDATE TRACK COUNTER
3657	5212		JMP	T45R1	/DO OTHERS
3660	7340		CLA	CLL CMA	
3661	3145		DCA	CRREG1	/SETUP FIRST TIME POINTER
3662	7346		CLA	CLL CMA RIL	
3663	3140		DCA	TCNTR4	/TRACK COUNTER POINTER
3664	1135		TAD	TCNTR1	
3665	3137		DCA	TCNTR3	/SETUP FOR READ CENTER FIRST
3666	5276		JMP	T45A2	/READ AND CHECK CENTER TRACK
3667	1140	T45R3,	TAD	TCNTR4	/POINTER
3670	7110		CLL	RAR	
3671	7630		SZL	CLA	
3672	1122		TAD	K7740	/CHECK UPPER OR LOWER
3673	1012		TAD	K0020	/CHECK LOWER
3674	1135		TAD	TCNTR1	
3675	3137		DCA	TCNTR3	/REDUCE OR UPDATE
3676	1107	T45A2,	TAD	K7760	/SAVE THE TRACK TO READ
3677	3136		DCA	TCNTR2	/AMOUNT OF SURFACE SECTORS
3700	3142		DCA	TCNTR6	/SETUP SECTOR COUNTER
3701	1137	T45R4,	TAD	TCNTR3	/START WITH 0
3702	7104		CLL	RAL	/GET DISK ADDRESS
3703	0107		AND	K7760	/PUT EXTENDED BIT IN LINK
3704	3146		DCA	CRREG2	
3705	7630		SZL	CLA	/SAVE RESULTS
3706	7001		IAC		/SET EXTENDED BIT
3707	3151		DCA	CHREG	/YES
3710	1142		TAD	TCNTR6	/SETUP COMMAND FOR READ DATA
3711	0116		AND	K0017	/GET SECTOR POINTER
3712	1146		TAD	CRREG2	/MASK
3713	4425		DISKGD		/ADD IN TRACK
3714	3745		T45T		/READ DATA
3715	5343		JMP	T45E	/TEXT POINTER
3716	1145		TAD	CRREG1	/ERROR, READ SKIP OR STATUS
3717	7650		SNA	CLA	/GET FIRST TIME POINTER
3720	1112		TAD	K2525	/FIRST TIME???
3721	1112		TAD	K2525	/NO
3722	4427		FIGURE		/CHECK DATA READ
3723	7610		SKP	CLA	/DATA ALL O,K,
3724	5343		JMP	T45E	/ERROR, DATA
3725	1142		TAD	TCNTR6	
3726	1076		TAD	K0005	/UPDATE SECTOR POINTER
3727	3142		DCA	TCNTR6	
3730	2136		ISZ	TCNTR2	/UPDATE SECTOR COUNTER
3731	5301		JMP	T45R4	/DO REST OF SURFACE
3732	3145		DCA	CRREG1	/CLEAR FIRST TIME FLAG
3733	2140		ISZ	TCNTR4	/UPDATE TRACK COUNTER
3734	5267		JMP	T45R3	/DO OTHER TRACKS
3735	1135		TAD	TCNTR1	/GET CURRENT TRACK POINTER
3736	1011		TAD	K0010	/UPDATE
3737	3135		DCA	TCNTR1	/SAVE IT
3740	2141		ISZ	TCNTR5	/UPDATE TOTAL AMOUNT TO DO
3741	5204		JMP	T45SC	/MORE TO DO
3742	4437		NERROR		/ALL O,K, TO END OF TEST

```

3743 4440 T45E, ERROR /ERROR, TRACKS AFFECTED
3744 3600 TST45 /SCOPE LOOP POINTER
3745 0000 T45T, 0000 /MODIFIED TEXT POINTER
/
3746 5741 JMP I ,+1 /TO END OF TEST
3747 4040 ENDTST
/
3750 7156 K7156, 7156
/
4000 PAGE
/
/PROGRAM TO AID IN HEAD ALIGNMENT,
/GET TWO SEPARATE SEEK ADDRESS FROM
/THE SWITCH REGISTER AND SEEK ONLY BETWEEN
/THEM, SECOND ADDRESS MAY BE CHANGED AT ANY TIME.
/
4000 7604 SWSK, LAS /GET FIRST ADDRESS
4001 3135 DCA TCNTR1 /SAVE IT
4002 7402 ENDHLT, HLT /WAIT FOR SECOND ADDRESS
4003 7604 RESEK, LAS /GET SECOND ADDRESS
4004 3135 DCA TCNTR2 /SAVE IT
4005 1136 TAD TCNTR2
4006 0100 AND K0007 /MASK DRIVE + EXT. BIT
4007 1103 TAD K3000 /GET SEEK FUNCTION
4010 4450 LDCMD /LOAD COMMAND REGISTER
4011 1136 TAD TCNTR2
4012 0107 AND K7760 /MASK OFF CYLINDER + SURFACE
4013 4452 LDADD /GO SEEK ONLY
4014 4447 DSKSKP /SKIP ON DONE
4015 5214 JMP ,+1
4016 4453 CLRALL /CLEAR STATUS
4017 4444 RDSTAT /READ STATUS
4020 7640 SZA CLA /DRIVE DONE?
4021 5216 JMP ,+3 /NO, WAIT
4022 1135 TAD TCNTR1 /GET FIRST ADDRESS
4023 0100 AND K0007 /MASK DRIVE + EXT. BIT
4024 1103 TAD K3000 /GET SEEK FUNCTION
4025 4450 LDCMD /LOAD COMMAND REGISTER
4026 1135 TAD TCNTR1
4027 0107 AND K7760 /MASK OFF CYLINDER AND SURFACE
4030 4452 LDADD /LOAD AND GO SEEK
4031 4447 DSKSKP /WAIT FOR DONE
4032 5231 JMP ,+1
4033 4453 CLRALL /CLEAR STATUS
4034 4444 RDSTAT /READ STATUS
4035 7640 SZA CLA /DRIVE DONE?
4036 5231 JMP ,+3 /NO, WAIT
4037 5203 RESEK /CHECK FOR NEW ADDRESS
/
/CONTAINS END OF TEST TYPE OUT AND A CHECK ON S-WR=1
/WHICH IS CONTINUE TO TEST CURRENT DISK.
/ALSO IF THERE IS MORE THAN 1 DISK ON THE SYSTEM
/AND THEY HAVE ALL RUN THE COMPLETE TEST, RUN OVERLAP
/SEEKS AND OVERLAP SEEKS, WRITE, AND READ DATA ON ALL
/DRIVES

```

```

4040 7604 ENDTST, LAS
4041 0016 AND K0400 /MASK SWITCH 3
4042 7640 SZA CLA /LOOP ON SAME DISK
4043 5264 JMP SAMDSK /YES
4044 1071 TAD DRIVSV
4045 7450 SNA /WAS THERE AND EXTRA
4046 5264 JMP SAMDSK /NO, ONLY DISK 0
4047 7104 CLL PAL
4050 7041 CIA
4051 1070 TAD DRIVNO /CURRENT DRIVE
4052 7650 SNA CLA /START OVER YET
4053 5260 JMP TSTSEK /YES, TEST OVERLAP SEEKS
4054 7326 CLA CLL CML RTL
4055 1070 TAD DRIVNO
4056 3070 DCA DRIVNO /UPDATE DRIVE NUMBER
4057 5273 JMP NEXDSK /TEST NEXT DISK DRIVE
4060 4765 TSTSEK, JMS I XLAP /PERFORM OVERLAP SEEKS
4061 4764 JMS I XGRONK /PERFORM OVERLAP SEEKS
4062 4766 JMS I XDVRRD /OVERLAP SEEKS + WRITES + READS
4063 3070 DCA DRIVNO /SETUP DRIVE NO.
4064 4462 SAMDSK, CRLF
4065 4457 PRNTER /PRINT PASS COMPLETE
4066 6741 YEXEND
4067 7604 LAS
4070 0075 AND K0004
4071 7640 SZA CLA /SWITCH 9 SET?
4072 7402 ENDHLT, HLT /YES, STOP PROGRAM
4073 7301 NEXDSK, CLA CLL IAC
4074 4453 CLRALL /DCLR
4075 3132 DCA REG0
4076 3133 DCA REG1
4077 5700 JMP I ,+1 /LOOP ON PROGRAM
4100 0235 TST0
/
/THE FOLLOWING IS A ROUTINE TO CHECK THE WRITE PROTECT
/FUNCTION WHEN IT IS MANUALLY SET BY THE OPERATOR,
/NOTE! NO SCOPE LOOPS ARE AVAILABLE FOR THIS TEST,
/
4101 7604 MANPRO, LAS /GET THE SWITCHES
4102 7104 CLL PAL
4103 0077 AND K0006 /MASK DRIVE NUMBER
4104 3070 DCA DRIVNO /SAVE DRIVE NUMBER
4105 1110 TAD K7700
4106 3133 DCA REG1 /SETUP PASS COUNTER
4107 3132 DCA REG0 /SETUP FLAG POINTER
4110 1112 TAD K2525 /DATA PATTERN TO WRITE
4111 4430 FILBUF /FILL OUTBOUND BUFFER
4112 1070 TAD DRIVNO
4113 3484 DCA I XHITPK /SETUP ADDRESS WORD IN BUFFER
4114 3463 DCA I XLOTHK /SETUP ADDRESS WORD IN BUFFER
4115 1114 TAD K5000 /WRITE ALL FUNCTION
4116 3151 DCA CMREG /SETUP COMMAND
4117 4425 DISKGO /WRITE ALL TO SECTOR 0
4120 4161 IMPROT /TEXT POINTER

```

```

4121 5357      JMP      MPERR      /ERROR, STATUS
4122 7402      MPHLT1, HLT      /HALT AND WAIT FOR OPERATOR
/
4123 4431      MPR1,  KILBUF      /CLEAR OUTBOUND BUFFER
4124 1070      TAD     DRIVND
4125 3469      DCA I  XNTRK      /SETUP ADDRESS WORD IN BUFFER
4126 3114      TAD     K5000
4127 3191      DCA     CMREG      /WRITE ALL FUNCTION
4130 4425      DISKGD
4131 4161      IMPROT      /SETUP COMMAND REGISTER
4132 7000      IMPROT      /WRITE ALL TO SECTOR 0
4133 7326      NOP
4134 1012      CLA CLL CML RIL      /TEXT POINTER
4135 3144      TAD     K0020      /MAKE EXPECTED STATUS
4136 1170      DCA     GOREG2      /SETUP COMPARE REGISTER
4137 3361      TAD     K5300
4140 1147      DCA     IMPROT      /SETUP TEXT POINTER
4141 4442      TAD     STREG      /GET STATUS READ
4142 7610      ACCMPL      /CHECK RESULTS
4143 5357      SKP CLA      /STATUS O.K.
4144 7301      JMP     MPERR      /ERROR, WRITE PROTECT
4145 4453      CLA CLL IAC      /ENABLE CLEAR CONTROL
4146 4431      CLRALL      /CLEAR CONTROL
4147 1017      KILBUF      /CLEAR DATA BUFFER
4150 3151      TAD     K1000      /FUNCTION READ ALL
4151 4425      DCA     CMREG      /SETUP COMMAND
4152 4161      DISKGD      /READ ALL SECTOR 0
4153 5357      IMPROT      /TEXT POINTER
4154 1112      JMP     MPERR      /ERROR
4155 4277      TAD     K2525      /EXPECTED PATTERN
4156 4427      FIGURE      /CHECK DATA READ
4157 4440      MERROR      /ALL O.K., GO LOOP 64 TIMES
4158 4123      MPERR,  ERROR      /ERROR, WRITE PROTECT
4161 0000      MPR1      /TEXT POINTER
4162 7402      MPR1,  0000      /SUCCESSFUL WRITE PROTECT
4163 5301      MPR1,  HLT      /REPEAT
/
4164 4265      XGRONK, GRONK
4165 4200      XLAP,  OVR1AP
4166 4400      XOVRRD, OVRRED
/
4200      PAGE
/
/ROUTINE TO DO OVERLAP SEEKS ON EXISTING DRIVES
/AFTER ALL HAVE RUN THE COMPLETE DIAGNOSTIC
/
4200 0000      OVR1AP,  0
4201 1104      TAD     K4000
4202 3141      DCA     TCNTR5      /PASS COUNTER
4203 1071      OVRP1,  TAD     DRIVSV      /GET AMOUNT OF DRIVES
4204 7040      CMA
4205 3140      DCA     TCNTR4      /SETUP COUNTER
4206 3137      DCA     TCNTR3      /START WITH DRIVE 0
4207 1137      OVRP2,  TAD     TCNTR3
4210 7104      CLL RAL

```

```

4211 3070      DCA     OVR1V0      /DISK NO. POINTER
4212 1137      TAD     TCNTR3
4213 4472      RANADD      /SELECT A RANDOM ADDRESS
4214 4420      BSKOUT      /SEND DISK OUT
4215 4453      CLRALL      /CLEAR STATUS
4216 2137      ISZ   TCNTR3      /UPDATE DRIVE NUMBER
4217 2140      ISZ   TCNTR4      /UPDATE DISK COUNTER
4220 5207      JMP     OVRP2      /DO ALL EXISTING DISKS
4221 3137      DCA     TCNTR3      /CLEAR FOR 0
4222 1071      TAD     DRIVSV      /GET AMOUNT OF DRIVES
4223 7040      CMA
4224 3140      DCA     TCNTR4      /SETUP COUNTER
4225 1137      OVRP3,  TAD     TCNTR3
4226 4421      OSVIN      /CHECK FOR DRIVE DONE
4227 5252      JMP     NOTDON      /DRIVE NOT DONE
4230 5240      JMP     OVR0K      /DRIVE DONE AND NO ERRORS
4231 5261      JMP     OVRERR      /DRIVE ERRORS
4232 2137      NOTDON, ISZ   TCNTR3      /UPDATE DISK NUMBER
4233 1137      TAD     TCNTR3
4234 1140      TAD     TCNTR4
4235 7640      SZA CLA      /LAST EXISTING DRIVE
4236 5225      JMP     OVRP3      /NO, DO REST
4237 5221      JMP     OVRP3 -4      /YES, RESET
4240 7340      OVR0K,  CLA CLL CMA
4241 3140      DCA     TCNTR4
4242 2141      ISZ   TCNTR5      /UPDATE PASS COUNTER, DONE ?
4243 5207      JMP     OVRP2      /NO, SEND OUT
4244 3137      DCA     TCNTR3      /SET FOR 0
4245 1071      TAD     DRIVSV
4246 7040      CMA
4247 3140      DCA     TCNTR4
4250 1137      ALLB1,  TAD     TCNTR3
4251 4421      OSVIN      /CHECK FOR DRIVE DONE
4252 5250      JMP     ALLB1      /WAIT FOR THIS DRIVE
4253 7610      SKP CLA      /WAIT FOR NEXT
4254 5261      JMP     OVRERR      /DRIVE ERRORS
4255 2137      ISZ   TCNTR3
4256 2140      ISZ   TCNTR4
4257 5250      JMP     ALLB1      /LAST DRIVE HOME YET
4260 4437      MERROR      /WAIT FOR ALL
4261 4440      OVRERR,  ERROR      /O.K., TO NEXT
4262 4201      OVR1AP +1      /ERROR, OVERLAP SEEKS
4263 5300      S300      /SCOPE LOOP POINTER
4264 5000      JMP I  OVR1AP      /TEXT POINTER
/
/ROUTINE TO DO OVERLAP SEEKS AND
/REALLY SHAKE THE DRIVES
/ALL DRIVES PERFORM "SEEK ONLY" BETWEEN TRACK
/112 AND SOME RANDOM TRACK.
/
4265 0000      GRONK,  0
4266 1105      TAD     K6000
4267 3141      DCA     TCNTR5      /CLEAR PASS COUNTER
4270 1071      TAD     DRIVSV      /AMOUNT OF DRIVES
4271 7040      CMA

```

```

4272 3140      DCA      TCNTR4      /SETUP POINTER
4273 3137      DCA      TCNTR3      /START WITH 0
4274 1137      GRNKR1, TAD      TCNTR3
4275 7104      CLL RAL
4276 3070      DCA      DRIVNO      /SETUP DRIVE NO. POINTER
4277 1137      TAD      TCNTR3
4300 1777      TAD      DSKPOT      /GET ADDRESS POINTER
4301 3136      DCA      TCNTR2      /SAVE IT
4302 1536      TAD I    TCNTR2      /GET LAST VALUE
4303 7110      CLL RAR
4304 7630      SZL CLA      /EXT. BIT SET?
4305 5311      JMP      ,+4      /YES, GO TO OTHER THAN 312
4306 1066      TAD      TRK212
4307 7121      CLU CML IAC      /SET INDICATORS
4310 5315      JMP      ,+5
4311 1137      TAD      TCNTR3      /SAVE AND SEND DRIVE OUT
4312 4422      RANADD      /GET SAVE POINTER
4313 0370      AND      A7776      /GET RANDOM ADDRESS
4314 7100      CLL
4315 3536      DCA I    TCNTR2      /RESET IT
4316 1536      TAD I    TCNTR2      /GET ADDRESS
4317 4420      DSKOUT      /SEND DRIVE OUT
4320 4453      CLRALL      /CLEAR STATUS
4321 2137      ISZ      TCNTR3      /UPDATE POINTER
4322 2140      ISZ      TCNTR4      /UPDATE COUNTER
4323 5274      JMP      GRNKR1      /MORE TO SEND OUT
4324 3137      DCA      TCNTR3      /START CHECK AT 0
4325 1071      TAD      DRIVSV
4326 7040      CMA
4327 3140      DCA      TCNTR4      /SETUP AMOUNT COUNTER
4330 1137      GRNKR2, TAD      TCNTR3
4331 4421      DSKIN      /CHECK FOR DRIVE DONE
4332 5335      JMP      NTRGRK      /DRIVE NOT DONE
4333 5343      JMP      GRNKRK      /DONE SEND BACK OUT
4334 5364      JMP      GRNKER      /DRIVE ERRORS
4335 2137      NTRGRK, ISZ      TCNTR3      /UPDATE DRIVE NO. POINTER
4336 1140      TAD      TCNTR4
4337 1137      TAD      TCNTR3
4340 7640      SZA CLA      /LAST ONE YET?
4341 5330      JMP      GRNKR2      /NO
4342 5324      JMP      GRNKR2 -4    /YES, RESET POINTER
4343 7340      GRNKRK, CLA CLL CMA
4344 3140      DCA      TCNTR4      /SETUP POINTER
4345 2141      ISZ      TCNTR5      /UPDATE PASS COUNTER
4346 5274      JMP      GRNKR1      /NOT DONE YET
4347 3137      DCA      TCNTR3
4350 1071      TAD      DRIVSV
4351 7040      CMA
4352 3140      DCA      TCNTR4
4353 1137      GRNKR3, TAD      TCNTR3
4354 4421      DSKIN      /CHECK FOR DISK DONE
4355 5353      JMP      GRNKR3      /WAIT FOR DRIVE
4356 7610      SKP CLA      /WAIT FOR NEXT ONE
4357 5364      JMP      GRNKER      /DRIVE ERRORS
4360 2137      ISZ      TCNTR3

```

```

4361 2140      ISZ      TCNTR4
4362 5353      JMP      GRNKR3      /MORE TO WAIT FOR
4363 4437      NERROR      /O.K. TO NEXT TEST
4364 4440      GRNKER, ERROR      /OVERLAP SEEK ERRORS
4365 4266      GRONK +1      /SCOPE LOOP POINTER
4366 5300      5300      /TEXT POINTER
4367 5665      JMP I    GRONK      /EXIT
/
4370 7776, 7776
/
4377 4535
4400
PAGE
/
/PROUTINE TO PERFORM RANDOM OVERLAP SEEKS, WRITES AND,
/READS ON ALL EXISTING DRIVES AFTER THEY HAVE RUN THE
/COMPLETE DIAGNOSTIC,
/
4400 0000      OVRPRD, 0
4401 7330      CLA CLL CML RAR
4402 3141      DCA      TCNTR5      /PASS COUNTER
4403 1071      OVRPRD1, TAD      DRIVSV      /GET AMOUNT OF DRIVES
4404 7040      CMA
4405 3140      DCA      TCNTR4      /SETUP COUNTER
4406 3137      DCA      TCNTR3      /START WITH DRIVE 0
4407 1137      OVRPRD2, TAD      TCNTR3
4410 7104      CLL RAL
4411 3070      DCA      DRIVNO      /SETUP DRIVE POINTER
4412 1137      TAD      TCNTR3
4413 4422      RANADD      /SELECT A RANDOM ADDRESS
4414 4420      DSKOUT      /SEND DISK OUT
4415 4453      CLRALL      /CLEAR STATUS
4416 2137      ISZ      TCNTR3      /UPDATE DISK NUMBER
4417 2140      ISZ      TCNTR4      /UPDATE DISK COUNTER
4420 5207      JMP      OVRPRD2      /DO ALL EXISTING DISKS
4421 3137      DCA      TCNTR3      /CLEAR FOR 0
4422 1071      TAD      DRIVSV      /GET AMOUNT OF DRIVES
4423 7040      CMA
4424 3140      DCA      TCNTR4      /SETUP COUNTER
4425 1137      OVRPRD3, TAD      TCNTR3
4426 4421      DSKIN      /CHECK THIS DRIVE
4427 5234      JMP      CHKNEX      /CHECK FOR NEXT DRIVE
4430 5242      JMP      OVRDOK      /DONE AND NO ERRORS
4431 1170      POLERR, TAD      K5300
4432 3332      DCA      OVRPRD1
4433 5330      JMP      OVRDOP      /SETUP TEXT POINTER
4434 2137      CHKNEX, ISZ      TCNTR3      /ERRORS
4435 1137      TAD      TCNTR3      /UPDATE DISK NUMBER
4436 1140      TAD      TCNTR4
4437 7640      SZA CLA      /LAST EXISTING DRIVE
4440 5225      JMP      OVRPRD3      /NO, GO REST
4441 5221      JMP      OVRPRD3 -4    /YES, RESET
4442 1335      OVRDOK, TAD      DSKPOT      /GET STORAGE POINTER
4443 1137      TAD      TCNTR3      /ADD IN DRIVE NUMBER
4444 3334      DCA      DSKADD      /MAKE ADDRESS
4445 1734      TAD I    DSKADD      /GET DISK ADDRESS

```



```

4446 3136 DCA TCNTR2 /SAVE IT
4447 1334 TAD DSKADD /GET POINTER
4450 1075 TAD K0004 /ADD IN FUDGE FACTOR
4451 3334 DCA DSKADD /MAKE ADDRESS
4452 1137 TAD TCNTR3 /GET DISK NUMBER POINTER
4453 7104 CLL RAL
4454 3070 DCA DRIYNO /MAKE DISK NUMBER
4455 1113 TAD K5252 /GET DATA PATTEN TO USE
4456 4430 FILBUF /FILL DATA BUFFER
4457 1734 TAD I DSKADD /GET EXTENDED BIT
4460 1070 TAD DRIYNO /ADD IN DRIVE NUMBER
4461 3464 DCA I XHITR4 /SETUP ADDRESS WORD IN BUFFER
4462 1136 TAD TCNTR2 /GET CYL., SURFACE, AND SECTOR
4463 3463 DCA I XLOTIR4 /SETUP ADDRESS WORD IN BUFFER
4464 1464 TAD I XHITR4 /GET EXTENDED BIT
4465 1104 TAD K4000 /ADD IN WRITE FUNCTION
4466 3151 DCA CMREG /SETUP COMMAND POINTER
4467 1463 TAD I XLOTIR4 /GET ADDRESS
4470 4425 DISKGO /DISK WRITE DATA
4471 4532 TOVRDT /TEXT POINTER
4472 5330 JMP OVRDER /ERROR, WRITE SKIP OR STATUS
4473 4431 KILBUF /CLEAR DATA BUFFER
4474 1734 TAD I DSKADD /GET EXTENDED BIT
4475 3151 DCA CMREG /SETUP COMMAND REGISTER
4476 1136 TAD TCNTR2 /GET DISK ADDRESS
4477 4425 DISKGO /GO, READ DATA
4500 4532 TOVRDT /TEXT POINTER
4501 5330 JMP OVRDER /ERROR
4502 1113 TAD K5252
4503 4427 FIGURE /WORD BY WORD COMPARE DATA
4504 7610 SKP CLA /DATA O,K, CONTINUE
4505 5330 JMP OVRDER /DATA ERROR
4506 1137 TAD TCNTR3
4507 4422 RANADD /GENERATE RANDOM ADDRESS
4510 4420 DSKDUT /SEND DRIVE BACK OUT
4511 2141 ISZ TCNTR5 /UPDATE PASS COUNTER, DONE ?
4512 5234 JMP CHKEX /CHECK FOR NEXT DRIVE
4513 3137 DCA TCNTR3 /SET FOR 0
4514 1071 TAD DRIYSV
4515 7640 CMA
4516 1140 DCA TCNTR4
4517 1137 TAD TCNTR3
4520 4421 REDBAK, DSKIN /CHECK THIS DRIVE
4521 5317 JMP REDBAK /WAIT FOR DRIVE
4522 7610 SKP CLA /CHECK FOR NEXT
4523 5231 JMP PULERR /ERROR
4524 2137 ISZ TCNTR3
4525 2140 ISZ TCNTR4 /LAST DRIVE HOME YET
4526 5317 JMP REDBAK /WAIT FOR ALL
4527 4437 NEPROR /O,K, TO NEXT
4530 4440 OVRDER, EHROR /OVERLAP SEEMS - READ DATA
4531 4401 OVRPRED +1 /SCOPE LOOP POINTER
4532 5300 TOVRDT, 5300 /TEXT POINTER
4533 5000 JMP I OVRRED /TO NEXT TEST
/

```

```

4534 0000 DSKADD, 0
4535 6365 DSKPOI, DSKOA
/
/ROUTINE TO CHECK DRIVE IN AC
4536 0000 DIN, 0 /MAKE DRIVE NO.
4537 7104 CLL RAL /FIRST SELECT DRIVE
4540 4450 LDCMD
4541 1151 TAD CMREG
4542 1015 TAD K0200 /ENABLE SET DONE BIT
4543 4450 LDCMD /LOAD COMMAND
4544 7332 CLA CLL CML RTR /MAYBE EXPECTED STATUS
4545 3144 DCA GDREG2 /SETUP COMPARE REGISTER
4546 4444 PDSTAT /READ STATUS
4547 4447 DSKSKP /CHECK FOR SKIP
4550 5361 JMP NDIN /CHECK FOR NOT DONE
4551 7330 CLA CLL CML RAR /EXPECTED STATUS
4552 3144 DCA GDREG2 /SETUP COMPARE REGISTER
4553 4444 PDSTAT /READ STATUS
4554 1104 TAD K4000 /ADD IN FUDGE FACTOR
4555 7640 SZA CLA /O,K,????
4556 2336 ISZ DIN /ERROR!!!!
4557 2336 ISZ DIN
4560 5736 JMP I DIN /EXIT
4561 1105 NDIN, TAD K6000
4562 7640 SZA CLA /SKIP IF NO ERROR
4563 5356 JMP ,+5 /ERROR EXIT
4564 5736 JMP I DIN /EXIT
/
4600 PAGE
/
/MANUAL FUNCTION TEST
/LOAD ADDRESS 0201 OR "MANUAL".
/SET SWITCHES TO FUNCTION
/PRESS START
/MACHINE SHOULD HALT
/SET SWITCHES TO DISK ADDRESS
/PRESS START
/MACHINE SHOULD HALT
/SET SWITCHES TO COMPLEMENT DATA PATTERN
/PRESS START
/MACHINE SHOULD HALT
/SET SWITCHES TO 0000
/PRESS START
/IN CASE OF FAILURES USE NORMAL SCOPE SWITCHES
/IF LOOP IS DESIRED USE NORMAL SCOPE SWITCHES
/
4600 7604 MANUAL, LAS
4601 0307 AND K7707 /MASK
4602 3135 DCA TCNTR1 /SAVE FUNCTION
4603 7340 CLA CLL CMA
4604 3132 DCA REGD /SETUP FOR ONE PASS
4605 6224 RIF /USE CURRENT FIELD
4606 1135 TAD TCNTR1
4607 3135 DCA TCNTR1 /ACTUAL FUNCTION

```

```

4610 1135 TAD TCNTR1
4611 0077 AND K0006 /MASK DISK DRIVE
4612 3070 DCA DRIVNO /ACTUAL DRIVE
4613 7402 HLT /WAIT FOR DISK ADDP. IN SWITCHES
4614 7604 LAS
4615 3136 DCA TCNTR2 /SAVE DISK ADDRESS
4616 7402 HLT /WAIT FOR COMPLEMENT DATA
4617 7604 LAS
4620 3137 DCA TCNTR3 /SAVE IT
4621 7402 HLT /WAIT FOR OPERATOR TO CONTINUE
4622 1137 TAD TCNTR3
4623 4430 FILBUF /FILL BUFFER WITH DATA
4624 7300 THANS. CLA CLL
4625 1135 TAD TCNTR1 /GET FUNCTION
4626 0106 AND K7000 /MASK
4627 1105 TAD K6000
4630 7630 SZL CLA /WAS IT A READ
4631 7340 CLA CLL CMA /NO. SET A FLAG
4632 3140 DCA TCNTR4 /READ FLAG
4633 1135 TAD TCNTR1 /GET FUNCTION
4634 0106 AND K7000 /MASK
4635 1114 TAC K5000
4636 7640 SZA CLA /WAS IT A SEEK
4637 5247 JMP NTSEK /NOT A SEEK
4640 1135 TAD TCNTR1 /YES
4641 3151 DCA CMREG /SETUP COMMAND
4642 1136 TAD TCNTR2 /DISK ADDRESS
4643 4423 SEEK /SEEK ONLY
4644 4705 THANT /TEXT POINTER
4645 5303 JMP THANE /ERROR, SKIP OR STATUS
4646 5302 JMP THANOK /TO HANDLER
4647 1135 NTSEK. TAD TCNTR1 /GET FUNCTION
4650 0100 AND K0007 /MASK
4651 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
4652 1135 TAD TCNTR1 /FUNCTION
4653 3151 DCA CMREG /SETUP COMMAND
4654 1136 TAD TCNTR2 /DISK ADDRESS
4655 3463 DCA I XLOTRK /SETUP ADDRESS WORD IN BUFFER
4656 1140 TAD TCNTR4 /GET READ FLAG
4657 7650 SNA CLA /WAS IT A READ
4660 4431 KILBUF /YES. CLEAR BUFFER
4661 1136 TAD TCNTR2 /GET DISK ADDRESS
4662 4425 DISKGO /DISK GO
4663 4705 THANT /TEXT POINTER
4664 5303 JMP THANE /ERROR
4665 1140 TAD TCNTR4 /GET READ FLAG
4666 7640 SZA CLA /WAS IT A READ
4667 5302 JMP THANOK /WAS A WRITE, TO HANDLER
4670 1151 TAD CMREG /GET LAST COMMAND
4671 0014 AND K0100 /MASK OUT HALF BIT
4672 7650 SNA CLA /WAS IT HALF BLOCK TRANSFERS
4673 5300 JMP .+5 /NO. COMPARE WHOLE BLOCK
4674 1137 TAD TCNTR3 /GET GOOD WORD POINTER
4675 4426 HAFCHK /CHECK FOR HALF BLOCK
4676 5302 JMP THANOK /O.K. NO ERRORS

```

```

4677 5303 JMP THANE /DATA ERROR
4700 1137 TAD TCNTR3 /WAS A READ
4701 4427 FIGURE /WORD BY WORD COMPARE OF DATA
4702 4437 THANOK. NEPROR /NO ERRORS
4703 4440 THANE. ERROR /ERROR IN FUNCTION SELECTED
4704 4624 THANS /SCOPE LOOP POINTER
4705 5373 THANT. /TEXT POINTER
/
4706 5224 JMP THANS / LOOP
/
4707 7707 X7707. 7707
/
/ROUTINE TO CHECK THE WRITE PROTECT FUNCTION
/WHEN IT IS SET UNDER PROGRAM CONTROL
/NOTE: NO SCOPE LOOPS ARE AVAILABLE FOR THIS TEST
/
4710 7604 AUTPRC. LAS /GET THE SWITCHES
4711 7104 CLL RAL
4712 0077 AND K0006 /MASK DRIVE NUMBER
4713 3070 DCA DRIVNO /SAVE DRIVE NUMBER
4714 7344 CLA CLL CMA RAL
4715 3133 DCA REG1 /SETUP REPEAT POINTER
4716 3132 DCA REG0
4717 1112 TAD K2525 /DATA PATTERN TO WRITE
4720 4430 FILBUF /FILL OUTBOUND BUFFER
4721 1070 TAD DRIVNO
4722 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
4723 3463 DCA I XLOTRK /SETUP ADDRESS WORD IN BUFFER
4724 1114 TAD K5000 /WRITE ALL FUNCTION
4725 3151 DCA CMREG /SETUP COMMAND
4726 4425 DISKGO /WRITE ALL TO SECTOR 0
4727 4775 TAPROT /TEXT POINTER
4730 5373 JMP APERR /ERROR. STATUS
4731 1102 APRI. TAD K2000 /FUNCTION WRITE PROTECT
4732 1070 TAD DRIVNO /CURRENT DRIVE
4733 4450 LUCMD /LOAD COMMAND REGISTER
4734 4452 LDADD /LOAD AND GO
4735 4444 RDSTAT /READ STATUS REGISTER
4736 7640 SZA CLA /SHOULD BE 0000 ???
4737 5352 JMP APRI /ERROR. STATUS
4740 4431 KILBUF /CLEAR OUTBOUND BUFFER
4741 1070 TAD DRIVNO
4742 3464 DCA I XHITRK /SETUP ADDRESS WORD IN BUFFER
4743 1114 TAD K5000 /WRITE ALL FUNCTION
4744 3151 DCA CMREG /SETUP COMMAND REGISTER
4745 4425 DISKGO /WRITE ALL TO SECTOR 0
4746 4775 TAPROT /TEXT POINTER
4747 7000 NUP
4750 7326 CLA CLL CML RIL /MAKE EXPECTED STATUS
4751 1012 TAD K0020 /SETUP COMPARE REGISTER
4752 3144 APRI. DCA GDREG2
4753 1170 TAD K5300
4754 3375 DCA TAPROT /SETUP TEXT POINTER
4755 1147 TAD STREG /GET STATUS READ
4756 4442 ACCMPI /CHECK RESULTS

```

```

4757 7610          SKP CLA          /STATUS O.K.
4760 5373          JMP APERR          /ERROR, WRITE PROTECT
4761 7301          CLA CLL IAC        /ENABLE CLEAR CONTROL
4762 4453          CLRALL           /CLEAR CONTROL
4763 1017          TAD K1000         /FUNCTION READ ALL
4764 3151          DCA CHREG         /SETUP COMMAND
4765 4425          DISKGO           /READ ALL SECTOR 0
4766 4775          TAPROT          /TEXT POINTER
4767 5373          JMP APERR          /ERROR
4770 1112          TAD K2525         /EXPECTED PATTERN
4771 4427          FIGURE           /CHECK DATA READ
4772 4437          NERRDP           /ALL O.K., DO ONE MORE TIME
4773 4440          APERR, ERRDP     /ERROR, WRITE PROTECT
4774 4731          TAPROT, APR1
4775 0000          TAPROT, 0000       /TEXT POINTER
4776 7402          APHLT1, HLT       /SUCCESSFUL WRITE PROTECT
4777 5310          JMP AUTPRD        /REPEAT

/
PAGE
/
/SUBROUTINE FOR "ERRORS," SCOPE LOOPS, AND
/ERROR TYPEDUTS.
/
5000 0000          ERRO, 0
5001 7300          CLA CLL
5002 1600          TAD I ERRO          /GET RESTART ADDRESS
5003 3175          DCA RESTRT        /STORE
5004 7604          LAS              /GET SWITCH 0
5005 7700          SMA CLA          /IS IT SCOPE LOOP
5006 5217          JMP ERRA1        /NO, CONTINUE
5007 7604          LAS              /GET SWR2
5010 7000          RTL
5011 7710          SPA CLA          /INHIBIT BELL????
5012 5215          JMP ,+3          /YES
5013 1354          TAD K0207
5014 4438          TYPE
5015 1600          TAD I ERRO
5016 5755          JMP I ESCOPE        /CHECK FOR BELL
5017 1600          ERRA1, TAD I ERRO
5020 3350          DCA RETRN2       /STORE FOR RETURN
5021 2200          ISZ ERRO
5022 7301          CLA CLL IAC
5023 1200          TAD ERRO
5024 3351          DCA INHIBT       /NEXT TEST POINTER
5025 4462          CRLF            /STORE FOR SPECIAL RETURN
5026 4462          CRLF
5027 1600          TAD I ERRO
5030 0100          AND K0007        /GET TEXT POINTER
5031 1365          TAD HEDTAD       /MASK 9=11
5032 3234          DCA ,+1          /MAKE ERROR HEADER TAD
5033 7402          HLT
5034 3236          DCA ,+2          /MODIFIED HEADER TAD
5035 4457          PRINTER         /MODIFIED HEADER POINTER
5036 7402          HLT
5037 4462          CRLF

```

```

5040 4457          PRINTER         /PRINT PCI
5041 5750          TEXPC
5042 7340          CLA CLL CHA
5043 1200          TAD ERRO          /GET PC POINTER
5044 4460          OCTEL           /PRINT PC STORED
5045 1600          TAD I ERRO
5046 7104          CLL RAL          /GET TEXT POINTER
5047 7420          SKL
5050 5264          JMP NTGD        /NOT GD1 REGISTER

5051 3200          DCA ERRO
5052 4457          PRINTER         /PRINT GD1
5053 5752          TEXGO
5054 1200          TAD ERRO
5055 7700          SMA CLA          /WAS IT A 6 BIT OCTAL BYTE
5056 5201          JMP ,+3          /NO
5057 1143          TAD GDREG1      /GET DATA
5060 4461          TAD OCT         /PRINT TWO OCTAL
5061 1144          TAD GDREG2
5062 4460          OCTEL           /PRINT FOUR OCTAL
5063 7610          SKP CLA
5064 3200          NTGD, DCA ERRO
5065 1200          TAD ERRO          /GET TEXT POINTER
5066 7104          CLL RAL
5067 7420          SWL
5070 5301          JMP NTCRC       /PRINT CR1
5071 3200          DCA ERRO
5072 4457          PRINTER
5073 5754          TEXCR
5074 1145          TAD CRREG1
5075 4461          TAD OCT         /PRINT
5076 1146          TAD CRREG2
5077 4460          OCTEL           /PRINT FOUR OCTAL
5100 7610          SKP CLA
5101 3200          NTCRC, DCA ERRO
5102 1361          TAD XTEXT
5103 1364          DCA PCNTR2
5104 1362          TAD XREG
5105 3010          DCA AUTO10
5106 1115          TAD K7771
5107 3363          DCA PCNTR1
5110 1200          STRAUT, TAD ERRO /COUNTER FOR # OF HEADS
5111 7500          SMA
5112 5346          JMP NOTEX       /GET TEXT POINTER
5113 7104          CLL RAL
5114 3200          DCA ERRO
5115 1364          TAD PCNTR2       /NOT THIS ONE
5116 2364          ISZ PCNTR2
5117 2364          ISZ PCNTR2
5120 3372          DCA ,+2
5121 4457          PRINTER         /GET TEXT MESSAGE POINTER
5122 7402          HLT
5123 1410          TAD I AUTO10
5124 4460          OCTEL           /STORE FOR PRINTER

```

```

5125 236J AGAIN, ISZ PCNTR1
5126 5310 JMP STRAUT
5127 7604 LAS
5130 700b RTL
5131 001b AND K0400
5132 7650 SNA CLA
5133 5342 JMP ERHLT9
5134 7630 SZL CLA
5135 5340 JMP ,+3
5136 1357 TAD INHIB1
5137 575b JMP I ESCOPE
5140 135b TAD RETRN2
5141 575b JMP I ESCOPE
5142 7492 ERHLT9, HLT
5143 4760 JMS I XGIREG
5144 575b JMP I RETRN2
5145 5264 JMP NTGD
5146 7104 NOTEX, CLL RAL
5147 3200 DCA ERRO
5150 2364 ISZ PCNTR2
5151 2364 ISZ PCNTR2
5152 2010 ISZ AUTO10
5153 5325 JMP AGAIN

/
5154 0207 K0207, 0207
5155 5470 ESCOPE, SCOPE
5156 0000 RETRN2, 0
5157 0000 INHIB1, 0
5160 8527 XGTREG, GTREG
5161 575b XTEXT, TEXT
5162 014b XREG, CRREG2
5163 0000 PCNTR1, 0
5164 0000 PCNTR2, 0
5165 136b HEDTAD, TAD HEDLST
5166 6615 HEDLST, ERTX1
5167 6630 ERTX2
5170 6644 ERTX3
5171 6662 ERTX4
5172 6672 ERTX5
5173 6704 ERTX6
5174 6716 ERTX7
5175 672b ERTX8

/ PAGE
/
/ SUBROUTINE TO WAIT FOR INTERRUPTS
/ IF INTERRUPT OCCURS GO BACK +1
/
5200 0000 IONAT, 0
5201 7480 SNA
5202 1122 TAD K7740
5203 3221 DCA COMP1
5204 7240 CLA CMA
5205 3231 DCA COMP2
5206 6001 ION

/ FAST OR SLOW
/ GET SLOW CONSTANT
/ SETUP COUNTER
/ SETUP COUNTER
/ TURN IT ON

```

```

5207 2231 ISZ COMP2
5210 5207 JMP ,+1
5211 2221 ISZ COMP1
5212 5207 JMP ,+3
5213 6002 IOF
5214 5600 JMP I IONAT
5215 2200 INTADD, ISZ IONAT
5216 4441 DSKSKP
5217 7402 ERHLT1, HLT
5220 5600 JMP I IONAT

/
/ ROUTINE TO COMPARE AC TO GOREG2
/
5221 0000 COMP1, 0
5222 315b DCA ACREG
5223 115b TAD ACREG
5224 7041 CIA
5225 1144 TAD GOREG2
5226 7640 SZA CLA
5227 2221 ISZ COMP1
5230 5621 JMP I COMP1

/
/ ROUTINE TO COMPARE CRREG1 AND CRREG2 TO
/ GDREG1 AND GDREG2,
/
5231 0000 COMP2, 0
5232 7300 CLA CLL
5233 1143 TAD GDREG1
5234 011b AND K0017
5235 7041 CIA
5236 1145 TAD CRREG1
5237 7640 SZA CLA
5240 5245 JMP CRERR
5241 1146 TAD CRREG2
5242 7041 CIA
5243 1144 TAD GDREG2
5244 7640 SZA CLA
5245 2231 CRERR, ISZ COMP2
5246 5631 JMP I COMP2

/
/ ROUTINE TO WAIT FOR 500 NS.
/
5247 0000 WTISZ, 0
5250 7300 CLA CLL
5251 1122 TAD K7740
5252 3221 DCA COMP1
5253 3231 DCA COMP2
5254 2231 ISZ COMP2
5255 5254 JMP ,+1
5256 2221 ISZ COMP1
5257 5254 JMP ,+3
5260 5647 JMP I WTISZ

/ GET TIME CONSTANT
/ EXIT
/
/ ROUTINE TO WAIT FOR DISK SKIPS
/

```

```

5261 0000 SKWAT, 0
5262 730C CLA CLL
5263 1122 TAD K7740 /GET TIME CONSTANT
5264 3221 DCA COMP1
5265 3231 DCA COMP2
5266 4447 DSKSKP 2 5 2 2 /DSKP "DISK SKIP IOT"
5267 7610 SKP CLA /NO SKIP OCCURRED YET
5270 5276 JHP ,+6 /GOT THE SKIP
5271 2231 ISZ COMP2
5272 5266 JHP ,+4
5273 2221 ISZ COMP1
5274 5266 JHP ,+6
5275 7610 SKP CLA /NO SKIP OCCURRED
5276 2261 ISZ SKWAT
5277 5661 JMP I SKWAT /EXIT

/SUBROUTINE TO READ STATUS REGISTER
/
5300 0000 NDST, 0
5301 6745 IOT5, DRST /READ STATUS IOT
5302 7410 SKP
5303 7402 ERHLT5, HLT /SKIP TRAP
5304 3147 DCA STREG /SAVE RESULTS
5305 1147 TAD SIREG
5306 5700 JMP I NDST /EXIT

/SUBROUTINE TO LOAD CURRENT ADDRESS REGISTER
/
5307 0000 LDCA, 0
5310 3154 DCA ADREG /SAVE IN ADDRESS
5311 1154 TAD ADREG
5312 3153 DCA CAREG /SETUP INITIAL CURRENT ADDRESS
5313 1154 TAD ADREG
5314 6744 IOT4, DLCA /LOAD CURRENT ADDRESS IOT
5315 5707 JMP I LDCA /EXIT

5316 7402 ERHLT4, HLT /SKIP TRAP
/
/SUBROUTINE TO LOAD TRACK ADDRESS REGISTER
/
5317 0000 LDAD, 0
5320 3152 DCA DAREG /SAVE OUTBOUND DATA
5321 1152 TAD DAREG
5322 6743 IOT3, DLG /LOAD DTSK ADDRESS REGISTER
5323 5717 JHP I LOAD /EXIT
5324 7402 ERHLT3, HLT /SKIP TRAP
/
/SUBROUTINE TO LOAD COMMAND REGISTER
/
5325 0000 LDCM, 0
5326 3151 DCA CMREG /SAVE OUTBOUND DATA
5327 1151 TAD CMREG
5330 6746 IOT6, DLCC /LOAD COMMAND REGISTER

```

```

5331 5725 JMP I LDCM /EXIT
5332 7402 ERHLT6, HLT /SKIP TRAP
/
/SUBROUTINE TO ISSUE "DSKP" DISK SKIP IOT
/
5333 0000 DSKP, 0
5334 6741 IOT1, DSKP /DISK SKIP IOT
5335 7410 SKP /DID NOT SKIP
5336 2333 ISZ DSKP
5337 5733 JMP I DSKP /EXIT

/SUBROUTINE TO ISSUE "DCLR" CLEAR IOT
/
5340 0000 CLDR, 0
5341 6742 IOT2, DCLR /DCLR "CLEAR IOT"
5342 5740 JMP I CLDR /EXIT
5343 7402 ERHLT2, HLT /SKIP TRAP
/
/SUBROUTINE TO ISSUE "DMAN" MAINTENANCE IOT
/
5344 0000 LDMN, 0
5345 6747 IOT7, DMAN /"DMAN" MAINTENANCE IOT
5346 5744 JMP I LDMN /EXIT
5347 7402 ERHLT7, HLT /SKIP TRAP
/
/SUBROUTINE TO SHIFT, THEN READ DISK ADDRESS
/INTO DATA BUFFER, 12 SHIFTS
/
5350 0000 RDAD, 0
5351 7300 CLA CLL
5352 1130 TAD M12
5353 3134 DCA SBCNT1
5354 7330 CLA CLL CML RAR /SET MAIN(1) ENABLE BIT
5355 4455 LDMAN /LOAD MAINTENANCE
5356 7010 RAR
5357 4455 LDMAN /LOAD MAINTENANCE
5360 7300 CLA CLL
5361 1015 TAD K0200 /SHIFT TRACK ADDRESS BIT
5362 4455 LDMAN /LOAD MAINTENANCE IOT
5363 2134 ISZ SBCNT1
5364 5362 JMP ,+2 /SHIFT 12 BITS
5365 7300 CLA CLL
5366 1012 TAD K0020
5367 4455 LDMAN /READ DATA BUFFER
5370 3152 DCA DAREG /SAVE RESULTS
5371 1152 TAD DAREG
5372 5750 JMP I RDAD /EXIT

PAGE
/
/SUBROUTINE TO READ DATA BUFFER TO AC
/
5400 0000 RDRF, 0
5401 7330 CLA CLL CML RAR

```

```

5402 4455 LDMAI
5403 1012 TAD K0020
5404 4455 LDMAI /LOAD MAINTENANCE
5405 3150 DCA DBREG
5406 1150 TAD DBREG
5407 1155 DCA DTREG
5410 1155 TAD DTREG
5411 5000 JMP I DRBF /EXIT
/
/SUBROUTINE TO SHIFT COMMAND REGISTER TO
/ DATA BUFFER WHEN READ DATA BUFFER
/
5412 0000 RDCM, 0
5413 7300 CLA CLL
5414 1130 TAD N12
5415 3134 DCA SBCNT1 /12 BIT SHIFT
5416 7330 CLA CLL CML RAR
5417 4455 LDMAI /LOAD MAINTENANCE
5420 7010 RAR
5421 4455 LDMAI /LOAD MAINTENANCE
5422 7300 CLA CLL
5423 1016 TAD K0400 /ENABLE BIT FOR SHIFT COMMAND
5424 4455 LDMAI /LOAD AND GO
5425 2134 ISZ SBCNT1
5426 5224 JMP ,+2 /SHIFT 12
5427 7300 CLA CLL
5430 1012 TAD K0020 /ENABLE READ BUFFER
5431 4455 LDMAI /LOAD AND GO
5432 3151 DCA CMREG /SAVE IT
5433 1151 TAD CMREG
5434 5612 JMP I RDCM /EXIT
/
/ROUTINE TO ZERO WORK BUFFER
/
5435 0000 KLBUF, 0
5436 7340 CLA CLL CMA
5437 1067 TAD BGNBUF /START OF BUFFER -1
5440 3010 DCA AUTO10 /SETUP AUTO INDEX
5441 1123 TAD K7400
5442 3154 DCA DATCNT /SETUP COUNTER
5443 3410 DCA I AUTO10 /CLEAR BUFFER
5444 2154 ISZ DATCNT /UPDATE COUNTER
5445 5243 JMP ,+2 /NOT ALL CLEARED YET
5446 5635 JMP I KLBUF /BUFFER CLEARED
/
/ROUTINE TO FILL THE WORK BUFFER WITH
/ THE COMPLEMENT DATA THATS IN THE AC.
/
5447 0000 FLBUF, 0
5450 3165 DCA SAVDAT /SAVE DATA WORD
5451 7340 CLA CLL CMA
5452 1067 TAD BGNBUF /START OF BUFFER -1
5453 3010 DCA AUTO10 /SETUP AUTO INDEX
5454 1124 TAD K7400
5455 3164 DCA DATCNT /SETUP COUNTER

```

```

5456 1165 LPDAT, TAD SAVDAT /GET FIRST WORD
5457 3410 DCA I AUTO10 /STORE IN BUFFER
5460 1165 TAD SAVDAI /GET SECOND WORD
5461 7040 CMA /COMPLEMENT IT
5462 3410 DCA I AUTO10 /STORE IN BUFFER
5463 2154 ISZ DATCNT /UPDATE COUNTER
5464 5256 JMP LPDAT /MORE WORDS TO GO
5465 1101 TAD K1234
5466 3410 DCA I AUTO10 /MAKE WORD IN BUFFER + 1
5467 5647 JMP I FLBUF /BUFFER FULL
/
/ROUTINE TO CHECK FOR WAIT AND RECALIBRATE
/
5470 3326 SCOPE, DCA TOTST /SAVE SCOPE LOOP POINTER
5471 7604 LAS /GET SWITCH 7
5472 0012 AND K0020 /MASK
5473 7640 SZA CLA /WAIT LOOP?
5474 4433 WATISZ /YES
5475 7604 LAS /GET SWITCH 6
5476 0013 AND K0040 /MASK
5477 7656 SNA CLA /IS IT CLEAR DISK
5500 5322 JMP NOCLP /NO, DON'T
5501 7301 CLA CLL IAC /ENABLE CLEAR CONTROL
5502 4453 CLRALL /CLEAR CONTROL
5503 1151 TAD CMREG /GET LAST COMMAND
5504 0325 AND K7577 /MASK OUT SET DONE
5505 4456 LDCMD /LOAD COMMAND
5506 7326 CLA CLL CML RIL /ENABLE RECALIBRATE
5507 4453 CLRALL /RECALIBRATE
5510 4432 SKPWAT /WAIT FOR FIRST DONE
5511 7000 NOP
5512 1151 TAD CMREG /LAST COMMAND
5513 1015 TAD K0200
5514 4450 LDCMD /LOAD COMMAND
5515 4432 SKPWAT /WAIT FOR SECOND DONE
5516 7000 NOP
5517 1151 TAD CMREG
5520 0325 AND K7577 /MASK SET DONE
5521 3151 DCA CMREG
5522 7301 CLA CLL IAC /ENABLE CLEAR CONTROL
5523 4453 CLRALL /CLEAR CONTROL
5524 5726 JMP I TOTST /GO TO TEST
/
5525 7577 K7577, 7577
5526 0000 TOTST, 0
/
/ROUTINE TO GET ALL REGISTERS
/ (NOTE: THIS ROUTINE WILL CAUSE ONE MAINTENANCE
/ DATA BREAK TO LOCATION 0 IF THE LAST PREVIOUS
/ FUNCTION EXECUTED WAS A READ DATA BREAK.)
/
5527 0000 GTRREG, 0
5530 7604 LAS /GET SWITCH 8
5531 0011 AND K0010 /MASK
5532 7656 SNA CLA /WAS IT GET ALL REGISTERS

```

```

5533 5727      JMP I  GTREG      /NO. GO BACK
5534 2227      ISZ   GTREG      /YES, UPDATE POINTER
5535 4444      RDSTAT      /READ STATUS
5536 4456      RDBUF      /READ LOWER BUFFER
5537 7300      CLA CLL      /SET CA TO 0 FOR BREAK
5540 4451      LDCUP      /ENABLE SHIFT TO LOWER BUFFER
5541 7332      CLA CLL CML RTR /BREAK IF LAST BREAK WAS A READ
5542 4455      LDMA      /READ CRC
5543 4454      RDCRC      /READ TRACK
5544 4446      RDADD      /READ COMMAND
5545 4445      RUCND      /ENABLE CLEAR CONTROL
5546 4462      CRLF      /CLEAR CONTROL
5547 7301      CLA CLL IAC
5550 4453      CLRALL
5551 1124      TAD    K7600
5552 5727      JMP I  GTREG      /EXIT

```

/ROUTINE TO SEND DRIVES OR AN OVERLAP SEEK

```

5553 0000      DOUT,  0
5554 3327      DCA   GTREG      /SAVE ADDRESS
5555 7004      RAL
5556 1070      TAD   DRVNO      /GET CURRENT DRIVE
5557 4450      LDCMD      /LOAD COMMAND REGISTER
5560 1151      TAD   CMREG      /GET LAST COMMAND ISSUED
5561 1103      TAD   K3000      /ADD IN SEEK ONLY FUNCTION
5562 1157      TAD   HMEMA      /ADD IN CURRENT FIELD
5563 4450      LDCMD      /LOAD COMMAND REGISTER
5564 1327      TAD   GTREG      /GET SAVED ADDRESS
5565 4452      LDADD      /LOAD AND GO
5566 4447      DSKSKP      /WAIT FOR FIRST DUNK FLAG
5567 5366      JMP    ,*1      /HANG IF NO SKIP
5570 5753      JMP I  DOUT      /DISK IS OUT

```

5600

PAGE

/ROUTINE TO READ OR WRITE ON DISK
/RETURN +1 SKIP OR STATUS ERROR
/RETURN +2 O.K.

```

5600 0000      DISK,  0
5601 3254      DCA   SAVTRK      /SAVE TRACK ADDRESS
5602 7340      CLA CLL CMA
5603 3173      DCA   SOFERR      /SET CRC ERROR FLAG
5604 1600      TAD I  DISK      /GET TEXT POINTER
5605 3174      DCA   SAVPCT      /SAVE IT
5606 2200      ISZ   DISK      /UPDATE POINTER
5607 1151      TAD   CMREG      /GET COMMAND
5610 0255      AND   K7501      /MASK OFF
5611 1157      TAD   HMEMA      /CURRENT FIELD
5612 1070      TAD   DRVNO      /CURRENT DRIVE
5613 4450      LDCMD      /LOAD COMMAND
5614 1067      TAD   BGNBUF      /GET BEGINNING OF BUFFER
5615 4451      LDCUR      /LOAD CURRENT ADDRESS
5616 1254      TAD   SAVTRK      /GET TRACK + SECTOR

```

```

5617 4452      LDADD      /LOAD AND GO
5620 4432      SKPAT      /WAIT FOR DISK SKIP
5621 5234      JMP    SKPERR      /ERRPR, NO SKIP
5622 7330      CLA CLL CML RAR /EXPECTED STATUS
5623 3144      DCA   GDRLG2      /SETUP COMPARE REGISTER
5624 4444      RDSTAT      /READ STATUS
5625 1104      TAD   K4000
5626 7640      SZA CLA      /WAS STATUS 4000
5627 5236      JMP    STAERR      /ERROR, STATUS
5630 1167      TAD   K5373      /TEXT POINTER
5631 2200      ISZ   DISK      /UPDATE FOR GOOD RETURN
5632 3574      RETRN, DCA I SAVPCT /STORE IN TEXT POINTER
5633 5600      JMP I  DISK      /EXIT
5634 1156      SKPERR, TAD K0306 /SKIP TEXT POINTER
5635 5232      JMP    RETRN      /EXIT
5636 1147      STAERR, TAD STREG /GET STATUS JUST READ
5637 0011      AND   K0010      /MASK OUT CRC ERRORS
5640 7650      SNA CLA      /WERE THERE ANY
5641 5252      JMP    HRDERR      /NO, OTHERS
5642 7300      CLA CLL
5643 1151      TAD   CMREG      /GET LAST COMMAND
5644 0106      AND   K7000      /MASK FUNCTION
5645 1105      TAD   K6000      /ADD IN FUDGE FACTOR
5646 7630      SZL CLA      /WAS IT A READ ALL OR READ
5647 5252      JMP    HRDERH      /NO, MUST BE A WRITE
5650 3173      DCA   SOFERR      /SET CRC ERROR FLAG
5651 5230      JMP    RLTRN -2      /GO CHECK DATA OR RETURN
5652 1170      HRDERH, TAD K3300
5653 5232      JMP    RETRN      /EXIT

```

5654 0000

SAVTRK, 0

K7501, 7501
/ROUTINE TO COMPARE WORDS IN BUFFER TO
/KNOWN DATA PATTERN IN THE AC.

```

5656 0000      FIGURE, 0
5657 3144      DCA   GDREG2      /SAVE FOR ERROR PRINTER
5660 1067      TAD   BGNBUF      /GET START OF BUFFER
5661 3154      DCA   ADREG      /SAVE FOR ERROR PRINTER
5662 1151      TAD   CMREG      /GET DISK NO. AND EXT. BIT
5663 0100      AND   K0007      /MASK THEM
5664 7041      CIA
5665 1554      TAD I  ADREG      /GET FIRST TRACK WORD
5666 7650      SNA CLA      /WAS IT O.K. ?
5667 5273      JMP    ,+4      /YES, CHECK NEXT TRACK WORD
5670 1151      TAD   CMREG      /GET DISK NO. AND EXT. BIT
5671 0100      AND   K0007      /MASK THEM
5672 5343      JMP    DTERR      /DATA ERROR
5673 2154      ISZ   ADREG      /UPDATE ADDRESS
5674 1554      TAD I  ADREG      /GET SECOND WORD
5675 7041      CIA
5676 1152      TAD   DAREG      /COMPARE TO ADDRESS
5677 7650      SNA CLA      /WAS SECOND TRACK WORD O.K.
5700 5303      JMP    ,+3      /YES, NOW CHECK DATA

```

```

5701 1152          TAD   DARLG          /GET GOOD INFO
5702 5343          JMP   DTERR          /DATA ERROR
5703 7326          CLA CLL CML RTL
5704 1123          TAD   K7400
5705 3164          DCA   DATCNT          /SETUP COUNTER
5706 2154          LPPFIG, ISZ  ADREG          /UPDATE ADDRESS
5707 1554          TAD I  ADREG          /GET DATA WORD
5710 7041          CIA
5711 1144          TAD   GDREG2          /COMPARE TO GOOD ONE
5712 7640          SZA CLA          /WAS WORD O.K.?
5713 5344          JMP   DTERR +1          /NO, DATA ERROR
5714 1144          TAD   GDREG2          /GET GOOD DATA
5715 7040          CMA
5716 3144          DCA   GDREG2          /IT IS A COMPLEMENT DATA PATTERN
5717 2164          ISZ  DATCNT          /UPDATE BUFFER COUNTER
5720 5306          JMP   LPPFIG          /MORE TO CHECK
5721 2154          ISZ  ADREG          /UPDATE ADDRESS
5722 1101          TAD   K1234
5723 7041          CIA
5724 1554          TAD I  ADREG          /GET WORD IN BUFFER +1
5725 7650          SNA CLA          /WAS IT O.K.
5726 5331          JMP   ,+3          /YES ALL DATA O.K.
5727 1101          TAD   K1234
5730 5343          JMP   DTERR          /WORD LOST IN BUFFER +1
5731 7330          CLA CLL CML RAR          /EXPECTED STATUS
5732 3144          DCA   GDREG2          /SETUP COMPARE REGISTER
5733 1173          TAD   SOFERN          /GET CRC ERROR FLAG
5734 7640          SZA CLA          /WAS IT SET
5735 5656          JMP I  FGURE          /NO THE BUFFER IS O.K.
5736 7340          CLA CLL CMA          /SETUP CRC FLAG
5737 3173          DCA   SOFERR          /RESET FLAG
5740 1170          TAD   K5300          /TEXT "ESS"
5741 3574          DCA I  SAVPCT          /SETUP TEXT POINTER
5742 7330          CLA CLL CML RAR          /EXPECTED STATUS
5743 3144          DTERR, DCA   GDREG2          /SETUP COMPARE
5744 1554          TAD I  ADREG          /GET BAD WORD
5745 3155          DCA   DTREG          /SAVE FOR PRINTER
5746 2256          ISZ  FGURE          /UPDATE FOR ERROR RETURN
5747 5656          JMP I  FGURE

/
5750 2003          TEXPC, TEXT  "PCI"
5751 7200
5752 0704          TEXGD, TEXT  "GDI"
5753 7200
5754 0322          TEXCR, TEXT  "CRI"
5755 7200
5756 2324          TEXST, TEXT  "STI"
5757 7200
5760 0402          TEXDR, TEXT  "DRI"
5761 7200
5762 0315          TEXCM, TEXT  "CHI"
5763 7200
5764 0401          TEXCA, TEXT  "DAI"
5765 7200
5766 0301          TEXCA, TEXT  "CAI"

```

```

5767 7200
5770 0104          TEXAD, TEXT  "ADI"
5771 7200
5772 0424          TEXDT, TEXT  "DTI"
5773 7200

/
PAGE
/
/SUBROUTINE TO SHIFT CRC REGISTER TO DATA
/BUFFER THEN READ IT.
/
6000 0000          RDCR,  0
6001 7300          CLA CLL
6002 1130          TAD   *12
6003 3134          DCA   SBCNT1          /12 SHIFTER
6004 7330          CLA CLL CML RAR          /LOAD MAINTENANCE
6005 4455          LDMAN
6006 7010          RAR
6007 4455          LDMAN          /LOAD MAINTENANCE
6010 7010          RAR
6011 4455          LDMAN          /LOAD AND GO
6012 2134          ISZ  SBCNT1
6013 5211          JMP   ,+2          /12 BIT SHIFT
6014 7300          CLA CLL
6015 1012          TAD   K0020          /ENABLE READ BUFFER
6016 4455          LDMAN
6017 3146          DCA   CRREG2          /SAVE IT
6020 1130          TAD   *12
6021 3134          DCA   SBCNT1          /12 BIT SHIFTER
6022 7332          CLA CLL CML RTR          /LOAD MAINTENANCE
6023 4455          LDMAN
6024 7010          RAR          /LOAD AND GO
6025 4455          LDMAN
6026 2134          ISZ  SBCNT1
6027 5225          JMP   ,+2          /12 BIT SHIFT

6030 7300          CLA CLL
6031 1012          TAD   K0020          /ENABLE READ BUFFER
6032 4455          LDMAN
6033 0116          AND   K0011
6034 3145          DCA   CRREG1          /SAVE OTHER HALF
6035 5600          JMP I  RDCR          /EXIT

/
/SUBROUTINE TO PRINT TWO OCTAL
/
6036 0000          TOCT,  0
6037 3134          DCA   SBCNT1          /SAVE AC
6040 1134          TAD   SBCNT1
6041 7010          RAR
6042 7012          RTR
6043 0100          AND   K0007
6044 1264          TAD   K0260
6045 4416          TYPE
6046 1134          TAD   SBCNT1          /PRINT FIRST BYTE

```



```

6047 0100 AND K0007
6050 1264 TAD K0260
6051 4436 TYPE /PRINT SECOND BIT
6052 5636 JMP I TUCT /EXIT

/
/
/ROUTINE TO DO CRLF
/
6053 0000 UPONE, 0
6054 7300 CLA CLL
6055 1262 TAD K0215
6056 4436 TYPE
6057 1263 TAD K0212
6060 4436 TYPE
6061 5653 JMP I UPONE

/
6062 0215 K0215, 0215
6063 0212 K0212, 0212
6064 0260 K0260, 0260
6065 0240 K0240, 0240

/
/ROUTINE TO PRINT FOUR OCTAL
/
6066 0000 FROCT, 0
6067 7006 RTL
6070 7006 RTL
6071 3253 DCA UPONE
6072 1131 TAD M4
6073 3236 DCA TUCT
6074 1253 TAD UPONE
6075 0100 AND K0007
6076 1264 TAD K0260
6077 4436 TYPE
6100 1253 TAD UPONE
6101 7006 RTL
6102 7006 RTL
6103 3253 DCA UPONE
6104 2236 ISZ TUCT
6105 5274 JMP ,=11
6106 1265 TAD K0240
6107 4436 TYPE
6110 5666 JMP I FROCT

/
/SUBROUTINE TO PRINT TEXT
/
6111 0000 PRN, 0
6112 7300 CLA CLL
6113 1711 TAD I PRN /GET POINTER

6114 2311 ISZ PRN
6115 3266 DCA FROCT
6116 1666 TAD I FROCT
6117 0110 AND K7700

```

```

6120 7450 SNA
6121 5345 JMP EXIT
6122 7500 SNA
6123 7026 CML
6124 7001 IAC
6125 7612 R1P
6126 7012 R1R
6127 7012 R1R
6130 4436 TYPE
6131 1666 TAD I FROCT
6132 0111 AND K0077
6133 7450 SNA
6134 5345 JMP EXIT
6135 1350 TAD K3740
6136 7500 SNA
6137 1347 TAD K4100
6140 1265 TAD K0240
6141 4436 TYPE
6142 2266 ISZ FROCT
6143 7300 CLA CLL
6144 5316 JMP PRN+5
6145 7300 EXIT, CLA CLL
6146 5711 JMP I PRN

/
6147 4100 K4100, 4100
6150 3740 K3740, 3740

/
/ROUTINE TO TYPE
/
6151 0000 PRINT, 0
6152 6046 ILS
6153 6041 T6F
6154 5153 JMP ,=1
6155 6042 TCF
6156 7200 CLA
6157 5751 JMP I PRINT

/
6200 PAGE

/
/ROUTINE TO RECALIBRATE SELECTED DRIVE OR
/SEEK ONLY POSITION IN AC ON SELECTED DRIVE.
/
6206 0000 RESTOR, 0
6201 7300 CLA CLL
6202 1600 TAD I RESTOR /GET TEXT POINTER
6203 3315 DCA SAVPC /SAVE FOR ERROR
6204 2200 ISZ RESTOR /UPDATE PC
6205 1200 TAD RESTOR /GET PC
6206 3215 DCA ONLY /SAVE FOR END OF SEEK ROUTINE
6207 1070 TAD DRIVNO /CURRENT DRIVE
6210 1157 TAD HOME%4 /CURRENT FIELD
6211 4450 LDCMD /LOAD COMMAND
6212 7326 CLA CLL CML RTL /ENABLE RECALIBRATE BIT
6213 4453 CLRALL /"RECALIBRATE"

```

```

6214 5232 / JMP CHECK /CHECK FOR ERRORS
/ ONLY, 4 /
6215 0000 DCA SAVIO /SAVE LOWER TRACK BITS
6216 3316 TAD I ONLY /GET TEXT POINTER
6217 1615 DCA SAVPC /SAVE FOR ERROR
6220 3315 ISZ ONLY /GET COMMAND
6221 7215 TAD CMREG /MASK OFF EXTENDED BIT
6222 1151 AND K0001 /CURRENT FIELD
6223 0072 TAD ROMEMA /CURRENT DRIVE
6224 1157 TAD DRIVNO /SEEK ONLY FUNCTION
6225 1070 TAD K3000 /LOAD COMMAND
6226 1103 LDCMD /GET POSITION
6227 4450 TAD SAVIO /LOAD AND GO
6230 1316 LDADD /WAIT FOR FIRST DONE FLAG
6231 4452 CHECK, SMP*AT /ERROR, NO SKIP
6232 4432 JMP SEKER1 /EXPECTED STATUS
6233 5313 CLA CLL CML RAR /SETUP COMPARE REGISTER
6234 7330 DCA GDREG2
6235 3144 TAD K7740
6236 1122 DCA RRA0
6237 3320 RDSTAT /SETUP SKIP TIMER
6240 4444 TAD K4000 /READ STATUS
6241 1104 SZA CLA /WAS DRIVE DONE?
6242 7650 JMP I+7 /YES
6243 5252 TAD K5000 /NO, DRIVE MUST BE BUSY
6244 1105 DCA GDREG2 /EXPECTED STATUS
6245 3144 TAD SIREG /GET STATUS READ
6246 1147 TAD K2000 /ADD IN FUDGE FACTOR
6247 1102 SZA CLA /WAS DRIVE BUSY
6250 7640 JMP SEKER2 /NO, ERROR
6251 5310 TAD K0200 /ENABLE SET SECOND DONE FLAG
6252 1015 TAD CMREG /ORIGINAL COMMAND
6253 1151 LDCMD /LOAD COMMAND
6254 4450 CLA CLL CML RTR /EXPECTED STATUS
6255 7332 DCA GDREG2 /READ STATUS
6256 3144 CHKSKP, RDSTAT /FLAG SET?
6257 4444 DSKSKP /NO
6260 4447 SKP /YES GOT IT!
6261 7410 JMP GOTSKP /DRIVE BUSY?
6262 5273 TAD K6000 /NO, ERROR
6263 1105 SZA CLA /ERROR, NO SKIP
6264 7640 JMP SEKER2 /SETUP EXPECTED STATUS
6265 5310 ISZ RNRWD4 /READ STATUS
6266 2364 JMP CHKSKP /FLAG SET?
6267 5257 ISZ PR30 /NO
6270 2420 JMP CHKSKP /ERROR, NO SKIP
6271 5257 JMP SEKER1 /SETUP EXPECTED STATUS
6272 5313 GOTSKP, CLA CLL CML RAR /READ STATUS
6273 7330 DCA GDREG2 /FLAG SET?
6274 3144 RDSTAT /NO
6275 4444 TAD K4000 /YES GOT IT!
6276 1104 SZA CLA /DRIVE BUSY?
6277 7640 JMP SEKER2 /NO, ERROR STATUS
6300 5310 TAD CMREG /GET LAST COMMAND
6301 1151

```

```

6302 0317 AND A7577 /MASK OUT
6303 4450 LDCMD /CLEAR STATUS
6304 3144 DCA GDREG2 /SETUP COMPARE REGISTER
6305 4444 RDSTAT /READ STATUS
6306 7650 SZA CLA /WAS STATUS 0000?
6307 2215 ISZ ONLY /UPDATE PC
6310 1170 SEKER2, TAD K5300 /SETUP TEXT POINTER
6311 3715 GOBAK, DCA I SAVPC /BACK TO TEST
6312 5615 JMP I ONLY /SKIP TEXT POINTER
6313 1166 SEKER1, TAD K0306 /EXIT
6314 5311 JMP GOBAK
/
6315 0000 SAVPC, 0
6316 0000 SAVIO, 0
6317 7577 A7577, 7577
/
/ROUTINE TO GET A RANDOM DISK ADDRESS
/
6320 0000 RRA0, 0
6321 3360 DCA SAVPOT /SAVE DISK NO. POINTER
6322 7101 CLL IAC
6323 1362 TAD RNRWD1
6324 1363 TAD RNRWD2
6325 7106 CLL RIL
6326 3362 DCA RNRWD1
6327 1363 TAD RNRWD2
6330 7012 RTR
6331 1362 TAD RNRWD1
6332 3363 DCA RNRWD2
6333 1363 TAD RNRWD2
6334 7420 SRL
6335 5341 JMP GOTADD /USE THIS AS DISK ADDRESS
6336 1172 TAD ENDRK /HAVE TO CHECK BOUNDARIES
6337 7200 CLA
6340 1363 TAD RNRWD2 /GET SAME
6341 3364 GOTADD, DCA RNRWD4 /SAVE WORD
6342 1361 TAD DSKSAV /GET POINTER
6343 1360 SAVPOT /ADD IN DRIVE NUMBER
6344 3360 DCA SAVPOT /MAKE ADDRESS
6345 1364 TAD RNRWD4 /GET WORD
6346 3760 DCA I SAVPOT /STORE IT
6347 1360 TAD SAVPOT
6350 1075 TAD K0004 /ADD IN FUDGE FACTOR
6351 3360 DCA SAVPOT /MAKE ADDRESS
6352 7004 RAL /GET THE LINK
6353 3760 DCA I SAVPOT /SAVE EXTENDED BIT
6354 1760 TAD I SAVPOT /GET IT
6355 7110 CLL RAR /SHIFT
6356 1344 TAD RNRWD4 /GET WORD
6357 5720 JMP I RRA0 /EXIT
/
6360 0000 SAVPOT, 0
6361 6365 DSKSAV, DSK04
6362 1234 RNRWD1, 1234
6363 2345 RNRWD2, 2345

```

```

6364 0000 RNWRD4, 0
6365 0000 DSK0A, 0
6366 0000 DSK1A, 0
6367 0000 DSK2A, 0
6370 0000 DSK3A, 0
6371 0000 DSKUR, 0
6372 0000 DSK1P, 0
6373 0000 DSK2P, 0
6374 0000 DSK3P, 0
/
6400 PAGE
/
/SUBROUTINE POP "NO ERRORS" AND SCOPE
/LOADPS, UPDATE UP COUNTER "REG1" ON EVERY ENTRY.
/
6400 0000 NERRO, 0
6401 2200 CLA CLL NERRO
6402 7300 TAD I NERRO /GET RSTART ADDRESS
6403 1600 DCA RSTR1 /STORE
6404 3175 DCA RSTR1 /GET SWITCH 4
6405 7604 LAS /MASK
6406 0015 AND K0200
6407 7640 SZA CLA /PROGRAM HALT
6410 7402 STPHLT, HLT /STOP HALT FROM SWR4#1
6411 7604 LAS /GET SWITCH 1
6412 7004 RAL
6413 7700 SZA CLA /IS IT SCOPE LOOP
6414 5217 JMP ,+3 /NO
6415 1600 TAD I NERRO /GET RETURN POINTER
6416 5631 JMP I NSCOPE /CHECK FOR WAIT AND RETURN
6417 1132 TAD REG0
6420 7640 SZA CLA /1 OR 4096 PASSES
6421 5224 JMP NEXTST /1 PASS PER TEST
6422 2133 ISZ REG1 /UPDATE UPCOUNTER
6423 5575 JMP I RSTR1 /BACK TO SAME TEST
6424 7301 NEXTST, CLA CLL IAC /ENABLE CLEAR CONTROL
6425 4453 CLRALL /CLEAR CONTROL
6426 2200 ISZ NERRO /UPDATE PC STORE
6427 2200 ISZ NERRO /UPDATE PC STORE
6430 5600 JMP I NERRO /TO NEXT SEQUENTIAL TEST
/
6431 8470 NSCOPE, SCOPE
/
/ROUTINE TO DO HALF BLOCK DATA CHECKS
/
6432 0000 HECHK, 0
6433 3144 DCA GDREG2 /SETUP FOR ERROR PRINTER
6434 1067 TAD BGNBUF /GET START OF BUFFER
6435 3154 DCA ADREG /FOR ERROR PRINTER
6436 1151 TAD CMREG
6437 0100 AND K0007
6440 7041 CIA
6441 1554 TAD I ADREG /COMPARE TO BUFFER WORD
6442 7650 SNA CLA /SAME ?
6443 5247 JMP ,+4 /YES

```

```

6444 1151 TAD CMREG
6445 0100 AND K0007 /NO
6446 5330 JMP HFERR /UPDATE ADDRESS
6447 2154 ISZ ADREG
6450 1554 TAD I ADREG
6451 7041 CIA /COMPARE TO DISK ADDRESS
6452 1152 TAD DAREG /SAME????
6453 7650 SNA CLA /YES
6454 5257 JMP ,+3
6455 1152 TAD DAREG /NO
6456 5330 JMP HFERR /UPDATE ADDRESS
6457 2154 ISZ ADREG
6460 7326 CLA CLL CML R1L
6461 1124 TAD K7600 /SETUP COUNTER FOR FIRST HALF
6462 3164 DCA DATCNT
6463 1554 HF1, TAD I ADREG
6464 7041 CIA
6465 1144 TAD GDREG2 /COMPARE TO GOOD VALUE
6466 7640 SZA CLA /WERE THEY THE SAME
6467 5331 JMP HFERR +1 /ERROR, DATA BREAK
6470 2154 ISZ ADREG /UPDATE ADDRESS POINTER
6471 1144 TAD GDREG2
6472 7040 CMA
6473 3144 DCA GDREG2 /NEXT WORD IS COMPLEMENT
6474 2164 ISZ DATCNT
6475 5263 JMP HF1 /MORE TO TEST IN FIRST HALF
6476 1124 TAD K7600 /SETUP COUNTER
6477 3164 DCA DATCNT /REST OF BUFFER SHOULD BE 0000
6500 3144 DCA GDREG2
6501 1554 HF2, TAD I ADREG /WAS IT 0
6502 7640 SZA CLA /ERROR
6503 5330 JMP HFERR
6504 2154 ISZ ADREG
6505 2164 ISZ DATCNT
6506 5301 JMP HF2 /MORE TO CHECK
6507 1554 TAD I ADREG /GET WORD IN BUFFER +1
6510 7041 CIA
6511 1101 TAD K1234 /WAS IT O.K.?
6512 7650 SNA CLA /YES
6513 5316 JMP ,+3
6514 1101 TAD K1234
6515 5330 JMP HFERR /ERROR, BUFFER +1
6516 7330 CLA CLL CML RAR /EXPECTED STATUS
6517 1144 DCA GDREG2 /SETUP COMPARE REGISTER
6520 1173 TAD SDFERR /GET CRC ERROR FLAG
6521 7640 SZA CLA /WAS IT SET
6522 5632 JMP I HFCHK /NO ERRORS
6523 7340 CLA CLL CMA /RESET CRC ERROR FLAG
6524 3173 DCA SDFERR /TEXT
6525 1170 TAD K0300
6526 3574 DCA I SAVPCT /SET UP POINTER
6527 7330 CLA CLL CML RAR /EXPECTED STATUS
6530 3144 HFERR, DCA GDREG2 /SETUP COMPARE
6531 1554 TAD I ADREG /GET BAD WORD
6532 3155 DCA DTRG /SAVE FOR PRINTER

```

```

6533 2232      ISZ   HFCHK
6534 5632      JMP I  HFCHK
/ROUTINE TO CHANGE PROGRAM DEVICE CODES
/
6535 7604      CHANG, LAS
6536 0126      AND   K0770
6537 3232      DCA   HFCHK           /SAVE DESIRED CODE
6540 1360      TAD   CCNTR1
6541 1200      DCA   NERR0
6542 1361      TAD   CHNPOT
6543 3357      DCA   CNGSAV
6544 1757      CHANG, TAD I CNGSAV           /GET ADDRESS POINTER
6545 3000      DCA   0           /SAVE IT
6546 1400      TAD I 0           /GET OLD IOT CODE
6547 0127      AND   K1007           /MASK
6550 1232      TAD   HFCHK           /ADD IN DESIRED
6551 3400      DCA I 0           /CHANGE CORE
6552 2357      ISZ   CNGSAV           /UPDATE ADDRESS POINTER
6553 2200      ISZ   NERR0           /UPDATE CHANGE COUNTER
6554 5344      JMP   CHANGR
6555 7402      CHNHDI,HLT           /DEVICE CODES CHANGED
6556 5355      JMP   .+1
/
6557 0000      CNGSAV, 0
6560 7745      CCNTR1, 7745
6561 6562      CHNPOT, CHNPOT +1
6562 5334      IOT1
6563 5341      IOT2
6564 5322      IOT3
6565 5314      IOT4
6566 5301      IOT5
6567 5330      IOT6
6570 5345      IOT7
6571 2676      IOT1A1
6572 2707      IOT2A1
6573 2675      IOT3A1
6574 2671      IOT4A1
6575 2700      IOT5A1
6576 2673      IOT6A1
6577 3026      IOT1A2
6600 3052      IOT2A2
6601 3025      IOT3A2
6602 3021      IOT4A2
6603 3030      IOT5A2
6604 3023      IOT6A2
6605 2018      T2810A
6606 2022      T2810b
6607 2027      T2810C
6610 2032      T2810D
6611 2073      T2910A
6612 2077      T2910b
6613 2104      T2910C
6614 2110      T2910D

```

```

6615 2324      ERTX1, TEXT "STATUS REGISTER ERROR"
6616 0124
6617 2523
6620 4022
6621 0507
6622 1123
6623 2405
6624 2240
6625 0522
6626 2217
6627 2200
6630 0317      ERTX2, TEXT "COMMAND REGISTER ERROR"
6631 1515
6632 0116
6633 0440
6634 2205
6635 0711
6636 2324
6637 0522
6640 4005
6641 2222
6642 1722
6643 0000
6644 0411      ERTX3, TEXT "DISK ADDRESS REGISTER ERROR"
6645 2313
6646 4001
6647 0404
6650 2205
6651 2323
6652 4022
6653 0507
6654 1123
6655 2405
6656 2240
6657 0522
6660 2217
6661 2200
6662 0411      ERTX4, TEXT "DISK DATA ERROR"
6663 2313
6664 4004
6665 0124
6666 0140
6667 0522
6670 2217
6671 2200
6672 0322      ERTX5, TEXT "CRC REGISTER ERROR"
6673 0340
6674 2205
6675 0711
6676 2324
6677 0522
6700 4005
6701 2222
6702 1722
6703 0000

```

```

/ PAL10 V142 20-DEC-73 13154 PAGE 1-72
6704 0401 ERTX6, TEXT "DATA REGISTER ERROR"
6705 2401
6706 4022
6707 0507
6710 1123
6711 2405
6712 2240
6713 0522
6714 2217
6715 2200
6716 0411 ERTX7, TEXT "DISK SKIP ERROR"
6717 2313
6720 4023
6721 1311
6722 2040
6723 0522
6724 2217
6725 2200
6726 0411 ERTX8, TEXT "DISK INTERRUPT ERROR"
6727 2313
6730 4011
6731 1624
6732 0522
6733 2225
6734 2024
6735 4005
6736 2222
6737 1722
6740 0000
/
6741 2213 TEXEND, TEXT "MKBE DRIVE CONTROL TEST PASS COMPLETE"
6742 7005
6743 4004
6744 2211
6745 2505
6746 4003
6747 1710
6750 2422
6751 1714
6752 4024
6753 0523
6754 2440
6755 2001
6756 2323
6757 4003
6760 1715
6761 2014
6762 0524
6763 0500
/
7000 *7000
/
7000 WKBUFF,
/
7000 H1TRK*,

```

```

/ PAL10 V142 20-DEC-73 13154 PAGE 1-73
7001 LOTRK*, +1
/
7377 ENDBUF*, +377
/
7400 SPCCHK*, +400
/
888

```


A7577	6317	DRST	6745	GOTSKP	6273	K0020	0012
A7776	4370	DSK0A	6365	GRNKER	4364	K0037	0117
ACCMF1	4442	DSK0B	6371	GRNKOK	4343	K0040	0013
ACCMF2	4443	DSK1A	6366	GRNKR1	4274	K0077	0111
ACPEG	0156	DSK1B	6372	GRNKP2	4330	K0100	0014
ADRELG	0154	DSK2A	6267	GRNKR3	4353	K0200	0015
AGAIN	5125	DSK2B	6373	GRONK	4265	K0207	5154
ALLBAX	4250	DSK3A	6370	GITREG	5527	K0212	6063
APA1	4752	DSK3B	6374	HAFCMK	4426	K0215	6062
APERR	4773	DSKAD1	4534	MEDHLT	4002	K0240	6065
APHLT1	4776	DSKIN	4421	MEDLST	5166	K0260	6064
APR1	4731	DSKOUT	4420	MEDTAD	5165	K0306	0166
AUTO1B	0010	DSKP	6741	MFCHK	6432	K0400	0016
AUTPR0	4710	DSKPD1	4535	MFERR	6530	K0770	0128
BGN	0200	DSKSAV	6361	MFR1	6463	K1000	0017
BGNBUF	0067	DSKSKP	4447	MFR2	6501	K1234	0101
CAPEC	0153	DTERR	5743	MITRK	7000	K2000	0102
CCNTR1	6560	DIREC	0155	MOXEMA	0157	K2525	0112
CHAMP	6535	ENDBUF	7377	MRDEPR	5652	K3000	0103
CHARGR	6544	ENDHLT	4072	INHBIT	5157	K3740	6150
CHEC	6232	ENDTRN	0172	INTADD	5215	K4000	0104
CHKEX	4434	ENDTST	4040	INTRQ	0034	K4100	6147
CHKSKP	6257	ERHLT1	5217	IGNMAT	4441	K5000	0114
CHNHLT	6555	ERHLT2	5343	IGNMT	5200	K5252	0113
CHNPOT	6561	ERHLT3	5324	IGT1	5334	K5300	0170
CLDN	5340	ERHLT4	5316	IGT1A1	2676	K5373	0167
CLRALL	4453	ERHLT5	5303	IGT1A2	3026	K5403	0125
CMREG	0151	ERHLT6	5332	IGT2	5341	K6000	0105
CMGSAV	6557	ERHLT7	5347	IGT2A1	2707	K6304	0171
COMP1	5221	ERHLT9	5142	IGT2A2	3052	K7000	0106
COMP2	5231	ERRA1	5017	IGT3	5322	K7007	0127
CRERR	5245	ERR0	5000	IGT3A1	2675	K7156	3750
CRFP	4462	ERROR	4440	IGT3A2	3025	K7400	0123
CRREG1	0145	ERTX1	6615	IDT4	5314	K7501	5655
CRREG2	0146	ERTX2	6630	IDT4A1	2671	K7577	5525
CRWRD1	0162	ERTX3	6644	IDT4A2	3021	K7600	0124
CRWRD2	0163	ERTX4	6662	IDT5	5301	K7700	0110
CYL450	0065	ERTX5	6672	IDT5A1	2700	K7707	4707
DAPEG	0152	ERTX6	6704	IDT5A2	3030	K7740	0122
DATCNT	0164	ERTX7	6716	IDT6	5330	K7760	0107
DBREG	0150	ERTX8	6726	IDT6A1	2673	K7771	0115
DCLR	6742	ESCOPE	5155	IDT6A2	3023	KCDF	0120
DIN	4536	EXIT	6145	IDT7	5345	KILBUF	4431
DISKG	5600	FIGURE	5656	K0001	0072	KLBUF	5435
DISKGO	4425	FIGUR	4427	K0002	0073	KRMF	0121
DLAG	6743	FILBUF	4430	K0003	0074	LDAD	5317
DLCA	6744	FLBUF	5447	K0004	0075	LDADD	4452
DLDC	6746	FRDCT	6066	K0005	0076	LDCA	5307
DMAN	6747	GDREG1	0143	K0006	0077	LDCM	5325
DNT	5553	GDREG2	0144	K0007	0100	LDCMD	4450
DRIVNO	0070	GOBAK	6311	K0010	0011	LDCUR	4451
DRIVSV	0071	GOTADD	6341	K0017	0116	LDMAN	4455

LDMN	5344	ROCM	5412	T12E	0705	T2810C	2027
LUTHK	7001	R0CHD	4445	T12R	0670	T2810D	2032
LFDAT	5458	RDCR	6000	T13E	0756	T280K	2045
LPFIG	5706	RDCRC	4454	T13P	0720	T28R	2006
M12	0130	RDST	5300	T14KE	1060	T28T	2052
M4	0131	R0STAT	4444	T14R	1004	T29E	2124
MANPPO	4101	RECAL	4424	T14SE	1054	T2910A	2073
MANUAL	4600	REDBAK	4517	T15E	1077	T2910B	2077
MPEPR	4157	REG0	0132	T15T	1101	T2910C	2104
MPHLT1	4172	REG1	0133	T16E	1117	T2910D	2110
MPHLT2	4162	RESEK	4003	T16T	1121	T290K	2121
MPR1	4173	RESTOR	6200	T17E	1160	T29R	2064
NDIN	4561	RESTR	0175	T17S	1124	T29T	2126
NERRO	6400	RETRN	5632	T17I	1162	T2E	0313
NERRDR	4437	RETRN2	5156	T18E	1235	T30E	2167
NEXDOK	4073	RNAD	6320	T18S	1202	T30R	2131
NEXTST	6424	RNRD1	6362	T18T	1237	T30T	2171
NOCLR	5522	RNRD2	6361	T19E	1265	T31E	2245
NOTOON	4212	RNRD4	6364	T19OK	1264	T31R	2202
NOTEX	5146	SAMDSK	4064	T19T	1267	T31T	2247
NSCOPE	6431	SAVDAT	0165	T1E	0266	T32E	2360
NTRC	5101	SAVPC	6315	T20E	1315	T32R1	2257
NTGB	5064	SAVPC1	0174	T20OK	1314	T32R2	2300
NTGNA	4335	SAVPOT	6360	T20T	1317	T32R3	2317
NTSEK	4647	SAVIO	6316	T21E	1346	T32R4	2341
OCTEL	4460	SAVTRK	5654	T21OK	1345	T32I	2362
ONLY	6215	SBCNT1	0134	T21T	1350	T33E	2507
OVRDEK	4530	SCOPE	5470	T22E	1442	T33R1	2404
OVRDOK	4442	SDKP	5333	T22R1	1404	T33R2	2431
OVRERR	4261	SEK	4423	T22R2	1423	T33R3	2450
OVRLAP	4200	SEKER1	6313	T22T	1444	T33R4	2467
OVROK	4240	SEKER2	6310	T23E	1506	T33T	2511
OVR1	4203	SKPERH	5634	T23R1	1451	T34E	2544
OVR2	4207	SKPWAT	4432	T23R2	1470	T34T	2546
OVR3	4225	SKWAT	5261	T23T	1510	T35E	2644
OVRD1	4403	SOFERR	0173	T24E	1554	T36E	2725
OVRD2	4407	STAERR	5636	T24S	1513	T36R	2664
OVRD3	4425	STCON	0161	T24T	1556	T36T	2727
OVRRED	4400	STPCHK	7400	T25E	1642	T37A	3051
PCNTR1	5163	STPHLT	6410	T25S	1602	T37E	3075
PCNTR2	5164	STRAUT	5110	T25T	1644	T37R	3013
PDLEPR	4431	STREG	0147	T26E	1714	T37T	3077
PRINT	6151	SWSEK	4000	T26R1	1651	T38DE	3151
PRN	6111	TOE	0253	T26R2	1673	T38E	3140
PRINTER	4457	T10E	0543	T26T	1716	T38OK	3150
PRFLD	0222	T10R	0514	T27E	1765	T38R	3110
RANADD	4422	T10T	0545	T27R1	1723	T38T	3153
RAPCNT	0160	T11E	0637	T27R2	1745	T39DE	3250
RDAD	5350	T11R1	0602	T27T	1767	T39E	3237
RDADD	4446	T11R2	0612	T28E	2050	T39OK	3247
RDRF	5400	T11R3	0616	T2810A	2016	T39R	3207
RDBUF	4456	T11T	0641	T2810B	2022	T39T	3252

T3E	0346	TCNTR6	0142	TST35	2600	XRDAD	0046
T3T	0350	TEXAD	5770	TST36	2647	XRDBF	0056
T40E	3276	TEXCA	5766	TST37	3000	XHDCM	0045
T40R	3255	TEXCM	5762	TST38	3100	XRDCE	0054
T40S	3281	TEXCR	5758	TST39	3200	XRDST	0044
T40T	3300	TEXDA	5764	TST4	0351	XREG	5162
T41E	3370	TEXDB	5760	TST40	3253	XRESTR	0024
T41R	3303	TEXDT	5772	TST41	3301	XRNAD	0022
T41S	3317	TEXEND	6741	TST42	3400	XGKPF	0047
T41T	3372	TEXGD	5752	TST43	3452	XSKWAI	0032
T42E	3447	TEXPC	5750	TST44	3515	XTEXT	9161
T42R	3402	TEXST	5756	TST45	3600	XTOCT	0061
T42S	3406	THSFLL	0035	TST5	0360	XWTIS2	0033
T42T	3451	TIMSTP	3536	TST6	0400		
T43E	3512	THANE	4703	TST7	0415		
T43R1	3454	THANDK	4702	TST8	0431		
T43R2	3461	THAKS	4624	TST9	0457		
T43T	3514	THAMT	4705	TSTSEK	4060		
T44E	3554	THPROI	4161	THOCT	4461		
T44DK	3564	TOCT	6036	TYPE	4436		
T44R	3524	TOTST	5526	UPONE	6053		
T44T	3567	TGWRDT	4532	WATIS2	4433		
T45A1	3622	THK212	0066	WRKBUF	7000		
T45A2	3676	TST0	0235	WTISZ	5247		
T45E	3743	TST1	0256	XCLDR	0053		
T45R1	3612	TST10	0512	XCOMP1	0042		
T45R2	3626	TST11	0600	XCOMP2	0043		
T45R3	3667	TST12	0656	XCRLF	0062		
T45R4	3701	TST13	0710	XDIH	0021		
T45SC	3604	TST14	1001	XDISKG	0025		
T45T	3745	TST15	1064	XDOGT	0020		
T4E	0355	TST16	1102	XERR0	0040		
T4T	0357	TST17	1122	XFGURE	0027		
T5E	0367	TST18	1200	XFLBUF	0030		
T5T	0371	TST19	1240	XPROCI	0060		
T6E	0412	TST2	0271	XGRONK	4164		
T6T	0414	TST20	1270	XGTREG	5160		
T7E	0428	TST21	1320	XHFCMK	0026		
T7T	0430	TST22	1400	XHTRK	0064		
T8E	0454	TST23	1445	XIOWNT	0041		
T8R	0433	TST24	1511	XKLBUF	0031		
T9T	0456	TST25	1600	XLAP	4165		
T9E	0507	TST26	1645	XLDAD	0052		
T9OK	0506	TST27	1717	XLDCA	0051		
T9P	0464	TST28	1773	XLDGM	0050		
T9T	0511	TST29	2053	XLDWN	0055		
TAPROT	4775	TST1	0317	XLOTRK	0063		
TCNTR1	0135	TST30	2127	XNERR0	0037		
TCNTR2	0136	TST31	2200	XONLY	0023		
TCNTR3	0137	TST32	2250	XOVHRD	4166		
TCNTR4	0140	TST33	2400	XPRINT	0036		
TCNTR5	0141	TST34	2512	XPRN	0057		

ERRORS DETECTED: 0
 LINKS GENERATED: 7
 RUN-TIME: 23 SECONDS
 3K CORE USED

