

8

MATE 9 EPT 4 - 90 T

TITLE
 ASSEMBLY, PCB DATA AND INTERFACE

DWG NO.
 200263-000

REV
 H

SHEET 2 OF 6

MODEL 270 BASIC BOARD

PERSCI, INC.

ITEM NO.	DRAWING TITLE	DWG NO.	QTY	REMARKS
1	BOARD, PROCESSED	200262	1	REV C
2				
3	BRACKET, DATA BD	200171	1	REV B
4	INSULATOR, DATA BD	200174	1	REV A
5				
6				
7				
8				
9				
10				
11	IC LM311N	150600	3	U18, 22, 61
12	IC MC1406L	150601	1	U55
13	IC MC1458C-P1	150602	2	U40, 51
14	IC 7400	150603	5	U15, 28, 53, 57, 60
15	IC 7404	150604	5	U20, 30, 38, 41, 4r
16	IC 7408	150605	4	U26, 29, 45, 50
17	IC 7432	150608	4	U19, 54, 56, 58
18	IC 7474	150609	6	U14, 24, 39, 46, 47, 52
19	IC 7486	150611	1	U21
20	IC 74123	150612	4	U10, 12, 25, 44
21	IC 74193	150614	2	U42, 43
22	IC 75451	150616	1	U17
23	IC 75452	150617	2	U31, 36
24	IC 75453	150618	9	U2, 3, 4, 5, 6, 7, 8, 23, 59
25	IC 72733	150619	2	U33, 35
26	IC 7416	150621	2	U13, 48
27	IC 7406	150622	1	U37
28	IC SN72306P	150646	2	U34, 32
29				
30	RESISTOR NETWORK 4.7K	150050	1	U9
31	RESISTOR NETWORK 220/330	150051	1	U1
32				
33				

TITLE ASSEMBLY, PCB DATA AND INTERFACE	DWG NO. 200263-000	REV H	SHEET 3 OF 6
---	-----------------------	----------	--------------

MODEL 270 BASIC BOARD	PERSCI, INC.		
-----------------------	---------------------	--	--

DWG NO. 200263-C

REV H

ITEM NO.	DRAWING TITLE	DWG NO.	QTY	REMARKS
34	TRANSISTOR 2N4400	150200	5	Q2,26,27,28,31
35	TRANSISTOR 2N4402	150201	25	Q3,4,5,6,7,8,9,10, 13,16,17,18,19,20, 21,22,23,24,25, 29,30,32,33,34,35
36	TRANSISTOR 2N5460	150202	4	Q11,12,14,15
37	TRANSISTOR 2N2913	150203	1	Q1
38	TRANSISTOR 2N706A	150207	4	Q36,37,38,39
39				
40				
41				
42	DIODE 1N3064	150300	16	CR3,4,5,6,7,8, 9,10,11,12,13,14, 15,16,17,18
43	DIODE, ZENER 1N752A	150302	1	VR1
44	DIODE, ZENER 1N759A	150313	2	VR2,4
45	DIODE, ZENER 1N751A	150311	1	VR3
46	INDUCTOR 200UH	150094	1	L1
47	CAPACITOR, MICA .001UF	150102-102	2	C58,59
48	CAPACITOR, MICA 220pf	150102-221	1	C14
49	CAPACITOR, MICA 100pf	150102-101	3	C1,50,51
50	CAPACITOR, MICA 510pf	150102-511	4	C21,26,46,49
51	CAPACITOR, MYLAR .001UF	150101-102	2	C3,4
52	CAPACITOR, CERAMIC .01UF	150103-103	15	C7,11,18,20,24,25, 28,30,34,37,38,43, 45,52,56
53	CAPACITOR, TANTL 10% 0.1UF	150100-104	3	C35,42,44
54	CAPACITOR, TANTL 10% 1UF	150100-105	23	C2,5,6,8,9,10,12, 13,15,16,17,19, 22, 23,27,29,33,39,47, 53,54,55,57

41

TITLE ASSEMBLY, PCB DATA AND INTERFACE	DWG NO. 200263-000	REV H	SHEET 4 OF 6
---	-----------------------	----------	--------------

MODEL 270 BASIC BOARD	PERSCI, INC.
-----------------------	---------------------

ITEM NO.	DRAWING TITLE	DWG NO.	QTY	REMARKS
55	CAPACITOR, TANTL 22UF	150100-226	1	- C48
56				
57				
58				
59	RESISTOR, VARIABLE 2K	150003-202	1	R154
60				
61	RESISTOR 1/2 W., 5% 10	150002-100	2	R121,126
62	RESISTOR 1/2 W., 5% 47	150002-470	2	R69,70
63	RESISTOR 1/2 W., 5% 68	150002-680	4	R104,105,106,107
64	RESISTOR 1/2 W., 5% 1K	150002-102	1	R169
65	RESISTOR, 1/2 W., 1% 1.50K	150001-1501	1	R81
66	RESISTOR 1/2 W., 1% 332	150001-3320	2	R13,14
67	RESISTOR 1/2 W., 1% 1.78K	150001-1781	1	R138
68	RESISTOR 1/2 W., 1% 3.01K	150001-3011	1	R78
69	RESISTOR 1/2 W., 1% 10K	150001-1002	5	R108,109,147,148,149
70	RESISTOR 1/2 W., 1% 24.9K	150001-2492	1	R152
71	RESISTOR 1/2 W., 1% 30.1K	150001-3012	1	R146
72	RESISTOR 1/2 W., 1% 4.64K	150001-4641	2	R86,87
73				
74	RESISTOR 1/2 W., 5% 10	150000-100	13	R3,10, 12,18,19, 33,34,37,38,41, 42,56,77
75	RESISTOR 1/2 W., 5% 47	150000-470	2	R26,27
76	RESISTOR 1/2 W., 5% 100	150000-101	13	R23,29,35,36,39, 40,82,83,84,85, 101,103,128
77				
78	RESISTOR 1/2 W., 5% 220	150000-221	7	R5,7,49,53,58, 120,125
79	RESISTOR 1/2 W., 5% 330	150000-331	13	R6,8,9,15,16,17, 59,65,66,67,68, 119,124

TITLE
ASSEMBLY, PCB DATA AND INTERFACE

DWG NO.
200263-000

REV
H

SHEET 5 OF 6

MODEL 270 BASIC BOARD

PERSCI, INC.

ITEM NO.	DRAWING TITLE	DWG NO.	QTY	REMARKS
80	RESISTOR 1/4 W., 5% 510	150000-511	1	R111
81	RESISTOR 1/4 W., 5% 1K	150000-102	24	R1,2,48,52,64,71, 72,73,74,89,92,95,98, 112,114,117,118,122, 123,132,134,158,166, 170
82	RESISTOR 1/4 W., 5% 2K	150000-202	10	R22,24,28,30, 110,115,116,133, 137,139
83	RESISTOR 1/4 W., 5% 680	150000-681	1	R25
84	RESISTOR 1/4 W., 5% 3.9K	150000-392	4	R4,45,57,135
85	RESISTOR 1/4 W., 5% 4.7K	150000-472	11	R60,61,175, 130,136,155,159, 160,161,167,168
86	RESISTOR 1/4 W., 5% 5.1K	150000-512	1	R153
87	RESISTOR 1/4 W., 5% 6.8K	150000-682	5	R46,47,50,51,62
88	RESISTOR 1/4 W., 5% 10K	150000-103	23	R20,21,31,32,43,44, 54,55,79,131,151,156, 157,162,163,164,165, 171,172,173,174,90,96
89	RESISTOR 1/4 W., 5% 15K	150000-153	2	R100, 102
90	RESISTOR 1/4 W., 5% 18K	150000-183	1	R63
91	RESISTOR 1/4 W., 5% 20K	150000-203	2	R141,144
92	RESISTOR 1/4 W., 5% 22K	150000-223	3	R75,76,80
93	RESISTOR 1/4 W., 5% 30K	150000-303	3	R93,99,140
94				
95	RESISTOR 1/4 W., 5% 39K	150000-393	2	R143,145
96	RESISTOR 1/4 W., 5% 47K	150000-473	3	R150,176,177
97	RESISTOR 1/4 W., 5% 220K	150000-224	2	R91,97
98	RESISTOR 1/4 W., 5% 100K	150000-104	2	R113,129
99	RESISTOR 1/4 W., 5% 240K	150000-244	1	R142
100	RESISTOR 1/4 W., 5% 1MEG	150000-105	1	R127

